

⚠ WARNINGS AND CAUTIONS

- Make sure **POWER** is **COMPLETELY OFF** at the fuse box
- Have your fixture installed by a qualified licensed electrician
- Prepare everything in a clear area
- Wear gloves at all times during this installation
- Read instructions carefully before you start assembly
- Keep this installation sheet for future reference

Please Note:

- This Alora LED fixture comes with pre-wired LED module(s)
- Unless instructed, Do Not touch any part of the LED module(s) as any unnecessary contact with the module could cause permanent damage
- For dimming, an ELV (Electronic Low Voltage) or TRIAC type of dimmer is required
- 120-277V input
- This fixture requires at least 2 certified personnel to install

NOTICE

- The important safeguards and instructions outlined in this sheet cannot cover all possible conditions and situations that may occur. It must be understood that caution and certain care factors must be followed. These instructions are provided for your safety and we highly recommend that a licensed, trained electrician install this unit.
- This fixture is designed to be mounted on a correctly installed standard round or octagon box OR through a wiring box with a plaster frame. The box must be securely mounted to the structure of the building. The crossbar and hardware supplied should be used, directly mounting the fixture to the outlet box may make it impossible to correctly align the fixture.

ASSEMBLY INSTRUCTIONS

Step 1

Remove fixture from its original package.

Step 2

Separate mounting plate (1c) from canopy (2a) by removing decorative nut (2c).

Step 3

Attach mounting plate (1c) to electrical junction box (1a) using junction box screws provided (1e) in hardware package.

Step 4

Place fixture on clean surface. Determine hanging height of fixture by securing rods (2d) to rod connectors (2e), canopy (2a) and fixture ring (5a) after feeding fixture wires (LED+ and LED-) through rods.

Step 5

Make proper electrical connections between LED and DC driver, LED- Negative, LED+ Positive using quick connector provided (See Illustration 1 and refer to diagram on driver).

Step 6

Carefully bring canopy (2a) up to ceiling, after fully assemble the fixture, by holding the fixture ring (5a). **DO NOT USE** shade support (3a) as a handle.

Step 7

Make proper electrical connections (**black to hot "L", white to neutral "N", ground to "GND"**) with wire nuts (1b) provided in hardware package and place driver (4a) in canopy (2a).

Step 8

Align and insert mounting plate RTN (1d) through hole on canopy (2a), secure with decorative nut (2c).

Step 9

Shade support (3a) and let the shade (3b) rest on shade support (3a) (See Illustration 2). Attach glass (3c) to LED module (3d) by threading clockwise to secure (See Illustration 3). Match number in shade (3b) to number on metal frame.

You are now ready to enjoy your fixture.

