

## **C-GES-18-S**

10/100/1000Base-TX(RJ-45) to 8x Open SFP Switch

### **Features**

- Supports 10/100/1000Base-T, 1000Base-X protocol
- Flow control for full duplex and half duplex
- Supports Fiber Port Trunking, Increasing Fiber Channel Bandwidth and Supply Fiber Channel Redundancy
- Flow control for full duplex and half duplex
- Supports Ports Based VLANs and TAG Based VLANs
- In conformity to safety code of FCC and CE MARK
- Supports up to 10k byte JUMBO frame

### **Product Description**

This is an unmanaged one port RJ-45 to eight port SFP switch. It is designed with a switch controller and buffer memory that connects two types of media. This switch supports 10/100/1000 Base-T and 1000Base-X protocol, and operates under full duplex mode or half duplex mode. This can extend your fiber footprint or convert fiber runs from short multi-mode links to extended single-mode links. Our media converters and switches are 100% compliant for all of our networking needs. Now you have a cost effective solution to your network upgrade needs. With our certification test program, we can guarantee your product will work right the first time.

## Technical Parameters

Parameter	Min	Typ	Max	Units
Standard Protocol	IEEE802.3, IEEE802.3u, IEEE802.3x			
Compatible OEM	Industry Standard			
Connector Types	RJ45 & SFP			
Connector 1 Number of Ports	1			
Connector 2 Number of Ports	8			
Data Rate			1000	Mbps
Operating Wavelength	830 1280 1480	850 1310 1550	860 1335 1580	nm
Fiber Interface	multi-mode: 50/125μm, 62.5/125μm or 100/140μm single-mode: 8.3/125μm, 8.7/125μm, 9/125μm or 10/125μm			
RJ45 Port	UTP-100-ohm Cat.5 cable			
Max Segment Length (UTP)	0		120	m
Power Supply	AC-DC Power Adaptor (INPUT AC110-265V 50~60Hz, OUTPUT DC +5V/2A)			

## Reccomended Operating Conditions

Parameter	Min	Typ	Max	Units
Operating Temperature	0 -20		70(Business Level) 85(Industry Level)	°C
Storage Temperature	-40		85	°C
Humidity	5%~90% (Non-condensing)			
EMI and Safety	CE, FCC Class A			

### LED Indicator Lamp Explanation

LED	Function	Status	Description
<b>PWR</b>	Power LED	ON	Power is ON
		OFF	Power is fail
<b>FX</b>	Fiber port signal detect LED	ON	Optical signal detected
		OFF	No laser input
<b>FX-LINK/ACT</b>	Fiber port link/action status LED	ON	Fiber link is ok
		Blink	Data is been received or transmitted
		OFF	Fiber link is fail
<b>1000M</b>	UTP port speed LED	ON	1000M speed
		OFF	10M speed
<b>TX-LINK/ACT</b>	UTP port link/action status LED	ON	Link is ok
		Blink	Data is been received or transmitted
<b>FDX/COL</b>	UTP port duplex LED	ON	Full Duplex