

## MINIATURE TOGGLES




Fig. 1




Fig. 2




Fig. 3

### Miniature Toggles with Printed Circuit Board Terminals

Retail Part No.	Figure No.	Circuit Function		Poles/Throws	125VAC/28VDC	AMPS 250VAC	Actuator Style	Actuator Material	Bushing Length	Mounting Hole	Terminal Type	Hardware	Spec. Drawing Page No.	
35-087	1	On		On	SPDT	5	2	Bat	BCP	0.350"	0.250"	PCB	2 N, LR, LW	H-5 A
35-079	2	On		On	DPDT	5	2	Bat	BCP	0.350"	0.250"	PCB	2 N, LR, LW	H-5 B
35-083	2	On	Off	(On)	DPDT	5	2	Bat	BCP	0.350"	0.250"	PCB	2 N, LR, LW	H-5 B
35-085	2	(On)	Off	(On)	DPDT	5	2	Bat	BCP	0.350"	0.250"	PCB	2 N, LR, LW	H-5 B

### Miniature Toggles with Printed Circuit Board with Integral Bracket Terminals

Retail Part No.	Figure No.	Circuit Function		Poles/Throws	125VAC/28VDC	AMPS 250VAC	Actuator Style	Actuator Material	Bushing Length	Mounting Hole	Terminal Type	Spec. Drawing Page No.	
35-093	3	On	Off	(On)	SPDT	5	2	Bat	BCP	0.350"	0.250"	PCB†	H-5 C

Notes: (On) = Momentary On  
BCP = Brass Chrome Plate

LW = Lock Washer  
N = Nut(s)

LR = Lock Ring  
PCB = Printed Circuit Board  
PCB† = Printed Circuit Board with Integral Bracket

All quantities are single unless otherwise noted.