

# WATER BOILER RELIEF VALVE SELECTIONS

## Table of Contents

---

|                                     |         |
|-------------------------------------|---------|
| AB Series 90 - 300                  | Page 2  |
| <i>CL</i> /CLM Series 75 - 180      | Page 3  |
| <i>CL</i> /CLM Series 210 - 300     | Page 4  |
| <i>D Series 350 - 650</i>           | Page 5  |
| DR Series 350 - 850                 | Page 6  |
| F Series 350 - 850                  | Page 7  |
| <i>HECL</i> /HECLM Series 75 - 180  | Page 8  |
| <i>HECL</i> /HECLM Series 210 - 300 | Page 9  |
| <i>HED Series 305 - 650</i>         | Page 10 |
| K Series 250 - 450                  | Page 11 |
| K Series 500 - 650                  | Page 12 |
| RV Series 200 - 400                 | Page 13 |
| RV Series 450 - 800                 | Page 14 |
| RW Series 850 - 2100                | Page 15 |

---

*Obsolete Models*

# RELIEF VALVE SELECTIONS

| AB SERIES WATER BOILERS |              |                    |        |       |      |         |                      |        |
|-------------------------|--------------|--------------------|--------|-------|------|---------|----------------------|--------|
| H.S.                    | Boiler Model | Pressure<br>(Psig) | Part # | Model | Qty. | Size    | Actual Cap.<br>(MBH) | Vendor |
| 113                     | AB90-W       |                    |        |       |      |         |                      |        |
|                         |              | 30#                | 26120  | 740   | 1    | 1¼x1½   | 2105                 | Watts  |
|                         |              | 45#                | 26113  | 740   | 1    | 1x1¼    | 1750                 | Watts  |
|                         |              | 50#                | 26124  | 740   | 1    | 1¼x1½   | 3075                 | Watts  |
|                         |              | 60#                | 26107  | 740   | 1    | 3/4x1   | 1566                 | Watts  |
|                         |              | 75#                | 26117  | 740   | 1    | 1x1¼    | 2649                 | Watts  |
|                         |              | 125#               | 26158  | 174A  | 1    | 3/4x3/4 | 2070                 | Watts  |
|                         |              | 150#               | 26159  | 174A  | 1    | 3/4x3/4 | 2445                 | Watts  |
| 148                     | AB120-W      |                    |        |       |      |         |                      |        |
|                         |              | 30#                | 26120  | 740   | 1    | 1¼x1½   | 2105                 | Watts  |
|                         |              | 45#                | 26113  | 740   | 1    | 1x1¼    | 1750                 | Watts  |
|                         |              | 50#                | 26124  | 740   | 1    | 1¼x1½   | 3075                 | Watts  |
|                         |              | 60#                | 26107  | 740   | 1    | 3/4x1   | 1566                 | Watts  |
|                         |              | 75#                | 26117  | 740   | 1    | 1x1¼    | 2649                 | Watts  |
|                         |              | 125#               | 26158  | 174A  | 1    | 3/4x3/4 | 2070                 | Watts  |
|                         |              | 150#               | 26159  | 174A  | 1    | 3/4x3/4 | 2445                 | Watts  |
| 184                     | AB150-W      |                    |        |       |      |         |                      |        |
|                         |              | 30#                | 26120  | 740   | 1    | 1¼x1½   | 2105                 | Watts  |
|                         |              | 45#                | 26123  | 740   | 1    | 1¼x1½   | 2830                 | Watts  |
|                         |              | 50#                | 26124  | 740   | 1    | 1¼x1½   | 3075                 | Watts  |
|                         |              | 60#                | 26126  | 740   | 1    | 1¼x1½   | 3560                 | Watts  |
|                         |              | 75#                | 26117  | 740   | 1    | 1x1¼    | 2649                 | Watts  |
|                         |              | 125#               | 26158  | 174A  | 1    | 3/4x3/4 | 2070                 | Watts  |
|                         |              | 150#               | 26159  | 174A  | 1    | 3/4x3/4 | 2445                 | Watts  |
| 244                     | AB200-W      |                    |        |       |      |         |                      |        |
|                         |              | 30#                | 26129  | 740   | 1    | 1½x2    | 2900                 | Watts  |
|                         |              | 45#                | 26123  | 740   | 1    | 1¼x1½   | 2830                 | Watts  |
|                         |              | 50#                | 26124  | 740   | 1    | 1¼x1½   | 3075                 | Watts  |
|                         |              | 60#                | 26126  | 740   | 1    | 1¼x1½   | 3560                 | Watts  |
|                         |              | 75#                | 26117  | 740   | 1    | 1x1¼    | 2649                 | Watts  |
|                         |              | 125#               | 26172  | 174A  | 1    | 1x1     | 3215                 | Watts  |
|                         |              | 150#               | 26159  | 174A  | 1    | 3/4x3/4 | 2445                 | Watts  |
| 303                     | AB250-W      |                    |        |       |      |         |                      |        |
|                         |              | 30#                | 26138  | 740   | 1    | 2x2½    | 5250                 | Watts  |
|                         |              | 45#                | 26132  | 740   | 1    | 1½x2    | 3903                 | Watts  |
|                         |              | 50#                | 26133  | 740   | 1    | 1½x2    | 4237                 | Watts  |
|                         |              | 60#                | 26126  | 740   | 1    | 1¼x1½   | 3560                 | Watts  |
|                         |              | 75#                | 26127  | 740   | 1    | 1¼x1½   | 4285                 | Watts  |
|                         |              | 125#               | 26172  | 174A  | 1    | 1x1     | 3215                 | Watts  |
|                         |              | 150#               | 26173  | 174A  | 1    | 1x1     | 3795                 | Watts  |
| 350                     | AB300-W      |                    |        |       |      |         |                      |        |
|                         |              | 30#                | 26138  | 740   | 1    | 2x2½    | 5250                 | Watts  |
|                         |              | 45#                | 26132  | 740   | 1    | 1½x2    | 3903                 | Watts  |
|                         |              | 50#                | 26133  | 740   | 1    | 1½x2    | 4237                 | Watts  |
|                         |              | 60#                | 26126  | 740   | 1    | 1¼x1½   | 3560                 | Watts  |
|                         |              | 75#                | 26127  | 740   | 1    | 1¼x1½   | 4285                 | Watts  |
|                         |              | 125#               | 26186  | 174A  | 1    | 1¼x1¼   | 5370                 | Watts  |
|                         |              | 150#               | 26173  | 174A  | 1    | 1x1     | 3795                 | Watts  |

# RELIEF VALVE SELECTIONS

| CL /CLM SERIES WATER BOILERS |              |                    |        |           |      |       |                      |          |
|------------------------------|--------------|--------------------|--------|-----------|------|-------|----------------------|----------|
| H.S.                         | Boiler Model | Pressure<br>(Psig) | Part # | Model     | Qty. | Size  | Actual Cap.<br>(MBH) | Vendor   |
| 90                           | CL75-W       |                    |        |           |      |       |                      |          |
|                              |              | 30#                | 26232  | 10-214-05 | 1    | 1x1   | 1000                 | ConBraCo |
|                              |              | 45#                | 26113  | 740       | 1    | 1x1¼  | 1750                 | Watts    |
|                              |              | 50#                | 26124  | 740       | 1    | 1¼x1½ | 3075                 | Watts    |
|                              |              | 60#                | 26107  | 740       | 1    | ¾x1   | 1566                 | Watts    |
|                              |              | 75#                | 26117  | 740       | 1    | 1x1¼  | 2649                 | Watts    |
|                              |              | 125#               | 26158  | 174A      | 1    | ¾x¾   | 2070                 | Watts    |
|                              |              | 150#               | 26159  | 174A      | 1    | ¾x¾   | 2445                 | Watts    |
| 110                          | CL /CLM90-W  |                    |        |           |      |       |                      |          |
|                              |              | 30#                | 26120  | 740       | 1    | 1¼x1½ | 2105                 | Watts    |
|                              |              | 45#                | 26113  | 740       | 1    | 1x1¼  | 1750                 | Watts    |
|                              |              | 50#                | 26124  | 740       | 1    | 1¼x1½ | 3075                 | Watts    |
|                              |              | 60#                | 26107  | 740       | 1    | ¾x1   | 1566                 | Watts    |
|                              |              | 75#                | 26117  | 740       | 1    | 1x1¼  | 2649                 | Watts    |
|                              |              | 125#               | 26158  | 174A      | 1    | ¾x¾   | 2070                 | Watts    |
|                              |              | 150#               | 26159  | 174A      | 1    | ¾x¾   | 2445                 | Watts    |
| 145                          | CL /CLM120-W |                    |        |           |      |       |                      |          |
|                              |              | 30#                | 26120  | 740       | 1    | 1¼x1½ | 2105                 | Watts    |
|                              |              | 45#                | 26113  | 740       | 1    | 1x1¼  | 1750                 | Watts    |
|                              |              | 50#                | 26124  | 740       | 1    | 1¼x1½ | 3075                 | Watts    |
|                              |              | 60#                | 26107  | 740       | 1    | ¾x1   | 1566                 | Watts    |
|                              |              | 75#                | 26117  | 740       | 1    | 1x1¼  | 2649                 | Watts    |
|                              |              | 125#               | 26158  | 174A      | 1    | ¾x¾   | 2070                 | Watts    |
|                              |              | 150#               | 26159  | 174A      | 1    | ¾x¾   | 2445                 | Watts    |
| 180                          | CL /CLM150-W |                    |        |           |      |       |                      |          |
|                              |              | 30#                | 26120  | 740       | 1    | 1¼x1½ | 2105                 | Watts    |
|                              |              | 45#                | 26123  | 740       | 1    | 1¼x1½ | 2830                 | Watts    |
|                              |              | 50#                | 26124  | 740       | 1    | 1¼x1½ | 3075                 | Watts    |
|                              |              | 60#                | 26126  | 740       | 1    | 1¼x1½ | 3560                 | Watts    |
|                              |              | 75#                | 26117  | 740       | 1    | 1x1¼  | 2649                 | Watts    |
|                              |              | 125#               | 26158  | 174A      | 1    | ¾x¾   | 2070                 | Watts    |
|                              |              | 150#               | 26159  | 174A      | 1    | ¾x¾   | 2445                 | Watts    |
| 215                          | CL /CLM180-W |                    |        |           |      |       |                      |          |
|                              |              | 30#                | 26129  | 740       | 1    | 1½x2  | 2900                 | Watts    |
|                              |              | 45#                | 26123  | 740       | 1    | 1¼x1½ | 2830                 | Watts    |
|                              |              | 50#                | 26124  | 740       | 1    | 1¼x1½ | 3075                 | Watts    |
|                              |              | 60#                | 26126  | 740       | 1    | 1¼x1½ | 3560                 | Watts    |
|                              |              | 75#                | 26117  | 740       | 1    | 1x1¼  | 2649                 | Watts    |
|                              |              | 125#               | 26172  | 174A      | 1    | 1x1   | 3215                 | Watts    |
|                              |              | 150#               | 26159  | 174A      | 1    | ¾x¾   | 2445                 | Watts    |

# RELIEF VALVE SELECTIONS

| CL /CLM SERIES WATER BOILERS |              |                    |        |       |      |       |                      |        |
|------------------------------|--------------|--------------------|--------|-------|------|-------|----------------------|--------|
| H.S.                         | Boiler Model | Pressure<br>(Psig) | Part # | Model | Qty. | Size  | Actual Cap.<br>(MBH) | Vendor |
| 251                          | CL/CLM210-W  |                    |        |       |      |       |                      |        |
|                              |              | 30#                | 26129  | 740   | 1    | 1½x2  | 2900                 | Watts  |
|                              |              | 45#                | 26123  | 740   | 1    | 1¼x1½ | 2830                 | Watts  |
|                              |              | 50#                | 26124  | 740   | 1    | 1¼x1½ | 3075                 | Watts  |
|                              |              | 60#                | 26126  | 740   | 1    | 1¼x1½ | 3560                 | Watts  |
|                              |              | 75#                | 26117  | 740   | 1    | 1x1¼  | 2649                 | Watts  |
|                              |              | 125#               | 26172  | 174A  | 1    | 1x1   | 3215                 | Watts  |
|                              |              | 150#               | 26173  | 174A  | 1    | 1x1   | 3795                 | Watts  |
| 287                          | CL/CLM240-W  |                    |        |       |      |       |                      |        |
|                              |              | 30#                | 26129  | 740   | 1    | 1½x2  | 2900                 | Watts  |
|                              |              | 45#                | 26132  | 740   | 1    | 1½x2  | 3903                 | Watts  |
|                              |              | 50#                | 26124  | 740   | 1    | 1¼x1½ | 3075                 | Watts  |
|                              |              | 60#                | 26126  | 740   | 1    | 1¼x1½ | 3560                 | Watts  |
|                              |              | 75#                | 26127  | 740   | 1    | 1¼x1½ | 4285                 | Watts  |
|                              |              | 125#               | 26172  | 174A  | 1    | 1x1   | 3215                 | Watts  |
|                              |              | 150#               | 26173  | 174A  | 1    | 1x1   | 3795                 | Watts  |
| 322                          | CL/CLM270-W  |                    |        |       |      |       |                      |        |
|                              |              | 30#                | 26138  | 740   | 1    | 2x2½  | 5250                 | Watts  |
|                              |              | 45#                | 26132  | 740   | 1    | 1½x2  | 3903                 | Watts  |
|                              |              | 50#                | 26133  | 740   | 1    | 1½x2  | 4237                 | Watts  |
|                              |              | 60#                | 26126  | 740   | 1    | 1¼x1½ | 3560                 | Watts  |
|                              |              | 75#                | 26127  | 740   | 1    | 1¼x1½ | 4285                 | Watts  |
|                              |              | 125#               | 26186  | 174A  | 1    | 1¼x1¼ | 5370                 | Watts  |
|                              |              | 150#               | 26173  | 174A  | 1    | 1x1   | 3795                 | Watts  |
| 360                          | CL/CLM300-W  |                    |        |       |      |       |                      |        |
|                              |              | 30#                | 26138  | 740   | 1    | 2x2½  | 5250                 | Watts  |
|                              |              | 45#                | 26132  | 740   | 1    | 1½x2  | 3903                 | Watts  |
|                              |              | 50#                | 26133  | 740   | 1    | 1½x2  | 4237                 | Watts  |
|                              |              | 60#                | 26135  | 740   | 1    | 1½x2  | 4907                 | Watts  |
|                              |              | 75#                | 26127  | 740   | 1    | 1¼x1½ | 4285                 | Watts  |
|                              |              | 125#               | 26186  | 174A  | 1    | 1¼x1¼ | 5370                 | Watts  |
|                              |              | 150#               | 26173  | 174A  | 1    | 1x1   | 3795                 | Watts  |

## RELIEF VALVE SELECTIONS

| <b>D SERIES WATER BOILERS</b> |              |                    |        |           |      |         |                      |          |
|-------------------------------|--------------|--------------------|--------|-----------|------|---------|----------------------|----------|
| H.S.                          | Boiler Model | Pressure<br>(Psig) | Part # | Model     | Qty. | Size    | Actual Cap.<br>(MBH) | Vendor   |
| 27                            | D350-W       |                    |        |           |      |         |                      |          |
|                               |              | 30#                | 26230  | 10-303-05 | 1    | 3/4X3/4 | 550                  | ConBraCo |
|                               |              | 45#                | 26113  | 740       | 1    | 1x1½    | 1750                 | Watts    |
|                               |              | 60#                | 26107  | 740       | 1    | 3/4x1   | 1566                 | Watts    |
|                               |              | 75#                | 26117  | 740       | 1    | 1x1½    | 2649                 | Watts    |
|                               |              | 125#               | 26158  | 174A      | 1    | 3/4x3/4 | 2070                 | Watts    |
|                               |              | 150#               | 26159  | 174A      | 1    | 3/4x3/4 | 2445                 | Watts    |
| 34                            | D450-W       |                    |        |           |      |         |                      |          |
|                               |              | 30#                | 26230  | 10-303-05 | 1    | 3/4x3/4 | 550                  | ConBraCo |
|                               |              | 45#                | 26113  | 740       | 1    | 1x1½    | 1750                 | Watts    |
|                               |              | 60#                | 26107  | 740       | 1    | 3/4x1   | 1566                 | Watts    |
|                               |              | 75#                | 26117  | 740       | 1    | 1x1½    | 2649                 | Watts    |
|                               |              | 125#               | 26158  | 174A      | 1    | 3/4x3/4 | 2070                 | Watts    |
|                               |              | 150#               | 26159  | 174A      | 1    | 3/4x3/4 | 2445                 | Watts    |
| 50                            | D650-W       |                    |        |           |      |         |                      |          |
|                               |              | 30#                | 26230  | 10-303-05 | 1    | 3/4x3/4 | 550                  | ConBraCo |
|                               |              | 45#                | 26113  | 740       | 1    | 1x1½    | 1750                 | Watts    |
|                               |              | 60#                | 26107  | 740       | 1    | 3/4x1   | 1566                 | Watts    |
|                               |              | 75#                | 26117  | 740       | 1    | 1x1½    | 2649                 | Watts    |
|                               |              | 125#               | 26158  | 174A      | 1    | 3/4x3/4 | 2070                 | Watts    |
|                               |              | 150#               | 26159  | 174A      | 1    | 3/4x3/4 | 2445                 | Watts    |

# RELIEF VALVE SELECTIONS

| DR SERIES WATER BOILERS |              |                    |        |           |      |                   |                      |          |
|-------------------------|--------------|--------------------|--------|-----------|------|-------------------|----------------------|----------|
| H.S.                    | Boiler Model | Pressure<br>(Psig) | Part # | Model     | Qty. | Size              | Actual Cap.<br>(MBH) | Vendor   |
| 66                      | DR350-W      |                    |        |           |      |                   |                      |          |
|                         |              | 30#                | 26232  | 10-214-05 | 1    | 1X1               | 1000                 | ConBraCo |
|                         |              | 45#                | 26113  | 740       | 1    | 1x1 $\frac{1}{4}$ | 1750                 | Watts    |
|                         |              | 60#                | 26107  | 740       | 1    | 3/4x1             | 1566                 | Watts    |
|                         |              | 75#                | 26117  | 740       | 1    | 1x1 $\frac{1}{4}$ | 2649                 | Watts    |
|                         |              | 125#               | 26158  | 174A      | 1    | 3/4x3/4           | 2070                 | Watts    |
|                         |              | 150#               | 26159  | 174A      | 1    | 3/4x3/4           | 2445                 | Watts    |
| 66                      | DR450-W      |                    |        |           |      |                   |                      |          |
|                         |              | 30#                | 26232  | 10-214-05 | 1    | 1X1               | 1000                 | ConBraCo |
|                         |              | 45#                | 26113  | 740       | 1    | 1x1 $\frac{1}{4}$ | 1750                 | Watts    |
|                         |              | 60#                | 26107  | 740       | 1    | 3/4x1             | 1566                 | Watts    |
|                         |              | 75#                | 26117  | 740       | 1    | 1x1 $\frac{1}{4}$ | 2649                 | Watts    |
|                         |              | 125#               | 26158  | 174A      | 1    | 3/4x3/4           | 2070                 | Watts    |
|                         |              | 150#               | 26159  | 174A      | 1    | 3/4x3/4           | 2445                 | Watts    |
| 103                     | DR650-W      |                    |        |           |      |                   |                      |          |
|                         |              | 30#                | 94014  | 740       | 1    | 1x1 $\frac{1}{4}$ | 1300                 | Watts    |
|                         |              | 45#                | 26113  | 740       | 1    | 1x1 $\frac{1}{4}$ | 1750                 | Watts    |
|                         |              | 60#                | 26107  | 740       | 1    | 3/4x1             | 1566                 | Watts    |
|                         |              | 75#                | 26117  | 740       | 1    | 1x1 $\frac{1}{4}$ | 2649                 | Watts    |
|                         |              | 125#               | 26158  | 174A      | 1    | 3/4x3/4           | 2070                 | Watts    |
|                         |              | 150#               | 26159  | 174A      | 1    | 3/4x3/4           | 2445                 | Watts    |
| 103                     | DR850-W      |                    |        |           |      |                   |                      |          |
|                         |              | 30#                | 94014  | 740       | 1    | 1x1 $\frac{1}{4}$ | 1300                 | Watts    |
|                         |              | 45#                | 26113  | 740       | 1    | 1x1 $\frac{1}{4}$ | 1750                 | Watts    |
|                         |              | 60#                | 26107  | 740       | 1    | 3/4x1             | 1566                 | Watts    |
|                         |              | 75#                | 26117  | 740       | 1    | 1x1 $\frac{1}{4}$ | 2649                 | Watts    |
|                         |              | 125#               | 26158  | 174A      | 1    | 3/4x3/4           | 2070                 | Watts    |
|                         |              | 150#               | 26159  | 174A      | 1    | 3/4x3/4           | 2445                 | Watts    |

# RELIEF VALVE SELECTIONS

| F SERIES WATER BOILERS |              |                    |        |           |      |         |                      |          |
|------------------------|--------------|--------------------|--------|-----------|------|---------|----------------------|----------|
| H.S.                   | Boiler Model | Pressure<br>(Psig) | Part # | Model     | Qty. | Size    | Actual Cap.<br>(MBH) | Vendor   |
| 27                     | F350-W       |                    |        |           |      |         |                      |          |
|                        |              | 30#                | 26230  | 10-303-05 | 1    | 3/4X3/4 | 550                  | ConBraCo |
|                        |              | 45#                | 26113  | 740       | 1    | 1x1¼    | 1750                 | Watts    |
|                        |              | 60#                | 26107  | 740       | 1    | 3/4x1   | 1566                 | Watts    |
|                        |              | 75#                | 26117  | 740       | 1    | 1x1¼    | 2649                 | Watts    |
|                        |              | 125#               | 26158  | 174A      | 1    | 3/4x3/4 | 2070                 | Watts    |
|                        |              | 150#               | 26159  | 174A      | 1    | 3/4x3/4 | 2445                 | Watts    |
| 34                     | F450-W       |                    |        |           |      |         |                      |          |
|                        |              | 30#                | 26230  | 10-303-05 | 1    | 3/4x3/4 | 550                  | ConBraCo |
|                        |              | 45#                | 26113  | 740       | 1    | 1x1¼    | 1750                 | Watts    |
|                        |              | 60#                | 26107  | 740       | 1    | 3/4x1   | 1566                 | Watts    |
|                        |              | 75#                | 26117  | 740       | 1    | 1x1¼    | 2649                 | Watts    |
|                        |              | 125#               | 26158  | 174A      | 1    | 3/4x3/4 | 2070                 | Watts    |
|                        |              | 150#               | 26159  | 174A      | 1    | 3/4x3/4 | 2445                 | Watts    |
| 50                     | F650-W       |                    |        |           |      |         |                      |          |
|                        |              | 30#                | 26230  | 10-303-05 | 1    | 3/4x3/4 | 550                  | ConBraCo |
|                        |              | 45#                | 26113  | 740       | 1    | 1x1¼    | 1750                 | Watts    |
|                        |              | 60#                | 26107  | 740       | 1    | 3/4x1   | 1566                 | Watts    |
|                        |              | 75#                | 26117  | 740       | 1    | 1x1¼    | 2649                 | Watts    |
|                        |              | 125#               | 26158  | 174A      | 1    | 3/4x3/4 | 2070                 | Watts    |
|                        |              | 150#               | 26159  | 174A      | 1    | 3/4x3/4 | 2445                 | Watts    |
| 66                     | F850-W       |                    |        |           |      |         |                      |          |
|                        |              | 30#                | 26232  | 740       | 1    | 1x1     | 1000                 | ConBraCo |
|                        |              | 45#                | 26113  | 740       | 1    | 1x1¼    | 1750                 | Watts    |
|                        |              | 60#                | 26107  | 740       | 1    | 3/4x1   | 1566                 | Watts    |
|                        |              | 75#                | 26117  | 740       | 1    | 1x1¼    | 2649                 | Watts    |
|                        |              | 125#               | 26158  | 174A      | 1    | 3/4x3/4 | 2070                 | Watts    |
|                        |              | 150#               | 26159  | 174A      | 1    | 3/4x3/4 | 2445                 | Watts    |

# RELIEF VALVE SELECTIONS

| HECL /HECLM SERIES WATER BOILERS |                |                    |        |       |      |         |                                   |                               |        |
|----------------------------------|----------------|--------------------|--------|-------|------|---------|-----------------------------------|-------------------------------|--------|
| H.S.                             | Boiler Model   | Pressure<br>(Psig) | Part # | Model | Qty. | Size    | Actual Cap.<br>Per Valve<br>(MBH) | Actual Cap.<br>Total<br>(MBH) | Vendor |
| 131                              | HECL75         |                    |        |       |      |         |                                   |                               |        |
|                                  |                | 30#                | 26120  | 740   | 1    | 1¼x1½   | 2105                              | 2105                          | Watts  |
|                                  |                | 45#                | 26113  | 740   | 1    | 1x1¼    | 1750                              | 1750                          | Watts  |
|                                  |                | 50#                | 26124  | 740   | 1    | 1¼x1½   | 3075                              | 3075                          | Watts  |
|                                  |                | 60#                | 26107  | 740   | 1    | 3/4x1   | 1566                              | 1566                          | Watts  |
|                                  |                | 75#                | 26117  | 740   | 1    | 1x1¼    | 2649                              | 2649                          | Watts  |
|                                  |                | 125#               | 26158  | 174A  | 1    | 3/4x3/4 | 2070                              | 2070                          | Watts  |
|                                  |                | 150#               | 26159  | 174A  | 1    | 3/4x3/4 | 2445                              | 2445                          | Watts  |
| 171                              | HECL /HECLM90  |                    |        |       |      |         |                                   |                               |        |
|                                  |                | 30#                | 26120  | 740   | 1    | 1¼x1½   | 2105                              | 2105                          | Watts  |
|                                  |                | 45#                | 26113  | 740   | 1    | 1x1¼    | 1750                              | 1750                          | Watts  |
|                                  |                | 50#                | 26124  | 740   | 1    | 1¼x1½   | 3075                              | 3075                          | Watts  |
|                                  |                | 60#                | 26126  | 740   | 1    | 1¼x1½   | 3560                              | 3560                          | Watts  |
|                                  |                | 75#                | 26117  | 740   | 1    | 1x1¼    | 2649                              | 2649                          | Watts  |
|                                  |                | 125#               | 26158  | 174A  | 1    | 3/4x3/4 | 2070                              | 2070                          | Watts  |
|                                  |                | 150#               | 26159  | 174A  | 1    | 3/4x3/4 | 2445                              | 2445                          | Watts  |
| 227                              | HECL /HECLM120 |                    |        |       |      |         |                                   |                               |        |
|                                  |                | 30#                | 26129  | 740   | 1    | 1½x2    | 2900                              | 2900                          | Watts  |
|                                  |                | 45#                | 26123  | 740   | 1    | 1¼x1½   | 2830                              | 2830                          | Watts  |
|                                  |                | 50#                | 26124  | 740   | 1    | 1¼x1½   | 3075                              | 3075                          | Watts  |
|                                  |                | 60#                | 26126  | 740   | 1    | 1¼x1½   | 3560                              | 3560                          | Watts  |
|                                  |                | 75#                | 26117  | 740   | 1    | 1x1¼    | 2649                              | 2649                          | Watts  |
|                                  |                | 125#               | 26172  | 174A  | 1    | 1x1     | 3215                              | 3215                          | Watts  |
|                                  |                | 150#               | 26159  | 174A  | 1    | 3/4x3/4 | 2445                              | 2445                          | Watts  |
| 282                              | HECL /HECLM150 |                    |        |       |      |         |                                   |                               |        |
|                                  |                | 30#                | 26129  | 740   | 1    | 1½x2    | 2900                              | 2900                          | Watts  |
|                                  |                | 45#                | 26123  | 740   | 1    | 1¼x1½   | 2830                              | 2830                          | Watts  |
|                                  |                | 50#                | 26124  | 740   | 1    | 1¼x1½   | 3075                              | 3075                          | Watts  |
|                                  |                | 60#                | 26126  | 740   | 1    | 1¼x1½   | 3560                              | 3560                          | Watts  |
|                                  |                | 75#                | 26127  | 740   | 1    | 1¼x1½   | 4285                              | 4285                          | Watts  |
|                                  |                | 125#               | 26172  | 174A  | 1    | 1x1     | 3215                              | 3215                          | Watts  |
|                                  |                | 150#               | 26173  | 174A  | 1    | 1x1     | 3795                              | 3795                          | Watts  |
| 338                              | HECL /HECLM180 |                    |        |       |      |         |                                   |                               |        |
|                                  |                | 30#                | 26138  | 740   | 1    | 2x2½    | 5250                              | 5250                          | Watts  |
|                                  |                | 45#                | 26132  | 740   | 1    | 1½x2    | 3903                              | 3903                          | Watts  |
|                                  |                | 50#                | 26133  | 740   | 1    | 1½x2    | 4237                              | 4237                          | Watts  |
|                                  |                | 60#                | 26126  | 740   | 1    | 1¼x1½   | 3560                              | 3560                          | Watts  |
|                                  |                | 75#                | 26127  | 740   | 1    | 1¼x1½   | 4285                              | 4285                          | Watts  |
|                                  |                | 125#               | 26186  | 174A  | 1    | 1¼x1¼   | 5370                              | 5370                          | Watts  |
|                                  |                | 150#               | 26173  | 174A  | 1    | 1x1     | 3795                              | 3795                          | Watts  |



# RELIEF VALVE SELECTIONS

| <b>HECL /HECLM SERIES WATER BOILERS</b> |                |                    |        |       |      |       |                                   |                               |        |
|-----------------------------------------|----------------|--------------------|--------|-------|------|-------|-----------------------------------|-------------------------------|--------|
| H.S.                                    | Boiler Model   | Pressure<br>(Psig) | Part # | Model | Qty. | Size  | Actual Cap.<br>Per Valve<br>(MBH) | Actual Cap.<br>Total<br>(MBH) | Vendor |
| 394                                     | HECL /HECLM210 |                    |        |       |      |       |                                   |                               |        |
|                                         |                | 30#                | 26138  | 740   | 1    | 2x2½  | 5250                              | 5250                          | Watts  |
|                                         |                | 45#                | 26141  | 740   | 1    | 2x2½  | 7067                              | 7067                          | Watts  |
|                                         |                | 50#                | 26133  | 740   | 1    | 1½x2  | 4237                              | 4237                          | Watts  |
|                                         |                | 60#                | 26135  | 740   | 1    | 1½x2  | 4907                              | 4907                          | Watts  |
|                                         |                | 75#                | 26127  | 740   | 1    | 1¼x1½ | 4285                              | 4285                          | Watts  |
|                                         |                | 125#               | 26186  | 174A  | 1    | 1¼x1¼ | 5370                              | 5370                          | Watts  |
|                                         |                | 150#               | 94054  | 174A  | 1    | 1¼x1¼ | 6340                              | 6340                          | Watts  |
| 451                                     | HECL /HECLM240 |                    |        |       |      |       |                                   |                               |        |
|                                         |                | 30#                | 26138  | 740   | 1    | 2x2½  | 5250                              | 5250                          | Watts  |
|                                         |                | 45#                | 26141  | 740   | 1    | 2x2½  | 7067                              | 7067                          | Watts  |
|                                         |                | 50#                | 26142  | 740   | 1    | 2x2½  | 7672                              | 7672                          | Watts  |
|                                         |                | 60#                | 26135  | 740   | 1    | 1½x2  | 4907                              | 4907                          | Watts  |
|                                         |                | 75#                | 94038  | 740   | 1    | 1½x2  | 5909                              | 5909                          | Watts  |
|                                         |                | 125#               | 26186  | 174A  | 1    | 1¼x1¼ | 5370                              | 5370                          | Watts  |
|                                         |                | 150#               | 94054  | 174A  | 1    | 1¼x1¼ | 6340                              | 6340                          | Watts  |
| 506                                     | HECL /HECLM270 |                    |        |       |      |       |                                   |                               |        |
|                                         |                | 30#                | 26138  | 740   | 1    | 2x2½  | 5250                              | 5250                          | Watts  |
|                                         |                | 45#                | 26141  | 740   | 1    | 2x2½  | 7067                              | 7067                          | Watts  |
|                                         |                | 50#                | 26142  | 740   | 1    | 2x2½  | 7672                              | 7672                          | Watts  |
|                                         |                | 60#                | 94046  | 740   | 1    | 2x2½  | 8883                              | 8883                          | Watts  |
|                                         |                | 75#                | 94038  | 740   | 1    | 1½x2  | 5909                              | 5909                          | Watts  |
|                                         |                | 125#               | 26186  | 174A  | 1    | 1¼x1¼ | 5370                              | 5370                          | Watts  |
|                                         |                | 150#               | 94054  | 174A  | 1    | 1¼x1¼ | 6340                              | 6340                          | Watts  |
| 564                                     | HECL /HECLM300 |                    |        |       |      |       |                                   |                               |        |
|                                         |                | 30#                | 26129  | 740   | 2    | 1½x2  | 2900                              | 5800                          | Watts  |
|                                         |                | 45#                | 26141  | 740   | 1    | 2x2½  | 7067                              | 7067                          | Watts  |
|                                         |                | 50#                | 26142  | 740   | 1    | 2x2½  | 7672                              | 7672                          | Watts  |
|                                         |                | 60#                | 26126  | 740   | 2    | 1¼x1½ | 3560                              | 7120                          | Watts  |
|                                         |                | 75#                | 26127  | 740   | 2    | 1¼x1½ | 4285                              | 8570                          | Watts  |
|                                         |                | 125#               | 26200  | 174A  | 1    | 1½x1½ | 6460                              | 6460                          | Watts  |
|                                         |                | 150#               | 26173  | 174A  | 2    | 1x1   | 3795                              | 7590                          | Watts  |

# RELIEF VALVE SELECTIONS

| <i>HED Series Water Boilers</i> |              |                    |        |           |      |         |                      |          |
|---------------------------------|--------------|--------------------|--------|-----------|------|---------|----------------------|----------|
| H.S.                            | Boiler Model | Pressure<br>(Psig) | Part # | Model     | Qty. | Size    | Actual Cap.<br>(MBH) | Vendor   |
| 68                              | HED305       |                    |        |           |      |         |                      |          |
|                                 |              | 30#                | 26232  | 10-214-05 | 1    | 1x1     | 1000                 | ConBraCo |
|                                 |              | 45#                | 26113  | 740       | 1    | 1x1¼    | 1750                 | Watts    |
|                                 |              | 60#                | 26107  | 740       | 1    | 3/4x1   | 1566                 | Watts    |
|                                 |              | 75#                | 26117  | 740       | 1    | 1x1¼    | 2649                 | Watts    |
|                                 |              | 125#               | 26158  | 174A      | 1    | 3/4x3/4 | 2070                 | Watts    |
|                                 |              | 150#               | 26159  | 174A      | 1    | 3/4x3/4 | 2445                 | Watts    |
| 68                              | HED350       |                    |        |           |      |         |                      |          |
|                                 |              | 30#                | 26232  | 10-214-05 | 1    | 1x1     | 1000                 | ConBraCo |
|                                 |              | 45#                | 26113  | 740       | 1    | 1x1¼    | 1750                 | Watts    |
|                                 |              | 60#                | 26107  | 740       | 1    | 3/4x1   | 1566                 | Watts    |
|                                 |              | 75#                | 26117  | 740       | 1    | 1x1¼    | 2649                 | Watts    |
|                                 |              | 125#               | 26158  | 174A      | 1    | 3/4x3/4 | 2070                 | Watts    |
|                                 |              | 150#               | 26159  | 174A      | 1    | 3/4x3/4 | 2445                 | Watts    |
| 95                              | HED450       |                    |        |           |      |         |                      |          |
|                                 |              | 30#                | 26232  | 10-214-05 | 1    | 1x1     | 1000                 | ConBraCo |
|                                 |              | 45#                | 26113  | 740       | 1    | 1x1¼    | 1750                 | Watts    |
|                                 |              | 60#                | 26107  | 740       | 1    | 3/4x1   | 1566                 | Watts    |
|                                 |              | 75#                | 26117  | 740       | 1    | 1x1¼    | 2649                 | Watts    |
|                                 |              | 125#               | 26158  | 174A      | 1    | 3/4x3/4 | 2070                 | Watts    |
|                                 |              | 150#               | 26159  | 174A      | 1    | 3/4x3/4 | 2445                 | Watts    |
| 132                             | HED650       |                    |        |           |      |         |                      |          |
|                                 |              | 30#                | 26120  | 740       | 1    | 1¼x1½   | 2105                 | Watts    |
|                                 |              | 45#                | 26113  | 740       | 1    | 1x1¼    | 1750                 | Watts    |
|                                 |              | 60#                | 26107  | 740       | 1    | 3/4x1   | 1566                 | Watts    |
|                                 |              | 75#                | 26117  | 740       | 1    | 1x1¼    | 2649                 | Watts    |
|                                 |              | 125#               | 26158  | 174A      | 1    | 3/4x3/4 | 2070                 | Watts    |
|                                 |              | 150#               | 26159  | 174A      | 1    | 3/4x3/4 | 2445                 | Watts    |

# RELIEF VALVE SELECTIONS

| K Series Water Boilers |              |                    |        |       |      |       |                                   |                               |        |
|------------------------|--------------|--------------------|--------|-------|------|-------|-----------------------------------|-------------------------------|--------|
| H.S.                   | Boiler Model | Pressure<br>(Psig) | Part # | Model | Qty. | Size  | Actual Cap.<br>Per Valve<br>(MBH) | Actual Cap.<br>Total<br>(MBH) | Vendor |
| 300                    | K250         | 30#                | 26138  | 740   | 1    | 2x2½  | 5250                              | 5250                          | Watts  |
|                        |              | 45#                | 26132  | 740   | 1    | 1½x2  | 3903                              | 3903                          | Watts  |
|                        |              | 50#                | 26124  | 740   | 1    | 1¼x1½ | 3075                              | 3075                          | Watts  |
|                        |              | 60#                | 26126  | 740   | 1    | 1¼x1½ | 3560                              | 3560                          | Watts  |
|                        |              | 75#                | 26127  | 740   | 1    | 1¼x1½ | 4285                              | 4285                          | Watts  |
|                        |              | 125#               | 26172  | 174A  | 1    | 1x1   | 3215                              | 3215                          | Watts  |
|                        |              | 150#               | 26173  | 174A  | 1    | 1x1   | 3795                              | 3795                          | Watts  |
| 361                    | K300         |                    |        |       |      |       |                                   |                               |        |
|                        |              | 30#                | 26138  | 740   | 1    | 2x2½  | 5250                              | 5250                          | Watts  |
|                        |              | 45#                | 26132  | 740   | 1    | 1½x2  | 3903                              | 3903                          | Watts  |
|                        |              | 50#                | 26133  | 740   | 1    | 1½x2  | 4237                              | 4237                          | Watts  |
|                        |              | 60#                | 26135  | 740   | 1    | 1½x2  | 4907                              | 4907                          | Watts  |
|                        |              | 75#                | 26127  | 740   | 1    | 1¼x1½ | 4285                              | 4285                          | Watts  |
|                        |              | 125#               | 26186  | 174A  | 1    | 1¼x1¼ | 5370                              | 5370                          | Watts  |
|                        |              | 150#               | 26173  | 174A  | 1    | 1x1   | 3795                              | 3795                          | Watts  |
| 424                    | K350         |                    |        |       |      |       |                                   |                               |        |
|                        |              | 30#                | 26138  | 740   | 1    | 2x2½  | 5250                              | 5250                          | Watts  |
|                        |              | 45#                | 26141  | 740   | 1    | 2x2½  | 7067                              | 7067                          | Watts  |
|                        |              | 50#                | 26142  | 740   | 1    | 2x2½  | 7672                              | 7672                          | Watts  |
|                        |              | 60#                | 26135  | 740   | 1    | 1½x2  | 4907                              | 4907                          | Watts  |
|                        |              | 75#                | 26127  | 740   | 1    | 1¼x1½ | 4285                              | 4285                          | Watts  |
|                        |              | 125#               | 26186  | 174A  | 1    | 1¼x1¼ | 5370                              | 5370                          | Watts  |
|                        |              | 150#               | 94054  | 174A  | 1    | 1¼x1¼ | 6340                              | 6340                          | Watts  |
| 480                    | K400         |                    |        |       |      |       |                                   |                               |        |
|                        |              | 30#                | 26138  | 740   | 1    | 2x2½  | 5250                              | 5250                          | Watts  |
|                        |              | 45#                | 26141  | 740   | 1    | 2x2½  | 7067                              | 7067                          | Watts  |
|                        |              | 50#                | 26142  | 740   | 1    | 2x2½  | 7672                              | 7672                          | Watts  |
|                        |              | 60#                | 26135  | 740   | 1    | 1½x2  | 4907                              | 4907                          | Watts  |
|                        |              | 75#                | 94038  | 740   | 1    | 1½x2  | 5909                              | 5909                          | Watts  |
|                        |              | 125#               | 26186  | 174A  | 1    | 1¼x1¼ | 5370                              | 5370                          | Watts  |
|                        |              | 150#               | 94054  | 174A  | 1    | 1¼x1¼ | 6340                              | 6340                          | Watts  |
| 540                    | K450         |                    |        |       |      |       |                                   |                               |        |
|                        |              | 30#                | 26129  | 740   | 2    | 1½x2  | 2900                              | 5800                          | Watts  |
|                        |              | 45#                | 26141  | 740   | 1    | 2x2½  | 7067                              | 7067                          | Watts  |
|                        |              | 50#                | 26142  | 740   | 1    | 2x2½  | 7672                              | 7672                          | Watts  |
|                        |              | 60#                | 26126  | 740   | 2    | 1¼x1½ | 3560                              | 7120                          | Watts  |
|                        |              | 75#                | 94038  | 740   | 1    | 1½x2  | 5909                              | 5909                          | Watts  |
|                        |              | 125#               | 26200  | 174A  | 1    | 1½x1½ | 6460                              | 6460                          | Watts  |
|                        |              | 150#               | 26173  | 174A  | 2    | 1x1   | 3795                              | 7590                          | Watts  |

# RELIEF VALVE SELECTIONS

| K Series Water Boilers |              |                    |        |       |      |       |                                   |                               |        |
|------------------------|--------------|--------------------|--------|-------|------|-------|-----------------------------------|-------------------------------|--------|
| H.S.                   | Boiler Model | Pressure<br>(Psig) | Part # | Model | Qty. | Size  | Actual Cap.<br>Per Valve<br>(MBH) | Actual Cap.<br>Total<br>(MBH) | Vendor |
| 600                    | K500         |                    |        |       |      |       |                                   |                               |        |
|                        |              | 30#                | 26138  | 740   | 2    | 2x2½  | 5250                              | 10500                         | Watts  |
|                        |              | 45#                | 26141  | 740   | 1    | 2x2½  | 7067                              | 7067                          | Watts  |
|                        |              | 50#                | 26142  | 740   | 1    | 2x2½  | 7672                              | 7672                          | Watts  |
|                        |              | 60#                | 26126  | 740   | 2    | 1¼x1½ | 3560                              | 7120                          | Watts  |
|                        |              | 75#                | 26127  | 740   | 2    | 1¼x1½ | 4285                              | 8570                          | Watts  |
|                        |              | 125#               | 26200  | 174A  | 1    | 1½x1½ | 6460                              | 6460                          | Watts  |
|                        |              | 150#               | 26173  | 174A  | 2    | 1x1   | 3795                              | 7590                          | Watts  |
| 661                    | K550         |                    |        |       |      |       |                                   |                               |        |
|                        |              | 30#                | 26138  | 740   | 2    | 2x2½  | 5250                              | 10500                         | Watts  |
|                        |              | 45#                | 26141  | 740   | 1    | 2x2½  | 7067                              | 7067                          | Watts  |
|                        |              | 50#                | 26142  | 740   | 1    | 2x2½  | 7672                              | 7672                          | Watts  |
|                        |              | 60#                | 26126  | 740   | 2    | 1¼x1½ | 3560                              | 7120                          | Watts  |
|                        |              | 75#                | 26127  | 740   | 2    | 1¼x1½ | 4285                              | 8570                          | Watts  |
|                        |              | 125#               | 26186  | 174A  | 2    | 1¼x1¼ | 5370                              | 10740                         | Watts  |
|                        |              | 150#               | 26173  | 174A  | 2    | 1x1   | 3795                              | 7590                          | Watts  |
| 717                    | K600         |                    |        |       |      |       |                                   |                               |        |
|                        |              | 30#                | 26138  | 740   | 2    | 2x2½  | 5250                              | 10500                         | Watts  |
|                        |              | 45#                | 26132  | 740   | 2    | 1½x2  | 3903                              | 7806                          | Watts  |
|                        |              | 50#                | 26142  | 740   | 1    | 2x2½  | 7672                              | 7672                          | Watts  |
|                        |              | 60#                | 26135  | 740   | 2    | 1½x2  | 4907                              | 9814                          | Watts  |
|                        |              | 75#                | 26127  | 740   | 2    | 1¼x1½ | 4285                              | 8570                          | Watts  |
|                        |              | 125#               | 26186  | 174A  | 2    | 1¼x1¼ | 5370                              | 10740                         | Watts  |
|                        |              | 150#               | 26173  | 174A  | 2    | 1x1   | 3795                              | 7590                          | Watts  |
| 777                    | K650         |                    |        |       |      |       |                                   |                               |        |
|                        |              | 30#                | 26138  | 740   | 2    | 2x2½  | 5250                              | 10500                         | Watts  |
|                        |              | 45#                | 26132  | 740   | 2    | 1½x2  | 3903                              | 7806                          | Watts  |
|                        |              | 50#                | 26133  | 740   | 2    | 1½x2  | 4237                              | 8474                          | Watts  |
|                        |              | 60#                | 26135  | 740   | 2    | 1½x2  | 4907                              | 9814                          | Watts  |
|                        |              | 75#                | 26127  | 740   | 2    | 1¼x1½ | 4285                              | 8570                          | Watts  |
|                        |              | 125#               | 26186  | 174A  | 2    | 1¼x1¼ | 5370                              | 10740                         | Watts  |
|                        |              | 150#               | 94064  | 174A  | 1    | 2x2   | 14370                             | 14370                         | Watts  |

# RELIEF VALVE SELECTIONS

| RV Series Water Boilers |              |                    |        |       |      |         |                                   |                               |        |
|-------------------------|--------------|--------------------|--------|-------|------|---------|-----------------------------------|-------------------------------|--------|
| H.S.                    | Boiler Model | Pressure<br>(Psig) | Part # | Model | Qty. | Size    | Actual Cap.<br>Per Valve<br>(MBH) | Actual Cap.<br>Total<br>(MBH) | Vendor |
| 240                     | RV200        |                    |        |       |      |         |                                   |                               |        |
|                         |              | 30#                | 26129  | 740   | 1    | 1½x2    | 2900                              | 2900                          | Watts  |
|                         |              | 45#                | 26123  | 740   | 1    | 1¼x1½   | 2830                              | 2830                          | Watts  |
|                         |              | 50#                | 26124  | 740   | 1    | 1¼x1½   | 3075                              | 3075                          | Watts  |
|                         |              | 60#                | 26126  | 740   | 1    | 1¼x1½   | 3560                              | 3560                          | Watts  |
|                         |              | 75#                | 26117  | 740   | 1    | 1x1¼    | 2649                              | 2649                          | Watts  |
|                         |              | 125#               | 26172  | 174A  | 1    | 1x1     | 3215                              | 3215                          | Watts  |
|                         |              | 150#               | 26159  | 174A  | 1    | 3/4x3/4 | 2445                              | 2445                          | Watts  |
| 299                     | RV250        |                    |        |       |      |         |                                   |                               |        |
|                         |              | 30#                | 26138  | 740   | 1    | 2x2½    | 5250                              | 5250                          | Watts  |
|                         |              | 45#                | 26132  | 740   | 1    | 1½x2    | 3903                              | 3903                          | Watts  |
|                         |              | 50#                | 26124  | 740   | 1    | 1¼x1½   | 3075                              | 3075                          | Watts  |
|                         |              | 60#                | 26126  | 740   | 1    | 1¼x1½   | 3560                              | 3560                          | Watts  |
|                         |              | 75#                | 26127  | 740   | 1    | 1¼x1½   | 4285                              | 4285                          | Watts  |
|                         |              | 125#               | 26172  | 174A  | 1    | 1x1     | 3215                              | 3215                          | Watts  |
|                         |              | 150#               | 26173  | 174A  | 1    | 1x1     | 3795                              | 3795                          | Watts  |
| 365                     | RV300        |                    |        |       |      |         |                                   |                               |        |
|                         |              | 30#                | 26138  | 740   | 1    | 2x2½    | 5250                              | 5250                          | Watts  |
|                         |              | 45#                | 26132  | 740   | 1    | 1½x2    | 3903                              | 3903                          | Watts  |
|                         |              | 50#                | 26133  | 740   | 1    | 1½x2    | 4237                              | 4237                          | Watts  |
|                         |              | 60#                | 26135  | 740   | 1    | 1½x2    | 4907                              | 4907                          | Watts  |
|                         |              | 75#                | 26127  | 740   | 1    | 1¼x1½   | 4285                              | 4285                          | Watts  |
|                         |              | 125#               | 26186  | 174A  | 1    | 1¼x1¼   | 5370                              | 5370                          | Watts  |
|                         |              | 150#               | 26173  | 174A  | 1    | 1x1     | 3795                              | 3795                          | Watts  |
| 419                     | RV350        |                    |        |       |      |         |                                   |                               |        |
|                         |              | 30#                | 26138  | 740   | 1    | 2x2½    | 5250                              | 5250                          | Watts  |
|                         |              | 45#                | 26141  | 740   | 1    | 2x2½    | 7067                              | 7067                          | Watts  |
|                         |              | 50#                | 26133  | 740   | 1    | 1½x2    | 4237                              | 4237                          | Watts  |
|                         |              | 60#                | 26135  | 740   | 1    | 1½x2    | 4907                              | 4907                          | Watts  |
|                         |              | 75#                | 26127  | 740   | 1    | 1¼x1½   | 4285                              | 4285                          | Watts  |
|                         |              | 125#               | 26186  | 174A  | 1    | 1¼x1¼   | 5370                              | 5370                          | Watts  |
|                         |              | 150#               | 94054  | 174A  | 1    | 1¼x1¼   | 6340                              | 6340                          | Watts  |
| 490                     | RV400        |                    |        |       |      |         |                                   |                               |        |
|                         |              | 30#                | 26138  | 740   | 1    | 2x2½    | 5250                              | 5250                          | Watts  |
|                         |              | 45#                | 26141  | 740   | 1    | 2x2½    | 7067                              | 7067                          | Watts  |
|                         |              | 50#                | 26142  | 740   | 1    | 2x2½    | 7672                              | 7672                          | Watts  |
|                         |              | 60#                | 26135  | 740   | 1    | 1½x2    | 4907                              | 4907                          | Watts  |
|                         |              | 75#                | 94038  | 740   | 1    | 1½x2    | 5909                              | 5909                          | Watts  |
|                         |              | 125#               | 26186  | 174A  | 1    | 1¼x1¼   | 5370                              | 5370                          | Watts  |
|                         |              | 150#               | 94054  | 174A  | 1    | 1¼x1¼   | 6340                              | 6340                          | Watts  |

# RELIEF VALVE SELECTIONS

| RV Series Water Boilers |              |                    |        |       |      |       |                                   |                               |        |
|-------------------------|--------------|--------------------|--------|-------|------|-------|-----------------------------------|-------------------------------|--------|
| H.S.                    | Boiler Model | Pressure<br>(Psig) | Part # | Model | Qty. | Size  | Actual Cap.<br>Per Valve<br>(MBH) | Actual Cap.<br>Total<br>(MBH) | Vendor |
| 544                     | RV450        |                    |        |       |      |       |                                   |                               |        |
|                         |              | 30#                | 26129  | 740   | 2    | 1½x2  | 2900                              | 5800                          | Watts  |
|                         |              | 45#                | 26141  | 740   | 1    | 2x2½  | 7067                              | 7067                          | Watts  |
|                         |              | 50#                | 26142  | 740   | 1    | 2x2½  | 7672                              | 7672                          | Watts  |
|                         |              | 60#                | 26126  | 740   | 2    | 1¼x1½ | 3560                              | 7120                          | Watts  |
|                         |              | 75#                | 94038  | 740   | 1    | 1½x2  | 5909                              | 5909                          | Watts  |
|                         |              | 125#               | 26200  | 174A  | 1    | 1½x1½ | 6460                              | 6460                          | Watts  |
|                         |              | 150#               | 26173  | 174A  | 2    | 1x1   | 3795                              | 7590                          | Watts  |
| 597                     | RV500        |                    |        |       |      |       |                                   |                               |        |
|                         |              | 30#                | 26138  | 740   | 2    | 2x2½  | 5250                              | 10500                         | Watts  |
|                         |              | 45#                | 26141  | 740   | 1    | 2x2½  | 7067                              | 7067                          | Watts  |
|                         |              | 50#                | 26142  | 740   | 1    | 2x2½  | 7672                              | 7672                          | Watts  |
|                         |              | 60#                | 26126  | 740   | 2    | 1¼x1½ | 3560                              | 7120                          | Watts  |
|                         |              | 75#                | 26127  | 740   | 2    | 1¼x1½ | 4285                              | 8570                          | Watts  |
|                         |              | 125#               | 26200  | 174A  | 1    | 1½x1½ | 6460                              | 6460                          | Watts  |
|                         |              | 150#               | 26173  | 174A  | 2    | 1x1   | 3795                              | 7590                          | Watts  |
| 668                     | RV550        |                    |        |       |      |       |                                   |                               |        |
|                         |              | 30#                | 26138  | 740   | 2    | 2x2½  | 5250                              | 10500                         | Watts  |
|                         |              | 45#                | 26141  | 740   | 1    | 2x2½  | 7067                              | 7067                          | Watts  |
|                         |              | 50#                | 26142  | 740   | 1    | 2x2½  | 7672                              | 7672                          | Watts  |
|                         |              | 60#                | 26126  | 740   | 2    | 1¼x1½ | 3560                              | 7120                          | Watts  |
|                         |              | 75#                | 26127  | 740   | 2    | 1¼x1½ | 4285                              | 8570                          | Watts  |
|                         |              | 125#               | 26186  | 174A  | 2    | 1¼x1¼ | 5370                              | 10740                         | Watts  |
|                         |              | 150#               | 26173  | 174A  | 2    | 1x1   | 3795                              | 7590                          | Watts  |
| 722                     | RV600        |                    |        |       |      |       |                                   |                               |        |
|                         |              | 30#                | 26138  | 740   | 2    | 2x2½  | 5250                              | 10500                         | Watts  |
|                         |              | 45#                | 26132  | 740   | 2    | 1½x2  | 3903                              | 7806                          | Watts  |
|                         |              | 50#                | 26142  | 740   | 1    | 2x2½  | 7672                              | 7672                          | Watts  |
|                         |              | 60#                | 26135  | 740   | 2    | 1½x2  | 4907                              | 9814                          | Watts  |
|                         |              | 75#                | 26127  | 740   | 2    | 1¼x1½ | 4285                              | 8570                          | Watts  |
|                         |              | 125#               | 26186  | 174A  | 2    | 1¼x1¼ | 5370                              | 10740                         | Watts  |
|                         |              | 150#               | 26173  | 174A  | 2    | 1x1   | 3795                              | 7590                          | Watts  |
| 847                     | RV700        |                    |        |       |      |       |                                   |                               |        |
|                         |              | 30#                | 26138  | 740   | 2    | 2x2½  | 5250                              | 10500                         | Watts  |
|                         |              | 45#                | 26141  | 740   | 2    | 2x2½  | 7067                              | 14134                         | Watts  |
|                         |              | 50#                | 26133  | 740   | 2    | 1½x2  | 4237                              | 8474                          | Watts  |
|                         |              | 60#                | 26135  | 740   | 2    | 1½x2  | 4907                              | 9814                          | Watts  |
|                         |              | 75#                | 26127  | 740   | 2    | 1¼x1½ | 4285                              | 8570                          | Watts  |
|                         |              | 125#               | 26186  | 174A  | 2    | 1¼x1¼ | 5370                              | 10740                         | Watts  |
|                         |              | 150#               | 94064  | 174A  | 1    | 2x2   | 14370                             | 14370                         | Watts  |
| 972                     | RV800        |                    |        |       |      |       |                                   |                               |        |
|                         |              | 30#                | 26138  | 740   | 2    | 2x2½  | 5250                              | 10500                         | Watts  |
|                         |              | 45#                | 26141  | 740   | 2    | 2x2½  | 7067                              | 14134                         | Watts  |
|                         |              | 50#                | 26142  | 740   | 2    | 2x2½  | 7672                              | 15344                         | Watts  |
|                         |              | 60#                | 26135  | 740   | 2    | 1½x2  | 4907                              | 9814                          | Watts  |
|                         |              | 75#                | 94048  | 740   | 1    | 2x2½  | 10700                             | 10700                         | Watts  |
|                         |              | 125#               | 26186  | 174A  | 2    | 1¼x1¼ | 5370                              | 10740                         | Watts  |
|                         |              | 150#               | 94064  | 174A  | 1    | 2x2   | 14370                             | 14370                         | Watts  |

## RELIEF VALVE SELECTIONS

| RW Series Water Boilers |              |                    |        |       |      |       |                                   |                               |        |
|-------------------------|--------------|--------------------|--------|-------|------|-------|-----------------------------------|-------------------------------|--------|
| H.S.                    | Boiler Model | Pressure<br>(Psig) | Part # | Model | Qty. | Size  | Actual Cap.<br>Per Valve<br>(MBH) | Actual Cap.<br>Total<br>(MBH) | Vendor |
| 1118                    | RW850        |                    |        |       |      |       |                                   |                               |        |
|                         |              | 30#                | 26138  | 740   | 3    | 2x2½  | 5250                              | 15750                         | Watts  |
|                         |              | 45#                | 26141  | 740   | 2    | 2x2½  | 7067                              | 14134                         | Watts  |
|                         |              | 50#                | 26142  | 740   | 2    | 2x2½  | 7672                              | 15344                         | Watts  |
|                         |              | 60#                | 94046  | 740   | 2    | 2x2½  | 8883                              | 17766                         | Watts  |
|                         |              | 75#                | 94038  | 740   | 2    | 1½x2  | 5909                              | 11818                         | Watts  |
|                         |              | 125#               | 26200  | 174A  | 2    | 1½x1½ | 6460                              | 12920                         | Watts  |
|                         |              | 150#               | 94054  | 174A  | 2    | 1½x1¼ | 6340                              | 12680                         | Watts  |
| 1266                    | RW1050       |                    |        |       |      |       |                                   |                               |        |
|                         |              | 30#                | 26138  | 740   | 3    | 2x2½  | 5250                              | 15750                         | Watts  |
|                         |              | 45#                | 26141  | 740   | 2    | 2x2½  | 7067                              | 14134                         | Watts  |
|                         |              | 50#                | 26142  | 740   | 2    | 2x2½  | 7672                              | 15344                         | Watts  |
|                         |              | 60#                | 26135  | 740   | 2    | 2x2½  | 8883                              | 17766                         | Watts  |
|                         |              | 75#                | 94048  | 740   | 2    | 2x2½  | 10700                             | 21400                         | Watts  |
|                         |              | 125#               | 26200  | 174A  | 2    | 1½x1½ | 6460                              | 12920                         | Watts  |
|                         |              | 150#               | 94058  | 174A  | 2    | 1½x1½ | 7630                              | 15260                         | Watts  |
| 1527                    | RW1260       |                    |        |       |      |       |                                   |                               |        |
|                         |              | 30#                | 26138  | 740   | 3    | 2x2½  | 5250                              | 15750                         | Watts  |
|                         |              | 45#                | 26141  | 740   | 3    | 2x2½  | 7067                              | 21201                         | Watts  |
|                         |              | 50#                | 26142  | 740   | 2    | 2x2½  | 7672                              | 15344                         | Watts  |
|                         |              | 60#                | 94046  | 740   | 2    | 2x2½  | 8883                              | 17766                         | Watts  |
|                         |              | 75#                | 94048  | 740   | 2    | 2x2½  | 10700                             | 21400                         | Watts  |
|                         |              | 125#               | 94062  | 174A  | 2    | 2x2   | 12170                             | 24340                         | Watts  |
|                         |              | 150#               | 94054  | 174A  | 3    | 1½x1¼ | 6340                              | 19020                         | Watts  |
| 1787                    | RW1500       |                    |        |       |      |       |                                   |                               |        |
|                         |              | 30#                | 26138  | 740   | 4    | 2x2½  | 5250                              | 21000                         | Watts  |
|                         |              | 45#                | 26141  | 740   | 3    | 2x2½  | 7067                              | 21201                         | Watts  |
|                         |              | 50#                | 26142  | 740   | 3    | 2x2½  | 7672                              | 23016                         | Watts  |
|                         |              | 60#                | 94046  | 740   | 3    | 2x2½  | 8883                              | 26649                         | Watts  |
|                         |              | 75#                | 94048  | 740   | 2    | 2x2½  | 10700                             | 21400                         | Watts  |
|                         |              | 125#               | 94062  | 174A  | 2    | 2x2   | 12170                             | 24340                         | Watts  |
|                         |              | 150#               | 94064  | 174A  | 2    | 2x2   | 14370                             | 28740                         | Watts  |
| 2048                    | RW1700       |                    |        |       |      |       |                                   |                               |        |
|                         |              | 30#                | 26138  | 740   | 4    | 2x2½  | 5250                              | 21000                         | Watts  |
|                         |              | 45#                | 26141  | 740   | 3    | 2x2½  | 7067                              | 21201                         | Watts  |
|                         |              | 50#                | 26142  | 740   | 3    | 2x2½  | 7672                              | 23016                         | Watts  |
|                         |              | 60#                | 94046  | 740   | 3    | 2x2½  | 8883                              | 26649                         | Watts  |
|                         |              | 75#                | 64048  | 740   | 2    | 2x2½  | 10700                             | 21400                         | Watts  |
|                         |              | 125#               | 94062  | 174A  | 2    | 2x2   | 12170                             | 24340                         | Watts  |
|                         |              | 150#               | 94064  | 174A  | 2    | 2x2   | 14370                             | 28740                         | Watts  |
| 2308                    | RW1900       |                    |        |       |      |       |                                   |                               |        |
|                         |              | 30#                | 26138  | 740   | 5    | 2x2½  | 5250                              | 26250                         | Watts  |
|                         |              | 45#                | 26141  | 740   | 4    | 2x2½  | 7067                              | 28268                         | Watts  |
|                         |              | 50#                | 26142  | 740   | 4    | 2x2½  | 7672                              | 30688                         | Watts  |
|                         |              | 60#                | 94046  | 740   | 3    | 2x2½  | 8883                              | 26649                         | Watts  |
|                         |              | 75#                | 94048  | 740   | 3    | 2x2½  | 10700                             | 32100                         | Watts  |
|                         |              | 125#               | 94062  | 174A  | 2    | 2x2   | 12170                             | 24340                         | Watts  |
|                         |              | 150#               | 94064  | 174A  | 2    | 2x2   | 14370                             | 28740                         | Watts  |
| 2569                    | RW2100       |                    |        |       |      |       |                                   |                               |        |
|                         |              | 30#                | 26138  | 740   | 5    | 2x2½  | 5250                              | 26250                         | Watts  |
|                         |              | 45#                | 26141  | 740   | 4    | 2x2½  | 7067                              | 28268                         | Watts  |
|                         |              | 50#                | 26142  | 740   | 4    | 2x2½  | 7672                              | 30688                         | Watts  |
|                         |              | 60#                | 94046  | 740   | 3    | 2x2½  | 8883                              | 26649                         | Watts  |
|                         |              | 75#                | 94048  | 740   | 3    | 2x2½  | 10700                             | 32100                         | Watts  |
|                         |              | 125#               | 94062  | 174A  | 3    | 2x2   | 12170                             | 36510                         | Watts  |
|                         |              | 150#               | 94064  | 174A  | 2    | 2x2   | 14370                             | 28740                         | Watts  |