



145 West Commercial Ave.
Moonachie, NJ 07074

Dimmer Compatibility Guide

PLEASE NOTE: Compatibility list is based upon testing conducted by the manufacturer in a lab simulation.

Product Family Name:

| | | | |
|-----------------------|-------------------------|---------------------|---------------------|
| Item Number: | 776707 | 776765 | 776718 |
| Ordering Code: | LED5T9/21K/11/FIL-NOS/3 | LED5T9/27K/11/FIL/3 | LED5T9/30K/11/FIL/3 |
| Item Number: | | | |
| Ordering Code: | | | |

| | Manufacturer | Product | Model Number |
|---|--------------|------------------------------------|---------------|
| Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers) | Leviton | IllumaTech | IPI06 |
| | | SureSlide | 6633-P |
| | | Vizia | VPI06-1LZ |
| | Lutron | Toggler | TG-600 |
| | | Lumea | LGCL-600 |
| | | Diva | DV-600 |
| | | Skylark | S-600 |
| | | Maestro | MAW-600 |
| | Legrand | Titan | CD703-PW |
| | | Harmony | D703-PTC |
| Harmony | | H703-PTC | |
| CFL/LED | Leviton | IllumaTech | IPL06 |
| | | Sureslide | 6674 |
| | | Decora | 6672 |
| | | Decora Slide | DSL06-1LZ |
| | Lutron | Skylark | CTCL-153 |
| | | Diva | DVCL-153PL |
| | | Maestro | MACL-153MLH |
| | | Skylark | SCL-153P |
| | | Toggler | TGCL-153PH |
| | Legrand | Harmony | DCL453-PTC |
| | | Radiant | RHCL453PW |
| | | Adorne Paddle | ADPD453LM2 |
| Electronic Low Voltage | Leviton | Vizia | VPE04 |
| | | IllumaTech | IPE04 |
| | | Decora | 6615-P |
| | Lutron | Skylark Countour | CTELV-303P |
| | | Diva | DVELV-300P |
| | | Maestro | MAELV-600 |
| | | Skylark | SELVB-300P |
| | Legrand | VIERTI | VTEL-600M-W |
| Scene Director | | SCELV | |
| Magnetic Low Voltage | Leviton | Vizia | VPM-06 |
| | | Decora | 6613-P |
| | Lutron | Maestro | MALV-600 |
| | Legrand | Harmony | DLV703-PW |
| | | Titan | CDLV703-PW |
| Smart Dimmer | Leviton | Decora Digital (Bluetooth) | DDMX1-BLZ |
| | Leviton | Decora Smart Z-Wave Technology | DZ6HD |
| | Leviton | Decora Smart WiFi Technology | DW1KD |
| | Lutron | Caseta Wireless smart dimmer Wi-Fi | PD-10NXD |
| | Lutron | Caseta Wireless smart dimmer Wi-Fi | PD-6WCL |
| | GE | Z WAVE | ZW3005 |
| Universal | Legrand | Adorne SofTap | ADTP703TU |
| | | Miro Decorator | DRD4-W |
| | | Harmony | H703PTUTC |
| | | Adorne Whisper | ADWR700MMTUW2 |
| | | Adorne Touch | ADTH700MMTUM2 |
| | Cooper | Decorator | DAL06P-C2-K-L |
| | | Skye | SAL06P-W-K-L |

*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.

†May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to fire.

were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

| Overall Rating | |
|------------------------------------|---|
| Not Compatible | One or more of the following observed: Major flickering at various points, significant audible noise, no dimming r |
| Bad | One or more of the following observed: Some flickering observed at various points, audible noise may be present |
| Good | One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which m light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise. |
| Best | Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBa), wide dimming ra |
| High End (H.E.) Dead Travel | Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is wh |
| Low End (L.E.) Dead Travel | |

Contact Information:

Bulbrite Industries Inc.
145 West Commercial Avenue
Moonachie, New Jersey 07074
PHONE: 1-800-528-5555
FAX: 1-800-441-7708
Email: ProductSupport@bulbrite.com
©2017 Bulbrite Industries Inc.
All Rights Reserved.

ide

ulated environment. Actual results may vary.

Lamps per Dimmer

| Overall Rating | Recommended Minimum | Maximum Tested* | Notes |
|----------------|---------------------|-----------------|-----------------------------------|
| Good | 1 | 6 | Minor flickering at LE with 4-6 |
| Good | 1 | 6 | Minor flickering at LE with 4-6 |
| Good | 1 | 6 | Minor flickering at LE with 2 |
| Best | 1 | 6 | Dims down to 1% |
| Best | 1 | 6 | Dims down to 1% |
| Best | 1 | 6 | Dims down to 1% |
| Best | 1 | 6 | Dims down to 1% |
| Bad | 5 | 6 | Dims down to 1% |
| Good | 4 | 6 | Dims down to 1% |
| Good | 4 | 6 | Dims down to 1% |
| Good | 4 | 6 | Dims down to 1% |
| Best | 1 | 6 | Dims down to 1% |
| Best | 1 | 6 | Dims down to 1% |
| Best | 1 | 6 | Dims down to 1% |
| Best | 1 | 6 | Dims down to 1% |
| Best | 1 | 6 | Dims down to 1% |
| Best | 1 | 6 | Dims down to 1% |
| Best | 1 | 6 | Dims down to 1% |
| Best | 1 | 6 | Dims down to 1% |
| Best | 1 | 6 | Dims down to 1% |
| Best | 1 | 6 | Dims down to 1% |
| Best | 1 | 6 | Dims down to 1% |
| Best | 1 | 6 | Dims down to 1% |
| Best | 1 | 6 | Dims down to 1% |
| Good | 1 | 6 | Minor flickering at LE with 1-6 |
| Good | 1 | 6 | Minor flickering at LE with 1-6 |
| Best | 1 | 6 | Dims down to 15% with 1-6 |
| Good | 1 | 6 | Minor flickering at LE with 1-6 |
| Good | 1 | 6 | Minor flickering at LE with 1-6 |
| Good | 1 | 6 | Minor flickering at LE with 1-6 |
| Good | 1 | 6 | Minor flickering at LE with 1-6 |
| Good | 1 | 6 | Minor flickering at LE with 1-6 |
| No compatible | 1 | 6 | Flickering from HE to LE with 1-6 |
| Good | 1 | 6 | Flickering at LE with 2 |
| Good | 1 | 6 | Flickering at Med with 1 |
| Not compatible | 1 | 6 | |
| Good | 1 | 6 | Dims down to 1% |
| Good | 1 | 6 | Flickering at Med with 2 |
| Best | 2 | 6 | Dims down to 1% |
| Best | 1 | 6 | Dims down to 1% |
| Best | 1 | 6 | Dims down to 1% |
| Good | 1 | 6 | Minor flickering at LE with 5 |
| Best | 2 | 6 | Dims down to 1% |
| Best | 2 | 6 | Dims down to 1% |
| Good | 3 | 6 | Dims down to 10% |
| Bad | 1 | 6 | Flickering from HE to LE with 1-6 |
| Not compatible | 1 | 6 | |
| Best | 1 | 6 | Dims down to 1% |
| Best | 1 | 6 | Dims down to 1% |
| Good | 1 | 6 | Flickering at LE with 1 |
| Good | 1 | 6 | Flickering at LE with 1 |

st turn on if they

ange, does not turn off.

; dimming not smooth.

eans there may be periods of time when the slider (or other form of control button) is moved without affecting the

inge - can dim down to 20% or less of light output.

en the slider can be moved without affecting the light level.