



### **BTI-MGBIC-GTX-OPC**

Telco® BTI-MGBIC-GTX Compatible TAA 10/100/1000Base-TX SFP Transceiver (Copper, 100m, RJ-45)

#### **Features**

- INF-8074 Compliance
- RJ-45 Connector
- Copper Media Type
- Commercial Temperature 0 to 70 Celsius
- Hot Pluggable
- Metal with Lower EMI
- Excellent ESD Protection
- RoHS Compliant and Lead Free



#### **Applications:**

- 1000Base Ethernet
- Access and Enterprise

#### **Product Description**

This Telco® BTI-MGBIC-GTX compatible SFP transceiver provides 10/100/1000Base-TX throughput up to 100m over a copper connection via a RJ-45 connector. It can operate at temperatures between 0 and 70C. This TX module supports 10/100/1000Base auto-negotiation and can be configured to fit your needs. Our transceiver is built to meet or exceed OEM specifications and is guaranteed to be 100% compatible with Telco®. It has been programmed, uniquely serialized, and tested for data-traffic and application to ensure that it will initialize and perform identically. All of our transceivers comply with Multi-Source Agreement (MSA) standards to provide seamless network integration. This transceiver is Trade Agreements Act (TAA) compliant. We stand behind the quality of our products and proudly offer a limited lifetime warranty.

OptioConnect's transceivers are RoHS compliant and lead-free.

### Absolute Maximum Ratings

| Parameter       | Symbol | Min. | Typ. | Max. | Unit | Notes |
|-----------------|--------|------|------|------|------|-------|
| Supply Current  | Is     |      | 320  | 375  | mA   | 1     |
| Input Voltage   | Vcc    | 3.13 | 3.3  | 3.47 | V    | 2     |
| Maximum Voltage | Vmax   |      |      | 4    | V    |       |
| Surge Current   | Isurge |      |      | 30   | mA   | 3     |

#### Notes:

1. 1.2W max power over full range of voltage and temperature. Power consumption and surge current are higher than the specified values in SFP MSA.
2. Referenced to GND
3. Hot plug above steady state current. Power consumption and surge current are higher than the specified values in SFP MSA.

### Recommended Operating Conditions

| Parameter             | Symbol | Min. | Typ. | Max. | Unit   | Notes |
|-----------------------|--------|------|------|------|--------|-------|
| Data Rate             | BR     | 10   |      | 1000 | Mb/sec | 3-5   |
| Distance Supported    | L      |      |      | 100  | m      | 1     |
| Operating Temperature | Top    | 0    |      | 85   | °C     |       |
| Storage Temperature   | Tsto   | -40  |      | 85   | °C     |       |

#### Notes:

1. Category 5 UTP. BER <10<sup>-12</sup>
2. Clock tolerance is +/- 50 ppm
3. By default, the GE-GB-P is a full duplex device in preferred master mode
4. Automatic crossover detection is enabled. External crossover cable is not required
5. 1000Base-T operation requires the host system to have an SGMII interface with no clocks, and the module PHY to be configured per Application Note AN-2036. With a SERDES that does not support SGMII, the module will operate at 1000Base-T only.

### Low-Speed Signals

| Parameter       | Symbol | Min.         | Typ. | Max.         | Unit | Notes |
|-----------------|--------|--------------|------|--------------|------|-------|
| SFP Output LOW  | VOL    | 0            |      | 0.5          | V    | 1     |
| SFP Output High | VOH    | Host_Vcc-0.5 |      | Host_Vcc+0.3 | V    | 1     |
| SFP Input LOW   | VIL    | 0            |      | 0.8          | V    | 2     |
| SFP Input HIGH  | VIH    | 2            |      | Vcc+0.3      | V    | 2     |

#### Notes:

1. 4.7k to 10k pull-up to Host\_Vcc, measured at host side of connector
2. 4.7k to 10k pull-up to Vcc, measured at SFP side of connector

### High-Speed Signals

| Parameter                      | Symbol   | Min. | Typ. | Max. | Unit | Notes |
|--------------------------------|----------|------|------|------|------|-------|
| Transmission Line-SFP          |          |      |      |      |      |       |
| Line Frequency                 | fL       |      | 125  |      | MHz  | 1     |
| TX Output impedance            | Zout, TX |      | 100  |      | Ohm  | 2     |
| Rx Input Impedance             | Zin, RX  |      | 100  |      | Ohm  | 2     |
| Host-SFP                       |          |      |      |      |      |       |
| Single ended data input swing  | Vinsing  | 250  |      | 1200 | mV   | 3     |
| Single ended data output swing | Voutsing | 350  |      | 800  | mV   | 3     |
| Rise/Fall Time                 | Tr,Tf    |      | 175  |      | Psec | 4     |
| Tx Input Impedance             | Zin      |      | 50   |      | Ohm  | 3     |
| Rx Output Impedance            | Zout     |      | 50   |      | Ohm  | 3     |

#### Notes:


1. 5-level encoding, per IEEE 802.3
2. Differential, for all Frequencies between 1MHz and 125MHz
3. Single ended
4. 20%-80%

## Pin Descriptions

| Pin | Symbol      | Name/Descriptions                                  | Ref. |
|-----|-------------|----------------------------------------------------|------|
| 1   | VeeT        | Transmitter Ground (Common with Receiver Ground).  | 1    |
| 2   | TX Fault    | Transmitter Fault. Not Supported                   |      |
| 3   | TDIS        | Transmitter Disabled. PHY disabled on high or open | 2    |
| 4   | MOD_DEF(2)  | Module Definition 2. Data line for serial ID       | 3    |
| 5   | MOD_DEF(1)  | Module Definition 1. Clock line for serial ID      | 3    |
| 6   | MOD_DEF(0)  | Module Definition 0. Grounded within the module    | 3    |
| 7   | Rate Select | No connection required                             |      |
| 8   | LOS         | Loss of Signal indication.                         | 4    |
| 9   | VeeR        | Receiver Ground (common with Transmitter ground)   | 1    |
| 10  | VeeR        | Receiver Ground (common with Transmitter ground)   | 1    |
| 11  | VeeR        | Receiver Ground (Common with Transmitter Ground).  | 1    |
| 12  | RD-         | Receiver Inverted DATA out. AC Coupled.            |      |
| 13  | RD+         | Receiver Non-inverted DATA out. AC Coupled.        |      |
| 14  | VeeR        | Receiver Ground (Common with Transmitter Ground).  | 1    |
| 15  | VccR        | Receiver Power Supply.                             |      |
| 16  | VccT        | Transmitter Power Supply.                          |      |
| 17  | VeeT        | Transmitter Ground (Common with Receiver Ground).  | 1    |
| 18  | TD+         | Transmitter Non-Inverted DATA in. AC Coupled.      |      |
| 19  | TD-         | Transmitter Inverted DATA in. AC Coupled.          |      |
| 20  | VeeT        | Transmitter Ground (Common with Receiver Ground).  | 1    |


### Notes:

1. Circuit ground is connected to chassis ground
2. PHY disabled on TDIS > 2.0V or open, enabled on TDIS <0.8V
3. Should be pulled up with 4.7k-10k Ohms on host board to a voltage between 2.0V and 3.6V. MOD\_DEF (0) pulls line low to indicate module is plugged in.
4. LVTTTL compatible with a maximum voltage of 2.5V. Not supported on GE-GB-P



Pin-out of connector Block on Host board

## Mechanical Specifications



## **OptioConnect**

### **Innovation for the Future of High-Speed Networking**

#### **Who We Are**

OptioConnect is reshaping the landscape of communication and high-speed networking through intelligent technology. With a core focus on cutting edge technology, we deliver smarter fiber optic solutions for enterprise networks, data centers, and next-gen telecom infrastructures.

#### **What We Do**

At OptioConnect, we fuse advanced engineering with intelligent automation to drive the future of networking. Our AI-integrated solutions are designed to optimize performance and streamline operations with:

- Superior Performance
- Network and traffic optimization
- Intelligent energy management
- Seamless OEM compatibility
- Scalable cost-efficiency

#### **Smarter Networks by Design**

Innovation isn't just a goal—it's our process. We embed AI and machine learning across our R&D and product lines, enabling adaptive performance, automated tuning, and faster deployment cycles. The result? Networks that don't just work—they learn, evolve, and outperform.

#### **Our Team**

Our engineers, data scientists, and network architects bring decades of experience and a future-focused mindset. We provide hands-on support with intelligent insights that turn complex challenges into simple solutions.

#### **Our Mission**

To deliver AI-enhanced connectivity that reduces cost, increases speed, and maximizes efficiency—empowering our partners to operate at the forefront of a rapidly evolving digital world.

#### **Let's Connect**

Discover how OptioConnect's intelligent infrastructure solutions can power your network's next leap forward.

[www.optioconnect.com](http://www.optioconnect.com) | [info@optioconnect.com](mailto:info@optioconnect.com)

