



### 02310QBJ-OPC

Huawei® 02310QBJ Compatible TAA 10GBase-BX SFP+ Transceiver (SMF, 1270nmTx/1330nmRx, 10km, LC, DOM, -40 to 85C)

#### Features

- SFF-8432 and SFF-8472 Compliance
- Simplex LC Connector
- Single-mode Fiber
- Industrial Temperature -40 to 85 Celsius
- Hot Pluggable
- Metal with Lower EMI
- Excellent ESD Protection
- RoHS Compliant and Lead Free



#### Applications:

- 10GBase-BX Ethernet
- 8x/10x Fibre Channel
- Access, Metro and Enterprise

#### Product Description

This Huawei® 02310QBJ compatible SFP+ transceiver provides 10GBase-BX throughput up to 10km over single-mode fiber (SMF) using a wavelength of 1270nmTx/1330nmRx via an LC connector. It is guaranteed to be 100% compatible with the equivalent Huawei® transceiver. This easy to install, hot swappable transceiver has been programmed, uniquely serialized and data-traffic and application tested to ensure that it will initialize and perform identically. Digital optical monitoring (DOM) support is also present to allow access to real-time operating parameters. This transceiver is Trade Agreements Act (TAA) compliant. We stand behind the quality of our products and proudly offer a limited lifetime warranty.

OptioConnect's transceivers are RoHS compliant and lead-free.

TAA refers to the Trade Agreements Act (19 U.S.C. & 2501-2581), which is intended to foster fair and open international trade. TAA requires that the U.S. Government may acquire only "U.S.-made or designated country end products.")



## Regulatory Compliance

- ESD to the Electrical PINs: compatible with MIL-STD-883E Method 3015.4.
- ESD to the LC Receptacle: compatible with IEC 61000-4-3.
- EMI/EMC: compatible with FCC Part 15 Subpart B Rules, EN55022:2010.
- Laser Eye Safety: compatible with FDA 21CFR, EN60950-1& EN (IEC) 60825-1, 2.
- RoHS: compliant with EU RoHS 2.0 directive 2015/863/EU.

## Absolute Maximum Ratings

| Parameter                  | Symbol           | Min. | Typ. | Max.              | Unit | Notes |
|----------------------------|------------------|------|------|-------------------|------|-------|
| Maximum Supply Voltage     | V <sub>cc</sub>  | -0.5 |      | 4.0               | V    | 1     |
| Storage Temperature        | T <sub>stg</sub> | -40  |      | 85                | °C   | 2     |
| Operating Case Temperature | T <sub>c</sub>   | -40  |      | 85                | °C   | 3     |
| Data Rate                  | DR               | 9.83 |      | 11.3              | Gbps | 4     |
| Bit Error Rate             | BER              |      |      | 10 <sup>-12</sup> |      |       |
| Supply Current             | I <sub>cc</sub>  |      | 200  | 350               | mA   | 1     |

## Notes:

1. For electrical power interface.
2. Ambient temperature.
3. Case temperature.
4. IEEE 802.3ae.

## Electrical Characteristics

| Parameter                                | Symbol                         | Min.            | Typ. | Max.                 | Unit | Notes |
|------------------------------------------|--------------------------------|-----------------|------|----------------------|------|-------|
| Power Supply Voltage                     | V <sub>cc</sub>                | 3.14            | 3.3  | 3.46                 | V    |       |
| Power Dissipation                        | P <sub>DISS</sub>              |                 | 0.65 | 1.2                  | W    |       |
| Transmitter                              |                                |                 |      |                      |      |       |
| Input Differential Impedance             | R <sub>IN</sub>                |                 | 100  |                      | Ω    |       |
| Differential Data Input Swing            | V <sub>IN,pp</sub>             | 180             |      | 700                  | mV   |       |
| Transmit Disable Voltage                 | V <sub>D</sub>                 | 2.0             |      | V <sub>cc</sub>      | V    |       |
| Transmit Enable Voltage                  | V <sub>EN</sub>                | V <sub>ee</sub> |      | V <sub>ee</sub> +0.8 | V    |       |
| Receiver                                 |                                |                 |      |                      |      |       |
| Differential Data Output Swing           | V <sub>out,pp</sub>            | 300             |      | 850                  | mV   |       |
| Data Output Rise Time/Fall Time (20-80%) | T <sub>r</sub> /T <sub>f</sub> | 28              |      |                      | ps   |       |
| LOS Assert                               | LOSA                           | 2               |      | Host_V <sub>cc</sub> | V    |       |
| LOS De-Assert                            | LOSD                           | V <sub>ee</sub> |      | V <sub>ee</sub> +0.5 | V    |       |

## Optical Characteristics

| Parameter                       | Symbol                                | Min. | Typ. | Max.  | Unit  | Notes |
|---------------------------------|---------------------------------------|------|------|-------|-------|-------|
| Transmitter                     |                                       |      |      |       |       |       |
| Output Optical Power            | Ptx                                   | -8.2 |      | 0.5   | dBm   | 1     |
| Optical Center Wavelength       | λC                                    | 1260 | 1270 | 1280  | nm    |       |
| Extinction Ratio                | ER                                    | 3.5  |      |       | dB    |       |
| Spectral Width (-20dB)          | Δλ                                    |      |      | 0.6   | nm    |       |
| Side-Mode Suppression Ratio     | SMSR                                  | 30   |      |       | dB    |       |
| Relative Intensity Noise        | RIN                                   |      |      | -128  | dB/Hz |       |
| Transmitter Dispersion Penalty  | TDP                                   |      |      | 3.2   | dB    |       |
| Launch Power of Off Transmitter | Poff                                  |      |      | -30   | dBm   | 1     |
| Transmitter Jitter              | According to IEEE 802.3ae Requirement |      |      |       |       |       |
| Receiver                        |                                       |      |      |       |       |       |
| Receiver Overload               |                                       | 0.5  |      |       | dBm   |       |
| Optical Center Wavelength       | λC                                    | 1320 | 1330 | 1340  | nm    |       |
| Receiver Sensitivity            | S                                     |      |      | -14.4 | dBm   | 2     |
| Receiver Reflectance            |                                       |      |      | -12   | dB    |       |
| LOS Assert                      | LOSA                                  | -30  |      |       | dBm   |       |
| LOS De-Assert                   | LOSD                                  |      |      | -17   | dBm   |       |
| LOS Hysteresis                  | LOSH                                  | 0.5  |      |       | dB    |       |

### Notes:

1. Average.
2. Average. Measured with worst ER: BER<10<sup>-12</sup> and 2<sup>31</sup>-1 PRBS.

## Pin Descriptions

| Pin | Symbol     | Name/Descriptions                                                | Notes |
|-----|------------|------------------------------------------------------------------|-------|
| 1   | VeeT       | Transmitter Ground. Common with receiver ground.                 | 1     |
| 2   | Tx_Fault   | Transmitter Fault.                                               | 2     |
| 3   | Tx_Disable | Transmitter Disable. Laser output disabled on "high" or "open."  | 3     |
| 4   | SDA        | 2-Wire Serial Interface Data.                                    | 4     |
| 5   | SCL        | 2-Wire Serial Interface Clock.                                   | 4     |
| 6   | MOD_ABS    | Module Absent. Grounded within the module.                       | 4     |
| 7   | RS0        | No connection required.                                          |       |
| 8   | LOS        | Loss of Signal indication. "Logic 0" indicates normal operation. | 5     |
| 9   | RS1        | No connection required.                                          | 1     |
| 10  | VeeR       | Receiver Ground. Common with transmitter ground.                 | 1     |
| 11  | VeeR       | Receiver Ground. Common with transmitter ground.                 | 1     |
| 12  | RD-        | Receiver Inverted Data Out. AC coupled.                          |       |
| 13  | RD+        | Receiver Non-Inverted Data Out. AC coupled.                      |       |
| 14  | VeeR       | Receiver Ground. Common with transmitter ground.                 | 1     |
| 15  | VccR       | Receiver Power Supply.                                           |       |
| 16  | VccT       | Transmitter Power Supply.                                        |       |
| 17  | VeeT       | Transmitter Ground. Common with receiver ground.                 | 1     |
| 18  | TD+        | Transmitter Non-Inverted Data In. AC coupled.                    |       |
| 19  | TD-        | Transmitter Inverted Data In. AC coupled.                        |       |
| 20  | VeeT       | Transmitter Ground. Common with receiver ground.                 | 1     |

## Notes:

1. Circuit ground is isolated from the chassis ground.
2. Tx\_Fault is the open collector output and should be pulled up with 4.7kΩ-10kΩ on the host board to a voltage between 2V and Vcc+0.3V.
3. Disabled: TDIS>2V or open. Enabled TDIS<0.8V.
4. Should be pulled up with the 4.7kΩ-10kΩ on the host board to a voltage between 2V and Vcc+0.3V.
5. LOS is open collector output and should be pulled with 4.7kΩ-10kΩ on the host board to a voltage between 2V and Vcc+0.3V. The logic "0" indicates normal operation, and the logic "1" indicates that the receiver signal is lost.

Transceiver Block Diagram



Electical Pad Layout

Top view



Bottom view



Mechanical Specifications



## **OptioConnect**

### **Innovation for the Future of High-Speed Networking**

#### **Who We Are**

OptioConnect is reshaping the landscape of communication and high-speed networking through intelligent technology. With a core focus on cutting edge technology, we deliver smarter fiber optic solutions for enterprise networks, data centers, and next-gen telecom infrastructures.

#### **What We Do**

At OptioConnect, we fuse advanced engineering with intelligent automation to drive the future of networking. Our AI-integrated solutions are designed to optimize performance and streamline operations with:

- Superior Performance
- Network and traffic optimization
- Intelligent energy management
- Seamless OEM compatibility
- Scalable cost-efficiency

#### **Smarter Networks by Design**

Innovation isn't just a goal—it's our process. We embed AI and machine learning across our R&D and product lines, enabling adaptive performance, automated tuning, and faster deployment cycles. The result? Networks that don't just work—they learn, evolve, and outperform.

#### **Our Team**

Our engineers, data scientists, and network architects bring decades of experience and a future-focused mindset. We provide hands-on support with intelligent insights that turn complex challenges into simple solutions.

#### **Our Mission**

To deliver AI-enhanced connectivity that reduces cost, increases speed, and maximizes efficiency—empowering our partners to operate at the forefront of a rapidly evolving digital world.

#### **Let's Connect**

Discover how OptioConnect's intelligent infrastructure solutions can power your network's next leap forward.

[www.optioconnect.com](http://www.optioconnect.com) | [info@optioconnect.com](mailto:info@optioconnect.com)

