## **Ceiling LED Chandelier**

**CH97358-UNV** 

INSTALLATION SHEET

## START FROM HERE

- Make sure **POWER** is **COMPLETELY OFF** at the fuse box
- Have your fixture installed by a qualified licensed electrician
- Prepare everything in a clear area
- · Wear gloves at all time during this installation
- · Read instructions carefully before you start assembly
- Keep this installation sheet for future reference

**Technical Support:** 1-855-855-8926

## Please Note:

- This Kuzco LED fixture comes with pre-wired LED module(s)
- Unless instructed, Do Not touch any part of the LED module(s) as any unnecessary contact with the module could cause permanent damage
- Use ELV (Electronic Low Voltage) or TRIAC type of dimmer for dimming application
- 120-277V input

- 1. Remove fixture from its original package.
- **2.** Separate mounting plate (1c) from canopy (2a) by removing canopy screws (2b).
- **3.** Determine hanging height of fixture by securing rods (2c) to canopy (2a) and to fixture body (3a)
- **4.** Attach mounting plate (1c) to electrical junction box (1a) using screws provided (1d) in hardware package.
- **5.** Make proper electrical connections (black to hot "L", white to neutral "N", ground to "GND", negative (black), positive (red) with wire nuts **(1b)** provided in hardware package.
- **6.** Attach canopy **(2a)** to mounting plate **(1c)** with canopy screws **(2b)**
- 1. Use DC jack (3b) to make connection and secure decorative arm with knurled nut (3c) and cover it with threaded cap (3d).
- **8.** Thread decorative glass sphere (3f) into pendant base (3e).

## Can Rotate Pendant Arms Up To 90°





