



145 West Commercial Ave.  
Moonachie, NJ 07074

### Dimmer Compatibility Guide

PLEASE NOTE: Compatibility is based upon testing conducted by the manufacturer in a lab simulated environment. Actual results may vary.

<b>Product Family Name:</b>	LED Flush Mount 7" Round & Square	773141	773142	773143
<b>Item Number:</b>	LED15DL7/927/WHRD//D	LED15DL7/930/WHRD//D	LED15DL7/940/WHRD//D	LED15DL7/927/SLRD//D
<b>Ordering Code:</b>	773144	773145	773146	773147
	LED15DL7/930/SLRD//D	LED15DL7/940/SLRD//D	LED15DL7/927/WHSQ//D	LED15DL7/930/WHSQ//D
	773148	773149	773150	773151
	LED15DL7/940/WHSQ//D	LED15DL7/927/SLSQ//D	LED15DL7/930/SLSQ//D	LED15DL7/940/SLSQ//D

	Manufacturer	Product	Model Number	Overall Rating	Recommended		Notes	
					Minimum	Maximum Tested*		
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	IlumaTech	IPI06	Best	1	6	Dims down to 10%	
		SureSlide	6633-P	Best	1	6	Dims down to 3%	
		Vizia	VPI06-1LZ	Good	4	6	Dims down to 5%	
	Lutron	Toggler	TG-600	Best	1	6	Dims down to 6%	
		Diva	DV-600	Best	1	6	Dims down to 3%	
		SkyLark	S-600	Best	1	6	Dims down to 5%	
	Legrand	Maestro	MAW-600	Good	6	6	Dims down to 5%	
		Titan	CD703-PW	Best	1	6	Dims down to 13%	
		Harmony	D703-PTC	Best	1	6	Dims down to 3%	
			Harmony	H703-PTC	Best	1	6	Dims down to 3%
	CFL/LED	Leviton	IlumaTech	IPI06	Best	1	6	Dims down to 1%
			SureSlide	6674	Best	1	6	Dims down to 5%
Decora			6672	Best	1	6	Dims down to 3%	
Lutron		SkyLark	CTCL-153	Best	1	6	Dims down to 0.1%	
		Diva	DVCL-153PL	Best	1	6	Dims down to 0.1%	
		Maestro	MAEL-153MLH	Best	1	6	Dims down to 4%	
Legrand		SkyLark	SCL-153P	Best	1	6	Dims down to 0.1%	
		Toggler	TGCL-153PH	Best	1	6	Dims down to 0.1%	
		Radio RA	RA2RR-6CL-PD	Best	1	6	Dims down to 4%	
			Harmony	DCL453-PTC	Best	1	6	Dims down to 5%
			Harmony	HCL453PTC	Best	1	6	Dims down to 7%
			Adorne Paddle	ADPD453LM2	Good	1	6	Dims down to 25%
Electronic Low Voltage	Leviton	Vizia	VPE04	Good	1	6	Dims down to 7%, flicker 25%-35%, flicker at 40% with 2	
		IlumaTech	IPE04	Good	1	6	Dims down to 5%, flicker at 60% with 1	
		Decora	6615-P	Bad	1	6	Dims down to 30%, flicker LE to Med with 1, flicker at Med with 2-3	
	Lutron	SkyLark Countour	CTELV-303P	Good	1	6	Dims down to 7%, flicker 25%-35% with 1-3	
		Diva	DVELV-300P	Good	1	6	Dims down to 7%, flicker 25%-35% with 1-3	
		Maestro	MAELV-600	Good	1	6	Dims down to 4%, minor flicker 20%-35% with 1-3	
	Legrand	SkyLark	SELVB-300P	Good	1	6	Dims down to 7%, flicker 25%-35% with 1-3	
		VIERTI	VTEL-600M-W	Best	1	6	Dims down to 5%	
		Scene Director	SCELV	Good	1	6	Dims down to 20%	
	Magnetic Low Voltage	Leviton	Vizia	VPM-06	Good	4	6	Dims down to 4%
			Decora	6613-P	Best	1	6	Dims down to 3%
		Lutron	Maestro	MALV-600	Good	6	6	Dims down to 3%
Harmony			DLV703-PW	Best	1	6	Dims down to 1%	
		Titan	CDLV703-PW	Best	1	6	Dims down to 10%	
Smart Dimmer	Leviton	Decora Digital (Bluetooth)	DDMX1-BLZ	Best	1	6	Dims down to 10%	
	Leviton	Decora Smart Wi-Fi	DX6HD-1B2	N/A				
	Insteon	SwitchIn Remote Control dimmer		N/A				
	Lutron	Caseta Wireless smart dimmer Wi-Fi	PD-6WCL	Best	1	6	Dims down to 4%	
	Legrand	Adorne touch Wi-Fi TRU Universal	ADTH700RMTUW1	N/A				
	Legrand	Adorne Sof Tap Wi-Fi TRU Universal	ADTP700RMTUW1	N/A				
Universal	Legrand	GE	Z WAVE	Best	1	6	Dims down to 1%	
		Adorne SoftTap	ADTP702TU	Best	1	6	Dims down to 11%	
		Miro Decorator	DRD4-W	Good	2	6	Flash at 5% with 1, dims down to 10% with 2-6	
		Harmony	H703P/UTC	Best	1	6	Dims down to 15%	
		Adorne Whisper	ADWR700MMTUW2	Best	1	6	Dims down to 1%	
	Cooper	Adorne Touch	ADTH700MMTUW2	Best	1	6	Dims down to 1%	
		Decorator	DAL06P-CZ-K-L	Best	1	6	Dims down to 10%	
		Skye	SAL06P-W-K-L	Best	1	6	Dims down to 10%, set the dial above 10% to avoid flicker	

\*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.  
 †May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

<b>Overall Rating</b>	
<b>Not Compatible</b>	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.
<b>Bad</b>	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.
<b>Good</b>	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.
<b>Best</b>	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dba), wide dimming range - can dim down to 20% or less of light output.
<b>High End (H.E.) Dead Travel</b>	
<b>Low End (L.E.) Dead Travel</b>	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.

**CONTACT INFORMATION:**  
 Bulbrite Industries Inc.  
 145 West Commercial Avenue  
 Moonachie, New Jersey 07074  
 PHONE: 1-800-528-5555  
 FAX: 1-800-441-7108  
 Email: ProductSupport@bulbrite.com  
 ©2017 Bulbrite Industries Inc.  
 All Rights Reserved.