

Dimmer Compatibility Guide

Product Family Name: Item Number: Ordering Code:

LED Flush Mount 9" Round & Square 773152 LED20DL/9/927/WHRD/I/D 773156 LED20DL/9/930/SLRD/I/D 773160 LED20DL/9/940/WHSQ/I/D LED20DL/9/930/WHRD/J/D 773157 LED20DL/9/940/SLRD/J/D 773161 LED20DL/9/927/SLSQ/J/D LED20DL/9/940/WHRD/J/D 773158 LED20DL/9/927/WHSQ/J/D 773162 LED20DL/9/930/SLSQ/J/D LED20DL/9/927/SLRD/J/D 773159 LED20DL/9/930/WHSQ/J/D 773163 LED20DL/9/940/SLSQ/J/D

	LED20DL/9/940/WHSQ/J/D	LED20DL/9/927/SLSQ/J/D	LED20DL/9/930/SLSQ/J/D	LED20DL/9/940/SLSQ/J/D	_		
	Manufacturer	Product	Model Number	Overall Rating	Recommended	Maximum	Notes
	wanuracturer				Minimum	Tested*	
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	IllumaTech	IPI06 6633-P	Best	1	6	Dims down to 11%
		SureSlide		Best	1	6	Dims down to 3%
		Vizia	VPI06-1LZ	Good	3	6	Dims down to 6%, lit effect when off when only using 1-2
	Lutron	Toggler	TG-600	Best	1	6	Dims down to 11%
		Diva	DV-600	Best	1	6	Dims down to 2%
		Skylark	S-600	Best	1	6	Dims down to 3%
		Maestro	MAW-600	Good	4	6	Dims down to 2%, lit effect when off when only using 1-3
	Legrand	Titan	CD703-PW	Best	1	6	Dims down to 16%
		Harmony	D703-PTC	Best	1	6	Dims down to 1%
		Harmony	H703-PTC	Best	1	6	Dims down to 4%
CFI/LED	Leviton	IllumaTech	IPL06	Best	1	6	Dims down to 1%
		Sureslide	6674	Best	1	6	Dims down to 7%
		Decora	6672	Best	1	6	Dims down to 5%
	Lutron	Skylark	CTCL-153	Best	1	6	Dims down to 0.3%
		Diva	DVCL-153PL	Best	1	6	Dims down to 0.3%
		Maestro	MACL-153MLH	Best	1	6	Dims down to 7%
		Skylark	SCL-153P	Best	1	6	Dims down to 0.3%
		Toggler	TGCL-153PH	Best	1	6	Dims down to 0.3%
		Radio RA	RA2RR-6CL-PD	Best	1	6	Dims down to 5%
	Legrand	Harmony	DCL453-PTC	Best	1	6	Dims down to 7%
		Harmony	HCL453PTC	Best	1	6	Dims down to 10%
		Adorne Paddle	ADPD453LM2	Good	1	6	Dims down to 30%
							•
Electronic Low Voltage	Leviton	Vizia	VPE04	Best	1	6	Dims down to 10%
		IllumaTech	IPE04	Best	1	6	Dims down to 7%
		Decora	6615-P	Good	1	6	Dims down to 30%
	Lutron	Skylark Countour	CTELV-303P	Best	1	6	Dims down to 8%,
		Diva	DVELV-300P	Best	1	6	Dims down to 8%.
		Maestro	MAELV-600	Best	1	6	Dims down to 8%
		Skylark	SELVB-300P	Best	1	6	Dims down to 8%
		VIERTI	VTEL-600M-W	Best	1	6	Dims down to 9%
	Legrand	Scene Director	SCELV	Best	1	6	Dims down to 20%
						-	
Magentic Low Voltage	Leviton	Vizia	VPM-06	Good	3	6	Dims down to 6%, lit effect when off when only using 1-2
		Decora	6613-P	Best	1	6	Dims down to 4%
	Lutron	Maestro	MALV-600	Good	4	6	Dims down to 6%
		Harmony	DLV703-PW	Best	1	6	Dims down to 2%, lit effect when off when only using 1-3
	Legrand	Titan	CDLV703-PW	Best	1	6	Dims down to 13%
	Legianu	inon	1000703111	best	1		Dilli down to 13/4
	Leviton	Decora Digital (Bluetooth)	DDMX1-BLZ	Best	1	6	Dims down to 15%
Smart Dimmer	Leviton	Decora Smart Wi-Fi	DX6HD-1BZ	N/A	1		Dilli down to 13/4
	Insteon	SwitchLin Remote Control dimmer	5,01,5-102	N/A N/A			
	Lutron	Caseta Wireless smart dimmer Wi-Fi	PD-6WCL	Best	1	6	Dims down to 8%
		Adorne touch Wi-Fi TRU Universal	ADTH700RMTUW1	N/A	1	- 0	Dillis down to 676
	Legrand Legrand	Adorne Sof Tap Wi-Fi TRU Universal	ADTP700RMTUW1	N/A N/A			
	Legrand	Z WAVE	ZW3005	N/A Best		6	Diese deute to 20/
	GE	Z WAVE	ZW3003	Best	1	ь	Dims down to 2%
Universal	Legrand	Adorne SofTap	ADTP703TU	Best	1	6	Dims down to 15%
		Miro Decorator	DRD4-W	Good	2	6	Dims down to 2%, minor flicker at LE with 1-3
		Harmony	H703PTUTC	Best	1	6	Dims down to 20%
		Adorne Whisper	ADWR700MMTUW2	Best	1	6	Dims down to 1%
	Cooper	Adorne Touch	ADTH700MMTUM2	Best	1	6	Dims down to 1%
		Decorator	DAL06P-C2-K-L	Best	1	6	Dims down to 20%
		Skye	SAL06P-W-K-L	Best	1	6	Dims down to 2%,

*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.

1 May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating						
Not Compatible	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.					
Bad	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.					
	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel a minor and most of the time not visible. Minor audible noise.					
Best	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBa), wide dimming range - can dim down to 20% or less of light output.					
High End (H.E.) Dead Travel	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.					
Low End (L.E.) Dead Travel	beter mines now much, it any, dead traver exists at the top and bottom of the diminer's range. Dead traver is when the shoet can be moved without an exting the light rever.					