BULBRITE turn life on

5 West Commercial Ave.

Dimmer Compatibility Guide

Product Family Name: tem Number

LED14RECJBOXDL/6/5CCT/827-850/WHRD/D Ordering Code: em Number

773302

Ordering Code: Lamps per Dimmer Manufactu Model N all R Mir IllumaTech IPI06 Good Minor flickering at LE with 1-6 1 6 Leviton SureSlide 6633-P Rest Dims down to 1% Vizia VPI06-1LZ Good Dims down to 1% Toggler TG-600 Best Dims down to 1% 1 6 ncandescent/Halogen (Triac/Pha Cut/Leading Edge Dimme<u>rs</u>) Lumea LGCL-600 Best Dims down to 1% Lutron Diva DV-600 Off at LF with 1-6 Skylark Off at LE with Good Maestro MAW-600 Good 4 6 Dims down to 1% Minor flickering at MID with 1-6, dims down to 10% Titan CD703-PW Good Legrand Off at LE with flickering with 1-6 Harmony D703-PTC Good 1 6 Harmon H703-PTC Good Off at LE with 1 IllumaTech IPL06 Good Off at LE with 1 Leviton Sureslide 6674 Best Dims down to 1% Decora 6672 Best Dims down to 1% 1 6 DSL06-1LZ Best Decora Slic Dims down to 1% Skylark Sunnata CTCL-153 Best Best Dims down to 1% STCL - 153 Dims down to 3% Diva DVCL-153PL Bad It turn on with a flash with 3-6 CFL/LED Lutron Maestro MACL-153MLH Best Dims down to 1% It turn on with a flash with 3-6 Skylark SCL-153P Bad 6 Toggler TGCL-153PH Best Dims down to 1% Radio RA RA2RR-6CL-PD Best Dims down to 1% 1 6 DCL453-PTC Best Dims down to 1% Harmony 6 Legrand Radiant RHCL453PV Best Dims down to 1% Adorne Paddle ADPD453LM2 Good 6 Dims down to 10% 1 VPE04 Best Dims down to 5% Leviton IllumaTeo It slide with no smooth dimming, dims down to 59 IPE04 Decora 6615-P Bad Only dims down to 25% 6 Skylark Co CTELV-303P Dims down to 5% Best 6 Electronic Low Voltage Diva DVELV-300P Best 1 6 Dims down to 5% Lutron Maestr MAELV-600 Dims down to 5% Skylark SELVB-300F Best Dims down to 5% Best Good VIERTI VTEL-600M-W Dims down to 5% dims down to 15%, Flickering at HE with 1 Legrand Scene Directo SCELV VPM-06 Vizia Good Dims down to 1% Leviton Decora 6613-P Good Off at LE with 1, dims down to 1% 6 Magnetic Low Voltage Lutron MALV-600 Not compatible Not turn on with 1-6 Maestro Harmony DLV703-PW Good Off at LE with 1. dims down to 1% 6 CDLV703-PW Legrand Titan Best Dims down to 5% Leviton Decora Digital (Bluetooth) DDMX1-BLZ Dims down to 5% Leviton Decora Smart Z-Wave Technology DZ6HD Best 6 Dims down to 5% Decora Smart WiFi Technology Leviton DW1KD Rest Dims down to 59 Best PD-10NX Lutron Caseta Wireless smart dimmer Wi-F Dims down to 3% Lutron Caseta Wireless smart dimmer Wi-Fi PD-6WCL Bad Flash with 3-6 ZW3005 Z WAVE dims down to 1% GE Best 6 ADTP703TU Adorne SofTap Dims down to 10% Best Miro Decorator DRD4-W Bad 6 Dims down to 1%, ghosting with 1 1 Legrand Harmony H703PTUTC Dims down to 15% Good Universal Adorne Whisper ADWR700MMTUW2 Best 1 6 Dims down to 1% Adorne Touch ADTH700MMTUM ms down to 19 Dims down to 1%, flickering at MID with 1-6 Decorator DAL06P-C2-K-L Bad Cooper Skve SAL06P-W-K-L Bad Dms down to 1%, flickering at MID with 1-6 6 Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacture tMay experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they vere initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level. Overall Rating One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off. Not Compatible

One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth. One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise. Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBa), wide dimming range - can dim down to 20% or less of light outpu ost High End (H.E.) Dead Travel Low End (L.E.) Dead Travel Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level

Contact Information: Bulbrite Industries Inc. 145 West Commercial Avenue Woonachie, New Jersey 07074 PHONE: 1-800-528-5555 AX: 1-800-441-7708 - ____ 441-7/08 I: ProductSupport@bulbrite.com 17 Bulbrite Industries Inc. ghts Reserved.