

145 West Commercial Ave. Moonachie, NJ 07074

Dimmer Compatib

PLEASE NOTE: Compatibility list is based upon testing conducted by the manufact

Product Family Name:

Item Number: 774260 774261

Ordering Code: LED11A19/PF75W/927/D/1P LED11A19/PF75W/930/D/1P

Item Number: Ordering Code:

	Manufacturer	Product	Model Number
		IllumaTech	IPI06
	Leviton	SureSlide	6633-P
		Vizia	VPI06-1LZ
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)		Toggler	TG-600
		Lumea	LGCL-600
	Lutron	Diva	DV-600
		Skylark	S-600
		Maestro	MAW-600
	Legrand	Titan	CD703-PW
		Harmony	D703-PTC
		Harmony	H703-PTC
			•
	Leviton	IllumaTech	IPL06
		Sureslide	6674
		Decora	6672
		Decora Slide	DSL06-1LZ
		Skylark	CTCL-153
		Diva	DVCL-153PL
CFL/LED		Maestro	MACL-153MLH
	Lutron	Skylark	SCL-153P
		Toggler	TGCL-153PH
		Radio RA	RA2RR-6CL-PD
		Harmony	DCL453-PTC
	Legrand	Harmony	HCL453PTC
	, and the second	Adorne Paddle	ADPD453LM2
		•	•
		Vizia	VPE04
	Leviton	IllumaTech	IPE04
		Decora	6615-P
		Skylark Countour	CTELV-303P
Electronic Low Voltage	Lutron	Diva	DVELV-300P
		Maestro	MAELV-600
		Skylark	SELVB-300P
		VIERTI	VTEL-600M-W
	Legrand	Scene Director	SCELV
	Leviton	Vizia	VPM-06
		Decora	6613-P
Magentic Low Voltage	Lutron	Maestro	MALV-600
		Harmony	DLV703-PW
	Legrand	Titan	CDLV703-PW
		In	IDDANYA DI T
	Leviton	Decora Digital (Bluetooth)	DDMX1-BLZ
	Leviton	Decora Smart Z-Wave Technology	DZ6HD
Smart Dimmer	Leviton	Decora Smart WiFi Technology	DW1KD
	Lutron		PD-10NXD
	Lutron		PD-6WCL
	GE	Z WAVE	ZW3005
Universal	Legrand	Adorne SofTap	ADTP703TU
		Miro Decorator	DRD4-W
		Harmony	H703PTUTC ADWR700MMTUW2
		Adorne Whisper Adorne Touch	ADTH700MMTUM2
		Decorator	DAL06P-C2-K-L
	Cooper		SAL06P-C2-K-L
		Skye	SALUUF-W-N-L

^{*}Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.
†May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the

were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating			
Not Compatible	ible One or more of the following observed: Major flickering at various points, significant audible noise, no		
Bad	One or more of the following observed: Some flickering observed at various points, audible noise may k		
Good	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise		
Best	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBa), wide d		
High End (H.E.) Dead Travel	Determines how much if any dead travel exists at the ten and bettem of the dimmer's range. Dead tr		
Low End (L.E.) Dead Travel	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel		

Contact Information:

Bulbrite Industries Inc. 145 West Commercial Avenue Moonachie, New Jersey 07074 PHONE: 1-800-528-5555 FAX: 1-800-441-7708

Email: ProductSupport@bulbrite.com © 2017 Bulbrite Industries Inc. All Rights Reserved.

ility Guide turer in a lab simulated environment. Actual results may vary.

Lamps per Dimmer

Overall Rating	Recommended Minimum	Maximum Tested*	Notes
Best	1	6	Dims down to 1%
Best	1	6	Dims down to 1%
Good	2	6	Dims down to 1%
Best	1	6	Dims down to 1%
Best	1	6	Dims down to 1%
Best	1	6	Dims down to 1%
Best	1	6	Dims down to 1%
Bad	5	6	Dims down to 1%
Good	2	6	Dims down to 1%, flicker at Med with 2
Good	1	6	Dims down to 1%, flicker at Med with 1-2
Good	1	6	Dims down to 1%, flicker at Med with 1-2
Best	1	6	Dims down to 1%
Best	1	6	Dims down to 1%
Best	1	6	Dims down to 1%
Best	1	6	Dims down to 1%
Best	1	6	Dims down to 1%
Best	1	6	Dims down to 1%
Best	1	6	Dims down to 1%
Best	1	6	Dims down to 1%
Best	1	6	Dims down to 1%
Best	1	6	Dims down to 1%
Best	1	6	Dims down to 1%
Best	1	6	Dims down to 1%
Best	1	6	Dims down to 1%
Doot	1		Dina dann ta 40/
Best	1	6	Dims down to 1% Dims down to 1%
Best Best	1	6 6	Dims down to 1% Dims down to 10%
	1	6	Dims down to 1%
Best Best	1	6	Dims down to 1%
Best	1	6	Dims down to 1%
Best	1	6	Dims down to 1%
Best	1	6	Dims down to 1%
Best	1	6	Dims down to 1%
Dest	1	Ü	Dinis down to 170
Best	1	6	Dims down to1%
Best	1	6	Dims down to 1%
Not compatible	1	6	Not turn with 1-6
Best	1	6	Dims down to 1%
Bad	1	6	Dims down to 1%, flicker at Med with 1-2, flicker at LE with 3-6
Dad	-	•	Dinib do will to 170, moner de med man 1 2, moner de 12 mono o
Good	1	6	Dims down to 1%, minor flicker at LE with 1-6
Good	1	6	Dims down to 1%, minor flicker at LE with 1-6
Good	1	6	Dims down to 1%, minor flicker at LE with 1-6
Good	1	6	Dims down to 1%, minor flicker at LE with 1-6
Good	1	6	Dims down to 1%, minor flicker at LE with 1-6
Good	1	6	Dims down to 1%, minor flicker at LE with 1-6
Best	1	6	Dims down to 1%
Good	1	6	Dims down to 1%, minor flicker at LE with 1-6
Bad	1	6	Dims down to 10%, flicker at LE with 1-4
Best	1	6	Dims down to 1%
Best	1	6	Dims down to 1%
Best	1	6	Dims down to 1%
Best	1	6	Dims down to 1%
-			

dimming range, does not turn off.
pe present, dimming not smooth.
, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the
limming range - can dim down to 20% or less of light output.
avel is when the slider can be moved without affecting the light level.