











## Dimmer Compatibility Guide

776626 LEDSB11/27K/FIL/E12/3 776627 776628 776629 776612
LEDSB11/30K/RIJ/E12/3 LEDSCA10/27K/FIL/E12/3 LEDSCA10/30K/RIJ/E12/3 LED4G16/27K/RIJ/M/3

			Lamps per Dimmer					
	Manufacturer	Product	Model Number	Overall Rating	Recommended Minimum	Maximum Tested	Notes	
	Leviton	IllumaTech	IPI06	Best	1	6	Dims down to 0.1%	
		SureSlide	6633-P	Best	1	6	Dims down to 0.1%	
		Vizia	VPI06-1LZ	Good	2	6	Dims down to 0.1%, minor flicker with 1-6	
	Lutron	Toggler	TG-600	Best	1	6	Dims down to 0.1%	
ncandescent/Halogen (Triac/Phase		Diva	DV-600	Best	1	6	Dims down to 0.1%	
Cut/Leading Edge Dimmers)	Lation	Skylark	S-600PH	Best	1	6	Dims down to 0.1%	
-		Maestro	MAW-600	Good	4	6	Dims down to 0.2%	
		Titan	CD703-PW	Good	4	6	Dims down to 0.1%, flicker at LE with 4-5	
	Legrand	Harmony	D703-PTC	Good	1	6	Dims down to 0.1%, flicker at Med with 1-3	
		Harmony	H703-PTC	Good	1	6	Dims down to 0.1%, flicker at HE with 1	
•				•				
		IllumaTech	IPL06	Good	1	6	Dims down to 0.1%, minor flicker at LE with 1-4	
	Leviton	Sureslide	6674	Good	1	6	Dims down to 0.1%, minor flicker at LE with 1-6	
		Decora	6672	Best	1	6	Dims down to 0.1%.	
		Skylark	CTCL-153	Best	1	6	Dims down to 0.1%	
		Diva	DVCL-153PL	Good	1	6	Dims down to 0.1%, minor flicker at LE with 1-6	
CEL (UED		Maestro	MACL-153MLH	Best	1	6	Dims down to 0.1%	
CFL/LED	Lutron	Skylark	SCL-153P	Best	1	6	Dims down to 0.1%	
		Toggler	TGCL-153PH	Good	1	6	Dims down to 0.1%, minor flicker at LE with 1-6	
		Radio RA	RA2RR-6CL-PD	Best	1	6	Dims down to 0.1%	
		Harmony	DCL453-PTC	Good	2	6	Dims down to 0.1%, minor flicker at LE & Med with 1 & Med1-2	
	Legrand	Harmony	HCL453PTC	Good	2	6	Dims down to 0.1%	
		Adorne Paddle	ADPD453LM2	Good	2	6	Dims down to 0.1%	
		Padriic I doube	NOI DESCRIE	GOOD .	*		Dillio down to 0.179	
		Vizia	VPE04	Good	1	6	Dims down to 0.1%, minor flicker at LE with 1-6	
	Leviton	IllumaTech	IPE04	Good	1	6	Dims down to 0.1%, minor flicker at LE with 1-6	
	Econon	Decora	6615-P	Good	1	6	Dims down to 10%, minor flicker at LE with 1-6	
_		Skylark Countour	CTELV-303P	Good	1	6	Dims down to 0.1%, minor flicker at LE with 1-6	
Electronic Low Voltage		Diva	DVELV-300P	Good	1	6	Dims down to 0.1%, minor flicker at LE with 1-6	
	Lutron	Maestro	MAELV-600	Good	1	6	Dims down to 0.1%, minor flicker at LE with 1-6	
		Skylark	SELVB-300P	Good	1	6	Dims down to 0.1%, minor flicker at LE with 1-6	
		VIERTI	VTEL-600M-W	Good	1	6	Dims down to 10%, minor flicker at LE with 1-6	
			SCELV SCELV	Good	1		Dims down to 10%, minor flicker at LE with 1-6  Dims down to 10%, minor flicker at LE with 1-6	
	Legrand	Scene Director	SCELV	Good	1	6	Dims down to 10%, minor flicker at LE with 1-6	
		Vizia	VPM-06	Good	3	6	Dims down to 1%. flicker at HE with 1-3	
Magentic Low Voltage	Leviton		6613-P					
		Decora		Good	1	6	Dims down to 1%, flicker at HE with 1-3	
Mageritic tow voltage	Lutron	Maestro	MALV-600	Bad	5	6	Dims down to 1%	
		Harmony	DLV703-PW	Good	1	6	Dims down to 10%, flicker at LE with 1-6	
	Legrand	Titan	CDLV703-PW	Good	1	6	Dims down to 10%, flicker at LE with 1-6	
_			1			_		
	Leviton	Decora Digital (Bluetooth)	DDMX1-BLZ	Good	1	6	Dims down to 0.1%, minor flicker at LE with 1-6	
	Leviton	Decora Smart Wi-Fi	DX6HD-1BZ	N/A				
Smart Dimmer	Insteon	SwitchLin Remote Control dimmer		N/A				
	Lutron	Caseta Wireless smart dimmer Wi-Fi	PD-6WCL	Good	1	6	Dims down to 0.1%, minor flicker at LE with 1-6	
	Legrand	Adorne touch Wi-Fi TRU Universal	ADTH700RMTUW1	N/A				
	Legrand	Adome Sof Tap Wi-Fi TRU Universal	ADTP700RMTUW1	N/A				
	GE	Z WAVE	ZW3005	Good			Dims down to 10%, minor flicker at LE with 2-6	
				1				
		Adome SofTap	ADTP703TU	Best	1	6	Dims down to 1%	
		Miro Decorator	DRD4-W	Good	1	6	Dims down to 1%, flicker at LE with 1-3	
	Legrand	Harmony	H703PTUTC	Best	1	6	Dims down to 1%	
Universal		Adome Whisper	ADWR700MMTUW2	Best	1	6	Dims down to 0.1%	
		Adome Touch	ADTH700MMTUM2	Best	1	6	Dims down to 0.1%	
	Cooper	Decorator	DAL06P-C2-K-L	Good	1	6	Dims down to 1%, minor flicker at LE & Med with 1-6	
	cooper	Skye	SAL06P-W-K-L	Good	1	6	Dims down to 1%, minor flicker at LE & Med with 1-6	

\*Maximum Tested (Lumps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer annufacturer

\*May experience "pop on", lights cannot be turned on immediately to their minimum level. The sider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the sider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating						
Not Compatible	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.					
Bad	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.					
Good	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the tim not visible. Minor audible noise.					
Best	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBa), wide dimming range - can dim down to 20% or less of light output.					
High End (H.E.) Dead Travel	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.					
Law Ford (L. F.) Dood Towns	Determines now much, in any, dead travel exists at the top and bottom of the diffinite sharinge. Dead travel is when the shoet can be moved without affecting the light level.					