

Dimmer Compatibility Guide

776860 LED3CA10/27K/FIL/M/3 776772 LED3B11/27K/FIL/M/3

Lamps per Dimmer

	Manufacturer	Product	Model Number	Overall Rating	Recommended Minimum	Maximum Tested*	Notes
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)		IllumaTech	IPI06	Good	1	6	Dims 1%,flicker HE&LEwith1,minor flicker below 15%
	Leviton	SureSlide	6633-P	Good	1	6	Dims 1%,minor flicker below 15%
		Vizia	VPI06-1LZ	Good	2	6	Dims 1%,flicker HE&LEwith1,minor flicker below 20%
	Lutron	Toggler	TG-600	Good	1	6	Dims 1%,flicker LE with1, minor flicker below 15%
		Diva	DV-600	Good	1	6	Dims 1%,flicker LE with1,minor flicker below 15%
		Skylark	S-600	Good	1	6	Dims 1%,flicker LE with1,minor flicker below 15%
		Maestro	MAW-600	Bad	5	6	Dims 1%,flicker LE with1,minor flicker below 20%
	Legrand	Titan	CD703-PW	Bad	4	6	Dims 1%,flicker LE with1,minor flicker below 10%
		Harmony	D703-PTC	Good	1	6	Dims 1%,flicker Med & LE with1 -3, minor flicker below 10%
		Harmony	H703-PTC	Good	1	6	Dims 1%,flicker LE with 1-3, minor flicker below 10%
		•	·	•	•		
	Leviton	IllumaTech	IPL06	Good	1	6	Dims down to 1%, minor flicker below 20%
		Sureslide	6674	Good	1	6	Dims down to 1%, minor flicker below 20%
		Decora	6672	Good	1	6	Dims down to 1%, minor flicker below 20%
		Decora Slide	DSL06-1LZ	Good	1	6	Dims down to 1%, minor flicker below 20%
	Lutron	Skylark	CTCL-153	Best	1	6	Dims down to 1%, adjust dimming above 20% to advoid flicker at LE
CFL/LED		Diva	DVCL-153PL	Best	1	6	Dims down to 1%, adjust dimming above 20% to advoid flicker at LE
		Maestro	MACL-153MLH	Best	1	6	Dims down to 1%, adjust dimming above 20% to advoid flicker at LE
		Skylark	SCL-153P	Best	1	6	Dims down to 1%, adjust dimming above 20% to advoid flicker at LE
		Toggler	TGCL-153PH	Best	1	6	Dims down to 1%, adjust dimming above 20% to advoid flicker at LE
		Radio RA	RA2RR-6CL-PD	Best	1	6	Dims down to 1%, adjust dimming above 20% to advoid flicker at LE
	Legrand	Harmony	DCL453-PTC	Best	1	6	Dims down to 1%, adjust dimming above 20% to advoid flicker at LE
		Harmony	HCL453PTC	Best	1	6	Dims down to 1%, adjust dimming above 20% to advoid flicker at LE
		Adorne Paddle	ADPD453LM2	Best	1	6	Dims down to 6%
Electronic Low Voltage	Leviton	Vizia	VPE04	Good	1	6	Dims down to 1%, minor flicker at LE
		IllumaTech	IPE04	Good	1	6	Dims down to 1%, minor flicker at LE
		Decora	6615-P	Good	1	6	Dims down to 1%, minor flicker at LE
	Lutron	Skylark Countour	CTELV-303P	Best	1	6	Dims down to 1%,
		Diva Maestro	DVELV-300P MAELV-600	Best Best	1	6	Dims down to 1%, Dims down to 1%.
				***	1	6	
		Skylark VIERTI	SELVB-300P VTEL-600M-W	Best Best	1	6	Dims down to 1%, Dims down to 1%.
	Legrand	Scene Director	SCELV SCELV	Good	1	6	Dims down to 1%, Dims down to 1%, minor flicker below 20%
	Legranu	Scelle Director	SCELV	9000	1	0	Diffis down to 1/6, fillifor flicker below 20/6
Magentic Low Voltage	Leviton	Vizia	VPM-06	Bad	2	6	Dims down to 1%. flicker at LE with 2-6. flicker at Med with 3
		Decora	6613-P	Bad	1	6	Dims down to 1%, flicker at LE with 1-6, flicker Med with 2&3
	Lutron	Maestro	MALV-600	Bad	5	6	Dims down to 1%, flicker at LE with 1-6, flicker with 26.5
	Eud Oil	Harmony	DLV703-PW	Bad	1	6	Dims down to 1%, flicker at LE with 3-6,
	Legrand	Titan	CDLV703-PW	Bad	1	6	Dims down to 1%, flicker at LE with 1, flicker at HE & LE with 2
	8				-	-	
Smart Dimmer	Leviton	Decora Digital (Bluetooth)	DDMX1-BLZ	Good	1	6	Dims down to 1%, flicker at LE below 20%
	Leviton	Decora Smart Z-Wave Technology	DZ6HD	Good	1	6	Dims down to 1%, licker at LE below 20%
	Lutron	Caseta Wireless smart dimmer Wi-Fi	PD-10NXD	Good	1	6	Dims down to 1%, licker at LE below 20%
	Lutron	Caseta Wireless smart dimmer Wi-Fi	PD-6WCL	Good	1	6	Dims down to 1%, licker at LE below 20%
	Legrand	Adorne touch Wi-Fi TRU Universal	ADTH700RMTUW1				
	Legrand	Adorne Sof Tap Wi-Fi TRU Universal	ADTP700RMTUW1				
	GE	Z WAVE	ZW3005	Good	1	6	Dims down to 1%, licker at LE below 20%
Universal	Legrand	Adorne SofTap	ADTP703TU	Good	1	6	Dims down to 1%, flicker at LE below 20%
		Miro Decorator	DRD4-W	Good	1	6	Dims down to 1%, flicker at LE below 20%
		Harmony	H703PTUTC	Good	1	6	Dims down to 1%, flicker at LE below 20%
		Adorne Whisper	ADWR700MMTUW2	Good	1	6	Dims down to 1%, flicker at LE below 20%
		Adorne Touch	ADTH700MMTUM2	Good	1	6	Dims down to 1%, flicker at LE below 20%
	Cooper	Decorator	DAL06P-C2-K-L	Good	1	6	Dims down to 1%, flicker at LE below 20%
		I E la co	CALOCD M/ K I	Cond	1	6	Dime down to 19/ flicker at LE below 209/

*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.

†May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating						
Not Compatible	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.					
Bad	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.					
Good	One or more of the following observed: Minor flickering at some point may exist. Dead travel are minor and most of the time not visible. Minor audible					
	noise.					
Best	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBa), wide dimming range - can dim down to 20% or less of light output.					
High End (H.E.) Dead Travel	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.					
Low End (L.E.) Dead Travel	petermines now much, in any, dead traver exists at the top and bottom of the diffinites a range. Dead traver is when the shoet can be moved without affecting the light level.					