

Dimmer Compatibility Guide

PLEASE NOTE: Compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment. Actual results may vary.

Product Family Name: Item Number: 776902
Ordering Code: LED4A19/21K/FIL-NOS/3
Item Number: Ordering Code:

		Lamps per Dimmer					
Manufacturer		Product	Model Number	Overall Rating	Recommended	Maximum Tested*	Minimum
							Notes
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	IlumaTech	IP06	Good	1	6	Dim's down to 1%, not smooth dimming
		SureSide	8633-P	Good	1	6	Dim's down to 1%, flickering HE with 1
		Vizia	VP06-1LZ	Good	1	6	Dim's down to 1%
	Lutron	Toggle	TG-600	Best	1	6	Dim's down to 1%
		Lumina	LGCL-600	Best	1	6	Dim's down to 1%
		Divi	DV-600	Best	1	6	Dim's down to 1%
		Skylark	S-600	Best	1	6	Dim's down to 1%
		Maestro	MAW-600	Bad	4	6	Dim's down to 1%
	Legrand	Titan	CD703-PW	Bad	4	6	Dim's down to 1%
		Harmony	H703-PTC	Bad	4	6	Dim's down to 1%
		Harmony	H703-PTC	Bad	4	6	Dim's down to 1%
CFL/LED	Leviton	IlumaTech	IPL06	Best	1	6	Dim's down to 1%
		Sureside	8674	Best	1	6	Dim's down to 1%
		Decora	8672	Best	1	6	Dim's down to 1%
		Decora Slide	DSL06-1LZ	Best	1	6	Dim's down to 1%
		Skylark	CTCL-153	Best	1	6	Dim's down to 1%
	Lutron	Sunnata	STCL-153	Best	1	6	Dim's down to 1%
		Divi	DVCL-153PL	Best	1	6	Dim's down to 1%
		Maestro	MACL-153MLH	Best	1	6	Dim's down to 1%
		Skylark	SCL-153P	Best	1	6	Dim's down to 1%
		Toggle	TGCL-153PH	Best	1	6	Dim's down to 1%
		Radio RA	RA2RR-6CL-PD	Best	1	6	Dim's down to 1%
		Harmony	DCL453-PTC	Best	1	6	Dim's down to 1%
	Legrand	Radiant	RHCL453PW	Good	1	6	Dim's down to 1%, flickering MID with 1
		Adorne Paddle	ADPD453LM2	Best	1	6	Dim's down to 1%
Electronic Low Voltage	Leviton	Vizia	VPE04	Bad	1	6	Flickering at LE with 6
		IlumaTech	IPE04	Bad	1	6	Not smooth dimming with 1-6
		Decora	8615-P	Bad	1	6	Flickering at LE with 1-6
		Skylark Countour	CTELV-303P	Best	1	6	Dim's down to 1%
	Lutron	Divi	DVELV-300P	Best	1	6	Dim's down to 1%
		Maestro	MAELV-600	Best	1	6	Dim's down to 1%
		Skylark	SELVB-300P	Best	1	6	Dim's down to 1%
		VIERTI	VTCL-600M-W	Good	1	6	Not smooth dimming with 1-6
	Legrand	Scene Director	SECLV	Best	1	6	Dim's down to 1%
Magnetic Low Voltage	Leviton	Vizia	VPM-06	Good	1	6	Dim's down to 1%, not smooth dimming with 1
		Decora	8613-P	Good	1	6	Dim's down to 1%
	Lutron	Maestro	MALV-600	Not compatible	1	6	Not turn on with 1-6
	Legrand	Harmony	DLV703-PW	Good	2	6	Dim's down to 1%
		Titan	CDLV703-PW	Good	3	6	Dim's down to 1%
Smart Dimmer	Leviton	Decora Digital (Bluetooth)	DDMX1-BLZ	Best	1	6	Dim's down to 1%
	Leviton	Decora Smart Z-Wave Technology	DZ9HD	Best	1	6	Dim's down to 1%
	Leviton	Decora Smart WiFi Technology	DW1KD	Best	1	6	Dim's down to 1%
	Lutron	Caseta Wireless smart dimmer Wi-Fi	PD-10NXD	Best	1	6	Dim's down to 1%
	Lutron	Caseta Wireless smart dimmer Wi-Fi	PD-6VCL	Best	1	6	Dim's down to 1%
	GE	Z WAVE	ZW3005	Best	1	6	Dim's down to 1%
Universal	Legrand	Adorne SoTap	ADTP703TU	Bad	4	6	Flashing HE with 4-6
		Miro Decorator	DRD4-W	Bad	1	6	Flickering HE with 1-6
		Harmony	H703PTUTC	Bad	4	6	Flickering HE with 4-6
		Adorne Whisper	ADWR700MMTUW2	Best	1	6	Dim's down to 1%
		Adorne Touch	ADTH700MMTUM2	Best	1	6	Dim's down to 1%
	Cooper	Decorator	DAL06P-C2-K-L	Good	2	6	Dim's down to 1%
		Skye	SAL06P-W-K-L	Good	2	6	Dim's down to 1%

*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.
†May experience "pop-on," lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum i light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating		
Not Compatible	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.	
Bad	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.	
Good	One or more of the following observed: Minor flickering at some point may exist. Dead t periods ravel may exist, which means there may be periods of time when the slider (or other form of control button) of dead travel are minor and most of the time not visible. Minor audible noise.	is moved without affecting the light level. These
Best	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBA), wide dimming range - can dim down to 20% or less of light output.	
High End (H.E.) Dead Travel	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's r nge. Dead travel is when the slider can be moved without affecting the light level.	
Low End (L.E.) Dead Travel		