

**Dimmer Compatibility Guide**

PLEASE NOTE: Compatibility has been tested using bulbs sold by the manufacturer in a standard environment. Actual results may vary.

Product Family Name: 776853 776908  
Item Number: LED375/27K/FIL/3 LED375/21K/FIL/NO3/3  
Ordering Code:  
Item Number:  
Ordering Code:

Lamps per Dimmer

	Manufacturer	Product	Model Number	Overall Rating	Recommended Minimum	Maximum Tested*	Notes		
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	HumanTouch	PO6	Best	1	6	Dimm down to 1%		
		SceneSlide	SE33-P	Best	1	6	Dimm down to 1%		
		Vista	VP06-IL2	Good	3	6	Dimm down to 1%		
		Tagalog	TG-600	Best	1	6	Dimm down to 1%		
		Qira	QI-600	Best	1	6	Dimm down to 1%		
		Dayark	DA-600	Best	1	6	Dimm down to 1%		
	Lagrand	Maestro	MAW-600	Not Compatible	1	6	Does not turn on with 1-6		
		Urban	UR303-FW	Best	1	6	Dimm down to 1%		
		Harmony	H303-PTC	Best	1	6	Dimm down to 1%		
		Harmony	H303-PTC	Good	1	6	Dimm down to 1%, Flicker at Mid with 1-3		
CFL/LED	Leviton	HumanTech	PO6	Best	1	6	Dimm down to 1%		
		SceneSlide	SE74	Best	1	6	Dimm down to 1%		
		Deora	DE72	Best	1	6	Dimm down to 1%		
		Deora Slide	DS06-IL2	Best	1	6	Dimm down to 1%		
		Dayark	CTCL-155	Best	1	6	Dimm down to 1%		
		Qira	QI-CL-153PL	Best	1	6	Dimm down to 1%		
		Maestro	MAEL-153BULH	Best	1	6	Dimm down to 1%		
		Dayark	CTCL-153P	Best	1	6	Dimm down to 1%		
		Tagalog	TGCL-153PH	Best	1	6	Dimm down to 1%		
		Audio RA	RAJMR-6CL-PO	Best	1	6	Dimm down to 1%		
	Lagrand	Maestro	MAEL-CL-PTC	Best	1	6	Dimm down to 1%		
		Harmony	HCL-453PTC	Best	1	6	Dimm down to 1%		
		Harmony	HCL-453PTC	Best	1	6	Dimm down to 1%		
		Adorne Puddle	ADPD453LUM2	Best	1	6	Dimm down to 10%		
		Electronic Low Voltage	Leviton	Vista	VP04	Best	1	6	Dimm down to 1%
				HumanTech	PE04	Best	1	6	Dimm down to 1%
				Deora	DE15-P	Bad	1	6	Dimm down to 10%
				Dayark Countour	CTEV-300P	Best	1	6	Dimm down to 1%
Lutron	Qira		QI-ELV-300P	Best	1	6	Dimm down to 1%		
	Maestro		MAELV-600	Best	1	6	Dimm down to 1%		
	Dayark		CTELV-300P	Best	1	6	Dimm down to 1%		
	UR318		CTELV-600A-W	Best	1	6	Dimm down to 1%		
	Lagrand		Scene Director	SCD1V	Bad	1	6	Dimm down to 1%	
Magnetic Low Voltage	Leviton	Vista	VPM-06	Good	2	6	Dimm down to 1%		
		Deora	DE13-P	Best	1	6	Dimm down to 1%		
	Lutron	Maestro	MAVLV-600	Bad	0	6	Dimm down to 1%		
	Lagrand	Harmony	DVLV303-FW	Best	1	6	Dimm down to 1%		
		Urban	UDLV303-FW	Best	1	6	Dimm down to 1%		
Smart Dimmer	Leviton	Deora Digital (Bluetooth)	CDMA01-BL2	Best	1	6	Dimm down to 1%		
	Leviton	Deora Smart 2-Wire Technology	CDMA01	Best	1	6	Dimm down to 7%		
	Lutron	Coasts Wireless smart dimmer Wi-Fi	PO-SDWIO	Best	1	6	Dimm down to 1%		
	Lutron	Coasts Wireless smart dimmer Wi-Fi	PO-SDWCL	Good	1	6	Dimm down to 1%, Flicker at 12 with 1-6		
	Lagrand	Adorne Touch Wi-Fi TRU Universal	ADTS700RMTUWIS						
	Lagrand	Adorne Soft Tap Wi-Fi TRU Universal	ADTS700RMTUWIS						
Universal	Lagrand	CS	ZV300S	Best	1	6	Dimm down to 1%		
		Adorne SoftTap	ADTS700TU	Best	1	6	Dimm down to 1%		
		Adorne Dimmer	ADDA-W	Best	1	6	Dimm down to 1%		
		Harmony	H303PTC	Best	1	6	Dimm down to 1%		
		Adorne Whispur	ADW700RMTUWIS	Best	1	6	Dimm down to 1%		
		Adorne Touch	ADTS700RMTUWIS	Not Compatible	1	6	Does not turn on with 1-6		
		Deconator	DADEP-C2-IL2	Best	1	6	Dimm down to 1%		
		Day	DADEP-W-IL2	Best	1	6	Dimm down to 1%		
	Cooper								

\*Maximum Tested Lamps per Dimmer - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.  
"May experience" "pop on": Lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

**Overall Rating**

**Not Compatible** One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.

**Bad** One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.

**Good** One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.

**Best** Most of the following observed: No flickering, minimal audible noise (typically less than 25 dba), wide dimming range - can dim down to 20% or less of light output.

**High Load (H.L.) Dead Travel** Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.

**Some Load (S.L.) Dead Travel**

Contact Information:  
Bulbrite Industries Inc.  
145 West Commercial Avenue Monrovia, New Jersey 07070  
PHONE: 1-800-528-5355 FAX: 1-800-443-7700  
Email: ProductSupport@bulbrite.com  
©2019 Bulbrite Industries Inc.  
All Rights Reserved.