



Tested Unit Item Number:	772858
Tested Unit Ordering Code:	LED11BR30/827/D/5
Related Item Number:	772859
Related Ordering Code:	LED11BR30/830/D/5

	Manufacturer	Product	Model Number	Overall Rating	Lamps per Dimmer		Notes
					Recommended Minimum	Maximum Tested*	
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	a IllumaTech	IPI06	Good	1	6	Not smooth, slight flicker during operation, dims completely
		b SureSlide	6633-P	Best	1	6	Dims completely
		c Vizia	VPI06-1LZ	Bad	1	6	Not smooth, flicker at high levels below MAX, slight flicker during operation, dims completely
	Lutron	d Toggler	TG-600	Good	1	6	Not smooth, slight flicker during operation, dims completely
		e Lumea	LGCL-600	Best	1	6	Dims completely
		f Diva	DV-600	Best	1	6	Dims completely
		g Skylark	S-600	Best	1	6	Dims completely
		h Maestro	MAW-600	Bad	2	6	Not compatible with 1, slight flicker at high end with 2, dims completely
	Legrand	i Titan	CD703-PW	Bad	1	6	Poor operation <3, not smooth, slight flicker during operation, dims completely
		j Harmony	D703-PTC	Bad	2	6	Not compatible with 1, slight flicker at high end with 2, dims completely
		k Harmony	H703-PTC	Bad	3	6	Not compatible with <3, dims completely
CFL/LED	Leviton	l IllumaTech	IPL06	Good	1	6	Delay in operation, dims completely
		m Sureslide	6674	Good	1	6	Delay in operation, dims completely
		n Decora	6672	Best	1	6	Dims completely
		o Decora Slide	DSL06-1LZ	Bad	1	6	Not smooth, flickers while operating, dims completely
		p Skylark	CTCL-153	Best	1	6	Dims completely
	Lutron	q Diva	DVCL-153PL	Bad	1	6	Not smooth, flickers while operating, dims completely
		r Maestro	MACL-153MLH	Good	1	6	Not smooth, slight flicker while operating, dims completely
		s Skylark	SCL-153P	Best	1	6	Dims completely
		t Toggler	TGCL-153PH	Best	1	6	Dims completely
		u Radio RA	RA2RR-6CL-PD	Best	1	6	Extremely slight flicker at some leves while adjusting, dims completely
		v Sunnata Touch	STCL-153M-BL		1	6	
	Legrand	w Harmony	DCL453-PTC	Best	1	6	Very slight flicker at low levels, dims completely
		x Harmony	HCL453PTC	Good	1	6	Not smooth, some flicker at several levels while operating, dims completely
			ADPD453LM2	Good	1	6	Not smooth, some flicker at several levels while operating, dims to 1%
Electronic Low Voltage	Leviton	y Vizia	VPE04	Good	1	6	Flickers at low levels during operation, dims completely
		z IllumaTech	IPE04	Not Compatible		6	
	Lutron	aa Decora	6615-P	Not Compatible		6	
		ab Skylark Countour	CTELV-303P	Good	1	6	HE dead travel (15 %), flickers while operating, jumps during operation, dims completely
		ac Diva	DVELV-300P	Good	1	6	Not smooth, flickers while dimming, dims completely
		ad Maestro	MAELV-600	Best	1	6	Dims completely
		ae Skylark	SELVB-300P	Good	1	6	Not smooth, slight flicker while dimming, dims completely
		af VIERTI	VTEL-600M-W	Best	1	6	Dims completely
		ag Scene Director	SCELV	Good	1	6	Not smooth, slight flicker while dimming, dims completely
Magnetic Low Voltage	Leviton	ah Vizia	VPM-06	Bad	1	6	Not smooth, flickers during operation, flickers at points steady state, dims completely
		ai Decora	6613-P	Best	1	6	Dims completely
	Lutron	aj Maestro	MALV-600	Not Compatible		6	
		ak Harmony	DLV703-PW	Bad	1	6	Poor operation with 1, heavy flicker at various levels, dims completely
	Legrand	al Titan	CDLV703-PW	Good	1	6	Not smooth, slight flicker during operation, dims completely
Smart Dimmer	Leviton	am Decora Digital (Bluetooth)	DDMX1-BLZ	Good	1	6	Not smooth, slight flicker during operation, dims completely
		an Decora Smart Z-Wave Technology	DZ6HD	Best	1	6	Dims completely
		ao Decora Smart WiFi Technology	DW1KD	Best	1	6	Dims completely
	Lutron	ap Caseta Wireless smart dimmer Wi-Fi	PD-10NXD	Best	1	6	Dims to 5%
		aq Caseta Wireless smart dimmer Wi-Fi	PD-6WCL	Bad	1	6	Not smooth, flickers during operation, flickers at low levels, dims to 5%
	GE	ar Z WAVE	ZW3005	Good	1	6	Not smooth, flickers during operation, dims completely
	Eaton	ay Eaton Smart Dimmer		Best	1	6	Dims completely
Universal	Legrand	as Adorne Softap	ADTP703TU	Bad	1	6	Not smooth, flickers while operating, flickers while stable, dims to 12%
		at Miro Decorator	DRD4-W	Not Compatible		6	Heavy flicker at MAX
		au Harmony	H703PTUTC	Bad	1	6	HE dead travel (50%), not smooth, slight jump while operating, dims completely
		av Adorne Whisper	ADWR700MMTUW2	Best	1	6	Dims completely
		aw Adorne Touch	ADTH700MMTUM2	Good	1	6	Not smooth, flickers while operating, dims completely
	Cooper	ax Decorator	DAL06P-C2-K-L	Best	1	6	Dims completely
		ay Universal Toggle Dimmer 120V	TUL06P-C2-KB-L	Good	1	6	Delay in operation, dims to 1%
	Eaton	ba Universal Slide Dimmer	FSUL06	Good	1	6	Delay in operation, dims to 1%
		bb Universal Slide Toggle Dimmer	LSO6P	Good	1	6	Delay in operation, dims to 1%
		bc Universal Slide Toggle Dimmer	LD06P	Good	1	6	Delay in operation, dims to 1%
		bd Universal Decorator Dimmer	DUL06P-W-2KB-LW	Good	1	6	Delay in operation, dims to 1%

*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.
†May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating	Description
Not Compatible	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.
Bad	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.
Good	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.
Best	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBA), wide dimming range - can dim down to 20% or less of light output.
High End (HE) Dead Travel Low End (LE) Dead Travel	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.