



Tested Unit Item Number: 776960 Tested Unit Ordering Code: LED14A19/50K/FIL/3 Related Item Number: 776961 Related Ordering Code: LED14A19/50K/FIL/M/3								
	Manufacturer	Product	Model Number	Overall Rating	Lamps per Dimmer		Notes	
					Recommended Minimum	Maximum Tested*		
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	a IllumaTech	IPI06	Good	1	6	Not smooth, dims to 10%, minor buzzing while dimming	
		b SureSlide	6633-P	Good	1	6	Dims to 10%, minor buzzing while dimming	
		c Vizia	VPI06-1LZ	Bad	3	6	Flickers below MAX <3, not smooth, dims to 10%, minor buzzing while dimming	
		d Toggle	TG-600	Good	1	6	Not smooth, dims to 8%, minor buzzing while dimming	
		e Lumea	LGCL-600	Good	1	6	Dims to 7%, minor buzzing while dimming	
	Lutron	f Diva	DV-600	Good	1	6	Dims to <1%, minor buzzing while dimming	
		g Skylark	S-600	Good	1	6	Dims to 1%, minor buzzing while dimming	
		h Maestro	MAW-600	Bad	1	6	Not compatible with 1, minor buzzing while dimming	
		i Titan	CD703-PW	Good	1	6	Dims to 15%, minor buzzing while dimming	
		Legrand	j Harmony	D703-PTC	Good	1	6	Minor buzzing while dimming
	k Harmony		H703-PTC	Good	1	6	Dims to 4%, minor buzzing while dimming	
CFL/LED	Leviton	l IllumaTech	IPL06	Good	1	6	Delay in operation, minor buzzing while dimming	
		m Sureslide	6674	Good	1	6	Dims to 8%, minor buzzing while dimming	
		n Decora	6672	Good	1	6	Minor buzzing while dimming	
		o Decora Slide	DSL06-1LZ	Bad	1	6	Delay in operation, not smooth, minor buzzing while dimming	
		p Skylark	CTCL-153	Not Compatible		6	Dims to 20%, minor buzzing while dimming	
	Lutron	q Diva	DVCL-153PL	Good		6	Not smooth, slight flicker while dimming, minor buzzing while dimming	
		r Maestro	MACL-153MLH	Not Compatible		6	Dims to 22%, minor buzzing while dimming	
		s Skylark	SCL-153P	Not Compatible	1	6	Dims to 25%, minor buzzing while dimming	
		t Toggle	TGCL-153PH	Bad	1	6	Dims to 18%, minor buzzing while dimming	
		u Radio RA	RA2RR-6CL-PD	Best	1	6	Dims to 4%, extremely faint buzzing while dimming	
	Legrand	v Harmony	DCL453-PTC	Not Compatible		6	Dims to 22%, minor buzzing while dimming	
		w Harmony	HCL453PTC	Bad	1	6	Dims to 18%, minor buzzing while dimming	
		x Adorne Paddle	ADPD453LM2	Not Compatible	1	6	Dims to 26%, minor buzzing while dimming	
		Electronic Low Voltage	Leviton	y Vizia	VPE04	Best	1	6
z IllumaTech	IPE04			Bad	1	6	Not smooth, dims to 5%, minor buzzing while dimming	
aa Decora	6615-P			Bad	1	6	HE dead travel (45%), not smooth, minor buzzing while dimming	
ab Skylark Countour	CTELV-303P			Best	1	6	Dims to 4%, very minor buzzing while dimming	
ac Diva	DVELV-300P			Best	1	6	Dims to 4%, very minor buzzing while dimming	
Lutron	ad Maestro		MAELV-600	Best	1	6	Dims to 4%, very minor buzzing while dimming	
	ae Skylark		SELVB-300P	Best	1	6	Dims to 4%, very minor buzzing while dimming	
	af VIERTI		VTCL-600M-W	Best	1	6	Dims to 4%, very minor buzzing while dimming	
	Legrand		ag Scene Director	SCELV	Best	1	6	Dims to 4%
			Magnetic Low Voltage	ah Vizia	VPM-06	Bad	1	6
ai Decora	6613-P	Bad		1	6	Dims to 4%, minor buzzing while dimming		
Lutron	aj Maestro	MALV-600		Not Compatible		6		
	ak Harmony	DLV703-PW		Good	1	6	minor buzzing while dimming	
Legrand	al Titan	CDLV703-PW		Good	1	6	Dims to 12%, minor buzzing while dimming	
Smart Dimmer	Leviton	am Decora Digital (Bluetooth)	DMMX1-BLZ	Good	1	6	Dims to 8%, minor buzzing while dimming	
	Leviton	Decora Smart Z-Wave Technology	DZ6HD	Not Compatible	1	6	Dims to 30%, minor buzzing while dimming	
	Leviton	Decora Smart WiFi Technology	DW1KD	Not Compatible		6		
	Lutron	ap Caseta Wireless smart dimmer Wi-Fi	PD-10NXD	Good	1	6	Dims to 3%, not smooth, minor buzzing while dimming	
	Lutron	aq Caseta Wireless smart dimmer Wi-Fi	PD-6WCL	Not Compatible		6	Dims to 30%, minor buzzing while dimming	
	GE	ar Z WAVE	ZW3005	Bad	1	6	Not smooth, slight flicker while dimming, minor buzzing while dimming	
Universal	Legrand	as Adorne SoftTap	ADTP703TU	Not Compatible		6	Not smooth, dims to 24%, minor buzzing while dimming	
		at Miro Decorator	DRD4-W	Not Compatible		6		
		au Harmony	H703PTUTC	Not Compatible		6		
		av Adorne Whisper	ADWR700MMTUW2	Best	1	6	Very minor buzzing while dimming	
		aw Adorne Touch	ADTH700MMTUM2	Best	1	6	Very minor buzzing while dimming	
	Cooper	ax Decorator	DAL06P-C2-K-L	Good	1	6	Dims to 2%, minor buzzing while dimming	
		ay Skye	SAL06P-W-K-L			6		
		*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.						
		†May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.						
Overall Rating	Description							
Not Compatible	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.							
Bad	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.							
Good	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.							
Best	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBa), wide dimming range - can dim down to 20% or less of light output.							
High End (HE) Dead Travel Low End (LE) Dead Travel	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.							
©2025 Bulbrite Industries Inc.								