



Dimmer Compatibility Guide

PLEASE NOTE: Compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment. Actual results may vary.

Product Family Name:
Item Number: 773275
Ordering Code: LED14DISC/7/930/J/BLRD/D
Item Number:
Ordering Code:

	Manufacturer	Product	Model Number	Overall Rating	Lamps per Dimmer		Notes
					Recommended Minimum	Maximum Tested*	
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	a IllumaTech	IP106	Bad	1	6	Dead travel LE&HE, some flicker, rough operation
		b SureSlide	6633-P	Not Compatible	4	6	Heavy flicker when less than 4, dim when less than 4, dim at HE
		c Vizia	VPI06-1LZ	Best	1	6	
	Lutron	d Toggle	TG-600	Best	1	6	
		e Lumea	LGCL-600	Best	1	6	
		f Diva	DV-600	Best	1	6	
		g Skylark	S-600	Good	1	6	Dead travel in middle
	Legrand	h Maestro	MAW-600	Not Compatible	3	6	Heavy flicker when more than 4, does not operate with 1 or 2
		i Titan	CD703-PW	Good	3	6	Dead travel in middle
		j Harmony	D703-PTC	Bad	4	6	Rough operation, initially gets brighter when dimming
CFL/LED	Leviton	k Harmony	H703-PTC	Bad	3	6	Heavy flicker when less than 3, initially gets brighter when dimming
		l IllumaTech	IP106	Best	1	6	
		m SureSlide	6674	Good	1	6	Dead travel HE
	Lutron	n Decora	6672	Best	1	6	
		o Decora Slide	DSL06-1LZ	Best	1	6	
		p Skylark	CTCL-153	Best	1	6	LE absent in operation, dims and fully extinguishes ~50% of slider travel
		q Diva	DVCL-153PL	Best	1	6	
		r Maestro	MACL-153MLH	Good	1	6	Dead travel HE with 6
		s Skylark	SCL-153P	Best	1	6	
		t Toggle	TGCL-153PH	Best	1	6	
	Legrand	u Radio RA	RA2RR-6CL-PD	Best	1	6	Dead travel LE
		v Harmony	DCL453-PTC	Best	1	6	
		w Harmony	HCL453PTC	Best	1	6	
		x Adorne Paddle	ADPD453LM2	Best	1	6	
Electronic Low Voltage	Leviton	y Vizia	VPE04	Best	1	6	
		z IllumaTech	IPE04	Good	1	6	Dead travel HE, flickers while adjusting
	Lutron	aa Decora	6615-P	Good	1	6	Dead travel ~top 50% of travel HE
		ab Skylark Countour	CTELV-303P	Bad	1	6	Dead travel in middle, low luminous flux at HE (~70% of others)
		ac Diva	DVELV-300P	Bad	1	6	Low luminous flux at HE (~80% of others)
		ad Maestro	MAELV-600	Best	1	6	
		ae Skylark	SELVB-300P	Best	1	6	
	Legrand	af VIER TI	VTEL-600M-W	Best	1	6	
		ag Scene Director	SECELV	Best	1	6	
Magnetic Low Voltage	Leviton	ah Vizia	VPM-06	Best	1	6	
		ai Decora	6613-P	Best	1	6	
	Lutron	aj Maestro	MALV-600	Not Compatible	6	6	Does not function
	Legrand	ak Harmony	DLV703-PW	Good	2	6	Dead travel LE, initially gets brighter when dimming
		al Titan	CDLV703-PW	Bad	2	6	Heavy flicker with 1 or 6, initially gets brighter when dimming
Smart Dimmer	Leviton	am Decora Digital (Bluetooth)	DDMX1-BLZ	Good	2	6	Dead travel HE, flickers LE with 1
		an Decora Smart Z-Wave Technology	DZ6HD	Good	1	6	Dead travel HE with 1
	Lutron	ao Decora Smart WiFi Technology	DW1KD	Best	1	6	Slight lag in operation
		ap Caseta Wireless smart dimmer Wi-Fi	PD-10NXD	Best	1	6	
	Lutron	aq Caseta Wireless smart dimmer Wi-Fi	PD-6WCL	Best	1	6	
		ar GE	ZWAVE	Best	1	6	
Universal	Legrand	as Adorne SoftTap	ADTP703TU	Best	1	6	Initialization is slow
		at Miro Decorator	DRD4-W	Good	1	6	Dead travel LE, flickers LE with 6, initially gets brighter when dimming
		au Harmony	H703PTUTC	Bad	2	6	Flickers with 1, dim with 1
		av Adorne Whisper	ADWR700MMTUW2	Best	1	6	
	Cooper	aw Adorne Touch	ADTH700MMTUM2	Best	1	6	
		ax Decorator	DAL06P-C2-K-L	Good	1	6	Dead travel LE&HE
		ay Skye	SAL06P-W-K-L	Best	1	6	

*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.

†May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating	Description
Not Compatible	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.
Bad	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.
Good	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.
Best	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBA), wide dimming range - can dim down to 20% or less of light output.
High End (HE) Dead Travel Low End (LE) Dead Travel	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.

©2025 Bulbrite Industries Inc.

All Rights Reserved.