

## **Dimmer Compatibility Guide**

Product Family Name: Item Number: 773607

Ordering Code: LED14FLUSH/7/5CCT/927-950/J/WH/D

Item Number: Ordering Code:

	Manufacturer			Model Number		Lamps per	Dimmer	Notes
			Product		Overall Rating	Recommended	Maximum	
'						Minimum	Tested*	
		а	IllumaTech	IPI06	Not Compatible		6	
ncandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	ь	SureSlide	6633-P	Bad	1	6	Flickers heavily w/5, not smooth w/6, Good with <5
			Vizia	VPI06-1LZ	Good	1	6	Not smooth
	Lutron		Toggler	TG-600	Good	1	6	Dims to <1%, SLIGHT flicker at MIN with <6
			Lumea	LGCL-600	Good	1	6	80% at MAX with >2
			Diva	DV-600	Best	1	6	
			Skylark	S-600	Best	1	6	
_			Maestro	MAW-600	Bad	2	6	Not compatible with <2
	Legrand		Titan	CD703-PW	Bad	2	6	Not compatible with <2
			Harmony	D703-PTC H703-PTC	Bad	2	6	Not compatible with <2
			Harmony		Bad	2	6	Not compatible with <2
CFL/LED	Leviton		IllumaTech	IPL06	Good	1	6	HE dead travel (10%), significant delay when ↑ from MIN
			Sureslide	6674	Best	1	6	
			Decora	6672	Best	1	6	
			Decora Slide	DSL06-1LZ	Best	1	6	HE dead travel (20%)
	Lutron		Skylark	CTCL-153	Best	1	6	
			Diva	DVCL-153PL	Best	1	6	
			Maestro	MACL-153MLH SCL-153P	Best	1	6	Dims to 2%
			Skylark Toggler	TGCL-153PH	Best Best	1	6	
			Radio RA	RA2RR-6CL-PD	Best	1	6	
	Legrand		Harmony	DCL453-PTC	Best	1	6	
			Harmony	HCL453PTC	Good	1	6	Not smooth (gets randomly brighter in the middle with all quantit
			Adorne Paddle	ADPD453LM2	Best	1	6	Dims to 3%
			•	•				
Electronic Low Voltage	Leviton		Vizia IllumaTech	VPE04	Best	1	6	
			Decora	6615-P	Bad Bad	1	6	Not smooth while adjusting. Slight flicker at most levels  Not smooth while adjusting. Slight flicker at most levels. Dead tra
			Skylark Countour	CTELV-303P	Best	1	6	Not smooth while adjusting. Slight lilicker at most levels. Dead th
	Lutron		Diva	DVELV-300P	Best	1	6	
			Maestro	MAELV-600	Best	1	6	
			Skylark	SELVB-300P	Best	1	6	
			f VIERTI	VTEL-600M-W	Best	1	6	
	Legrand	_	Scene Director	SCELV	Best	1	6	
	8	_						
	Leviton		Vizia	VPM-06	Bad	1	6	Slight flicker while adjusting. Some flicker when stationary
			Decora	6613-P	Best	1	6	LE dead travel (20%)
Magnetic Low Voltage	Lutron		Maestro	MALV-600	Not Compatible		6	
	Legrand		Harmony	DLV703-PW	Best	1	6	Fully extinguished @ 20%
		а	Titan	CDLV703-PW	Bad	2	6	Not smooth with 1, significant delay when ↑ from MIN
	Leviton	ar	Decora Digital (Bluetooth)	DDMX1-BLZ	Good	1	6	Not perfectly smooth, but stable
			Decora Smart Z-Wave Technology	DZ6HD	Best	1	6	, , , , , , , , , , , , , , , , , , , ,
				DW1KD	Best	1	6	
-	Leviton							
Smart Dimmer	Leviton	a	Decora Smart WiFi Technology					
Smart Dimmer	Leviton Lutron	aı	Caseta Wireless smart dimmer Wi-Fi	PD-10NXD	Best	1	6	
Smart Dimmer	Leviton Lutron Lutron	ar ar	Caseta Wireless smart dimmer Wi-Fi Caseta Wireless smart dimmer Wi-Fi	PD-10NXD PD-6WCL	Best Bad	1	6	7 0
Smart Dimmer	Leviton Lutron	ar ar	Caseta Wireless smart dimmer Wi-Fi	PD-10NXD	Best	1	6	7 0
Smart Dimmer	Leviton Lutron Lutron	ar ar ar	Caseta Wireless smart dimmer Wi-Fi Caseta Wireless smart dimmer Wi-Fi	PD-10NXD PD-6WCL	Best Bad	1	6	7 0
Smart Dimmer	Leviton Lutron Lutron	ar ar ar	Caseta Wireless smart dimmer Wi-Fi Caseta Wireless smart dimmer Wi-Fi Z WAVE	PD-10NXD PD-6WCL ZW3005	Best Bad Good	1 1	6 6 6	Slight flicker while dimming at low levels, slight flicker at most le
Smart Dimmer	Leviton Lutron Lutron	ar ar ar ar	Caseta Wireless smart dimmer Wi-Fi Caseta Wireless smart dimmer Wi-Fi Z WAVE Adorne SofTap	PD-10NXD PD-6WCL ZW3005	Best Bad Good Bad	1 1 1 2	6 6 6	Slight flicker while dimming at low levels, slight flicker at most le Not compatible with 1
Smart Dimmer Universal	Leviton Lutron Lutron GE	at a	Caseta Wireless smart dimmer Wi-Fi Caseta Wireless smart dimmer Wi-Fi Z WAVE Adorne SofTap Miro Decorator	PD-10NXD PD-6WCL ZW3005 ADTP703TU DRD4-W	Best Bad Good Bad Bad	1 1 1 2 1	6 6 6 6	Slight flicker while dimming at low levels, slight flicker at most le  Not compatible with 1  Not compatible with <3
	Leviton Lutron Lutron GE	a a a a a a a a a a a a a a a a a a a	Caseta Wireless smart dimmer Wi-Fi Caseta Wireless smart dimmer Wi-Fi Z WAVE Adorne SofTap Miro Decorator Harmony	PD-10NXD PD-6WCL ZW3005 ADTP703TU DRD4-W H703PTUTC	Best Bad Good Bad Bad Not Compatible	1 1 1 2 1 5	6 6 6 6 6	Slight flicker while dimming at low levels, slight flicker at most lev  Not compatible with 1  Not compatible with <3
	Leviton Lutron Lutron GE	at a	Caseta Wireless smart dimmer Wi-Fi Caseta Wireless smart dimmer Wi-Fi Z WAVE Adorne SofTap Miro Decorator Harmony Adorne Whisper	PD-10NXD PD-6WCL ZW3005 ADTP703TU DRD4-W H703PTUTC ADWR700MMTUW2	Best Bad Good Bad Bad Not Compatible Best	1 1 1 1 2 1 5	6 6 6 6 6 6	Not compatible with <3 Not smooth. Not compatible with <5

\*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.

\*May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating	Description
Not Compatible	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.
Bad	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.
Good	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.
Best	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBa), wide dimming range - can dim down to 20% or less of light output.
High End (HE) Dead Travel Low End (LE) Dead Travel	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.

2025 Bulbrite Industries Inc.