



Dimmer Compatibility Guide

PLEASE NOTE: Compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment. Actual results may vary.

Product Family Name: 773604
Item Number: LED14FLUSH/7/930/3/MH/D
Ordering Code:
Item Number:
Ordering Code:

	Manufacturer	Product	Model Number	Overall Rating	Lamps per Dimmer		Notes
					Recommended Minimum	Maximum Tested*	
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	a IllumaTech	IPI06	Good	1	6	Not smooth, flickers and dim @ MAX with 5 or 6
		b SureSlide	6633-P	Good	1	6	Not smooth, flickers and dim @ MAX with 5 or 6
		c Vizia	VPI06-1LZ	Good	1	6	Not smooth, flickers with 1 or 2
	Lutron	d Toggler	TG-600	Bad	1	6	Flickers when dimming at low levels, not smooth
		e Lumea	LGCL-600	Good	1	6	Not smooth while adjusting with 6
		f Diva	DV-600	Good	1	6	Not smooth
		g Skylark	S-600	Best	1	6	
	Legrand	h Maestro	MAW-600	Bad	2	6	Not compatible with 1, not smooth
		i Titan	CD703-PW	Bad	2	6	Not compatible with 1, some flickering with various quantities
		j Harmony	D703-PTC	Good	2	6	Not compatible with 1
		k Harmony	H703-PTC	Bad	2	6	Not compatible with 1, poor operation with 2
CFL/LED	Leviton	l IllumaTech	IPL06	Best	1	6	
		m Sureslide	6674	Best	1	6	
		n Decora	6672	Best	1	6	
	Lutron	o Decora Slide	DSL06-1LZ	Best	1	6	
		p Skylark	CTCL-153	Good	1	6	Not smooth
		q Diva	DVCL-153PL	Best	1	6	
		r Maestro	MACL-153MLH	Best	1	6	
		s Skylark	SCL-153P	Best	1	6	
		t Toggler	TGCL-153PH	Best	1	6	
		u Radio RA	RA2RR-6CL-PD	Best	1	6	
	Legrand	v Harmony	DCL453-PTC	Bad	1	6	Not smooth
		w Harmony	HCL453PTC	Best	1	6	
		x Adorne Paddle	ADPD453LM2	Best	1	6	
Electronic Low Voltage	Leviton	y Vizia	VPE04	Best	1	6	
		z IllumaTech	IPE04	Bad	1	6	Not smooth, flickers a lot while adjusting
	Lutron	aa Decora	6615-P	Good	1	6	HE dead travel (20%)
		ab Skylark Countour	CTELV-303P	Best	1	6	
		ac Diva	DVELV-300P	Best	1	6	
		ad Maestro	MAELV-600	Best	1	6	
		ae Skylark	SELVB-300P	Best	1	6	
		af VIERTI	VTEL-600M-W	Best	1	6	
		ag Scene Director	SCELV	Best	1	6	
Magnetic Low Voltage	Leviton	ah Vizia	VPM-06	Best	1	6	
		ai Decora	6613-P	Best	1	6	
	Lutron	aj Maestro	MALV-600	Bad	2	6	Not compatible with 1
		ak Harmony	DLV703-PW	Bad	2	6	Not compatible with 1
		al Titan	CDLV703-PW	Bad	3	6	Not compatible with 1, not smooth with 1
Smart Dimmer	Leviton	am Decora Digital (Bluetooth)	DDMX1-BLZ	Best	1	6	
	Leviton	an Decora Smart Z-Wave Technology	DZ6HD	Best	1	6	
	Leviton	ao Decora Smart WiFi Technology	DW1KD	Best	1	6	
	Lutron	ap Caseta Wireless smart dimmer Wi-Fi	PD-10NXD	Best	1	6	Dims to 4%
	Lutron	aq Caseta Wireless smart dimmer Wi-Fi	PD-6WCL	Best	1	6	Dims to 3%
	GE	ar Z WAVE	ZW3005	Best	1	6	
Universal	Legrand	as Adorne SofTap	ADTP703TU	Best	1	6	
		at Miro Decorator	DRD4-W	Bad	1	6	Not compatible with 2, flickers at MAX with 1
		au Harmony	H703PTUTC	Bad	1	6	Not smooth, dims to 12%
		av Adorne Whisper	ADWR700MMTUM2	Best	1	6	
	Cooper	aw Adorne Touch	ADTH700MMTUM2	Best	1	6	
		ax Decorator	DAL06P-C2-K-L	Bad	3	6	Not smooth with 1 or 2
		ay Skye	SAL06P-W-K-L	Best	6	6	

*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.

†May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating	Description
Not Compatible	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.
Bad	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.
Good	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.
Best	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBa), wide dimming range - can dim down to 20% or less of light output.
High End (HE) Dead Travel	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.
Low End (LE) Dead Travel	

©2025 Bulbrite Industries Inc.

All Rights Reserved.