



Tested Unit Item Number: 773166
Tested Unit Ordering Code: LED14REC/5/6/930/WHRD

	Manufacturer	Product	Model Number	Overall Rating	Lamps per Dimmer		Notes
					Recommended Minimum	Maximum Tested*	
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	a IllumaTech	IP106	Good	1	6	Not smooth while operating, stable at constant, dims to 5%
		b SureSlide	6633-P	Best	1	6	Dims completely
		c Vizia	VPI06-1LZ	Best	1	6	Dims to 4%
		d Toggle	TG-600	Best	1	6	Dims to 4%
		e Lumea	LGCL-600	Best	1	6	Dims to <1%
	Lutron	f Diva	DV-600	Best	1	6	Dims completely
		g Skylark	S-600	Good	1	6	Not completely smooth while dimming, dims completely
		h Maestro	MAW-600	Best	1	6	Dims completely
		i Titan	CD703-PW	Bad	1	6	Poor control and operation, dims to 1%
		Legrand	j Harmony	D703-PTC	Best	1	6
k Harmony	H703-PTC		Good	1	6	Not smooth while adjusting at high end, dims completely	
CFL/LED	Leviton	l IllumaTech	IPLO6	Best	1	6	Delay in operation, dims completely
		m Sureslide	6674	Best	1	6	Delay in operation, smooth operation, dims to 3%
		n Decora	6672	Best	1	6	Dims to 2%
		o Decora Slide	DSL06-1LZ	Good	1	6	Not smooth, flickers while operating, dims to 4%
		p Skylark	CTCL-153	Good	1	6	HE dead travel (20%), dims to 5%
	Lutron	q Diva	DVCL-153PL	Best	1	6	Slight jumps while operating, dims completely
		r Maestro	MACL-153MLH	Best	1	6	Dims to 4%
		s Skylark	SCL-153P	Best	1	6	Extinguishes by 25% L.E. dims completely
		t Toggle	TGCL-153PH	Best	1	6	Dims completely
		u Radio RA	RA2RR-6CL-PD	Best	1	6	Dims to <1%
		v Sunnata Touch	STCL-153M-BL		1	6	
		w Harmony	DCL453-PTC	Good	1	6	LE dead travel (20%), dims to 7%
	Legrand	x Harmony	HCL453PTC	Good	1	6	LE dead travel (20%), dims to 7%
		y Adorne Paddle	ADPD453LM2	Good	1	6	LE dead travel (20%), dims to 10%
Electronic Low Voltage	Leviton	y Vizia	VPE04	Good	1	6	Dims to 6%
		z IllumaTech	IEPE04	Not Compatible		6	
		aaa Decora	6615-P	Bad	1	6	Not smooth during operation, dims to 18%
	Lutron	abb Skylark Countour	CTELV-303P	Good	1	6	Dims to 5%
		ac Diva	DVELV-300P	Good	1	6	Dims to 5%
		ad Maestro	MAELV-600	Good	1	6	Dims to 5%
		ae Skylark	SELVB-300P	Good	1	6	HE dead travel (20%), dims to 4%
		af VIERTI	VTEL-600M-W	Best	1	6	Dims completely
Legrand	ag Scene Director	SECLV	Best	1	6	Dims completely	
Magnetic Low Voltage	Leviton	ah Vizia	VPM-06	Bad	1	6	Not smooth, poor operation with 1, dims to 4%
		ai Decora	6613-P	Best	1	6	Dims completely
	Lutron	aj Maestro	MALV-600	Not Compatible		6	
		ak Harmony	DLV703-PW	Good	1	6	Slight flicker while operating, dims completely
	ai Titan	CDLV703-PW	Bad	1	6	Not smooth, jumps during operation, stops dimming, dims to 30%	
Smart Dimmer	Leviton	am Decora Digital (Bluetooth)	DDMX1-BLZ	Good	1	6	Dims to 9%
		an Decora Smart Z-Wave Technology	DZ6HD	Good	1	6	Not smooth, light jump at low levels, dims to 2%
		ao Decora Smart WiFi Technology	DW1KD	Best	1	6	Dims completely
	Lutron	ap Caseta Wireless smart dimmer Wi-Fi	PD-10NXD	Best	1	6	Dims completely
		aq Caseta Wireless smart dimmer Wi-Fi	PD-6WCL	Good	1	6	Slight flicker while operating, dims to 8%
	GE	ar Z WAVE	ZW3005	Bad	1	6	Not smooth, jumps while adjusting, dims to <1%
	Eaton	av Eaton Smart Dimmer		Best	1	6	Dims completely
Universal	Legrand	as Adorne SoTap	ADTP703TU	Bad	1	6	Dims to 17%
		at Miro Decorator	DRD4-W	Best	1	6	Dims completely
		au Harmony	H703PTUTC	Bad	1	6	HE dead travel, dims to 11%
		av Adorne Whisper	ADWR700MMTUW2	Best	1	6	Dims completely
		aw Adorne Touch	ADTH700MMTUM2	Best	1	6	Dims completely
	Cooper	ax Decorator	DAL06P-C2-K-L	Good	1	6	Not smooth, jumps while operating, dims to 4%
		az Universal Toggle Dimmer 120V	TUL06P-C2-KB-L	Good	1	6	Significant delay in operation, dims completely
	Eaton	baa Universal Slide Dimmer	FSUL06	Good	1	6	Significant delay in operation, dims completely
		bb Universal Slide Toggle Dimmer	LSO6P	Good	1	6	Significant delay in operation, dims completely
		bc Universal Slide Toggle Dimmer	LD06P	Good	1	6	Significant delay in operation, dims completely
		bd Universal Decorator Dimmer	DUL06P-W-2KB-LW	Good	1	6	Significant delay in operation, dims completely

*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.

†May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating	Description
Not Compatible	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.
Bad	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.
Good	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.
Best	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBA), wide dimming range - can dim down to 20% or less of light output.
High End (HE) Dead Travel Low End (LE) Dead Travel	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.