

Dimmer Compatibility Guide

Product Family Name:

Item Number: Ordering Code:

LED17FLUSH/9/930/J/WH/D

Item Number: Ordering Code:

	Manufacturer					Lamps per		Notes
			Product	Model Number	Overall Rating	Recommended	Maximum	
						Minimum	Tested*	
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton		IllumaTech	IPI06	Good	1	6	Not smooth with >4
			SureSlide	6633-P	Good	1	6	Not smooth with >4
			Vizia	VPI06-1LZ	Best	1	6	
	Lutron		Toggler	TG-600	Good	1	6	Not smooth with >4
			Lumea	LGCL-600	Good	1	6	80% MAX with >3
			Diva	DV-600	Best	1	6	
			Skylark	S-600	Best	1	6	
		h	Maestro	MAW-600	Good	2	6	Not compatible with 1
	Legrand	i	Titan	CD703-PW	Good	2	6	Not smooth with 1, dims when brightening with 1
			Harmony	D703-PTC	Bad	1	6	Not smooth, dims when brightening
		k	Harmony	H703-PTC	Good	2	6	Not smooth with 1, dims when brightening with 1
			IllumaTech	IPL06	Best	1	6	
_	Leviton		Sureslide	6674	Best	1	6	
			Decora	6672	Best	1	6	
			Decora Slide	DSL06-1LZ	Best	1	6	
	Lutron		Skylark	CTCL-153	Best	1	6	LE dead travel (25%)
			Diva	DVCL-153PL	Best	1	6	LL dodd saver (2070)
CFL/LED			Maestro	MACL-153PL	Best	1	6	Dims to 2%
CFL/LED			Skylark	SCL-153P	Best	1	6	Dims to 2%
			Toggler	TGCL-153PH	Best	1	6	Dims to 3%
		- 1	Radio RA	RA2RR-6CL-PD	Best	1	6	Dims to <1%
	Legrand		Harmony	DCL453-PTC	Best	1	6	Dims to 2%
			Harmony	HCL453PTC	Best	1	6	Dims to 2%
			Adorne Paddle	ADPD453LM2	Best	1	6	Dims to 4%
				•		·		Danie to 170
	Leviton		Vizia	VPE04	Best	1	6	
			IllumaTech	IPE04	Good	1	6	Not smooth
_			Decora	6615-P	Good	1	6	Not smooth, dims to 7%
	Lutron		Skylark Countour	CTELV-303P	Best	1	6	
Electronic Low Voltage			Diva	DVELV-300P	Best	1	6	
			Maestro	MAELV-600	Best	1	6	
			Skylark	SELVB-300P	Best	1	6	
			f VIERTI	VTEL-600M-W	Best	1	6	
	Legrand	ag	Scene Director	SCELV	Best	1	6	Dims to <1%
Magnetic Low Voltage	Leviton	al	Vizia	VPM-06	Best	1	6	
			Decora	6613-P	Best	1	6	
				MALV-600			6	
Magnetic Low Voltage	Lutron		Maestro		Not Compatible		-	
	Legrand		Harmony	DLV703-PW	Good	2	6	Not smooth with 1
	-	al	Titan	CDLV703-PW	Good	2	6	70% at MAX with 1
	Leviton	an	Decora Digital (Bluetooth)	DDMX1-BLZ	Best	1	6	
	Leviton		Decora Smart Z-Wave Technology	DZ6HD	Best	1	6	
		_	0,	DW1KD		1		
Smart Dimmer	Leviton		Decora Smart WiFi Technology		Best		6	
	Lutron		Caseta Wireless smart dimmer Wi-Fi	PD-10NXD	Best	1	6	
	Lutron	ac	Caseta Wireless smart dimmer Wi-Fi	PD-6WCL	Best	1	6	Dims to 4%
	GE	aı	Z WAVE	ZW3005	Best	1	6	
	Legrand		Adorne SofTap	IADTP703TU	Best	1	6	Dims to 5%
			Miro Decorator	DRD4-W	Good	1	6	Not smooth with 1
			Harmony	H703PTUTC	Good	1	6	Dims to 10%, not smooth
			Adorne Whisper	ADWR700MMTUW2	Best	1	6	DITTS TO 1076, HOLSMOOTH
Universal								
-		_	Adorne Touch	ADTH700MMTUM2	Best	1	6	
	Cooper		Decorator Skye	DAL06P-C2-K-L SAL06P-W-K-L	Good	1	6	Not smooth with 6
							l 6	

*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.
†May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating	Description				
Not Compatible	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.				
Bad	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.				
Good	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.				
Best	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBa), wide dimming range - can dim down to 20% or less of light output.				
High End (HE) Dead Travel Low End (LE) Dead Travel	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.				

©2025 Bulbrite Industries Inc.