



Dimmer Compatibility Guide

PLEASE NOTE: Compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment. Actual results may vary.

Tested Unit Item Number: 776951
Tested Unit Ordering Code: LED2T6/27K/FIL/3
Related Item Number: 776952
Related Ordering Code: LED2T6/30K/FIL/4

	Manufacturer	Product	Model Number	Overall Rating	Lamps per Dimmer		Notes
					Recommended Minimum	Maximum Tested*	
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	a IllumaTech	IPI06	Best	1	6	Dims completely
		b SureSlide	6633-P	Best	1	6	LE dead travel 15%, dims completely
		c Vizia	VPI06-1LZ	Bad	1	6	Poor operation with 1, 80% MAX with 1
	Lutron	d Toggler	TG-600	Best	1	6	Dims completely
		e Lumea	LGCL-600	Good	1	6	90% at MAX, 80% at MAX with 1, dims completely
		f Diva	DV-600	Best	1	6	Dims completely
		g Skylark	S-600	Best	1	6	Dims completely
		h Maestro	MAW-600	Not Compatible		6	
		i Titan	CD703-PW	Not Compatible		6	
	Legrand	j Harmony	D703-PTC	Bad	4	6	Not compatible <4, dims completely
		k Harmony	H703-PTC	Bad	1	6	Not compatible <4, dims completely
CFL/LED	Leviton	l IllumaTech	IPL06	Bad	1	6	Delay in operation, poor operation <5, LE dead travel >50%, dims completely
		m Sureslide	6674	Bad	1	6	Delay in operation, HE dead travel 30%, dims completely
		n Decora	6672	Best	1	6	Dims completely
	Lutron	o Decora Slide	DSL06-1LZ	Best	1	6	Dims completely
		p Skylark	CTL-153	Good	1	6	Poor operation with 1, dims completely
		q Diva	DVCL-153PL	Best	1	6	Dims completely
		r Maestro	MACL-153MLH	Best	1	6	Dims completely
		s Skylark	SCL-153P	Best	1	6	Dims to 2%
		t Toggler	TGCL-153PH	Best	1	6	Dims to <1%
		u Radio RA	RA2RR-6CL-PD	Best	1	6	Dims completely
	Legrand	v Harmony	DCL453-PTC	Best	1	6	Dims to 4%
		w Harmony	HCL453PTC	Good	2	6	Not compatible with 1, dims completely
		x Adorne Paddle	ADPD453LM2	Best	1	6	Dims to 7%
Electronic Low Voltage	Leviton	y Vizia	VPE04	Bad	1	6	Heavily flickers while dimming with 3, dims completely
		z IllumaTech	IPE04	Bad	1	6	Inconsistent operation, brightens and dims randomly
		aa Decora	6615-P	Not Compatible		6	
	Lutron	ab Skylark Countour	CTELV-303P	Bad	1	6	Poor operation, HE dead travel (20%), abrupt changes while adjusting
		ac Diva	DVELV-300P	Bad	1	6	Poor operation, HE dead travel (20%), abrupt changes while adjusting
		ad Maestro	MAELV-600	Best	1	6	Dims to 3%
		ae Skylark	SELVB-300P	Best	1	6	Dims completely
		af VIERTI	VTLE-600M-W	Good	1	6	90% at MAX, dims completely
Magnetic Low Voltage	Leviton	ah Vizia	VPM-06	Bad	1	6	80% at MAX with 1, dims completely
		ai Decora	6613-P	Best	1	6	Dims completely
	Lutron	aj Maestro	MALV-600	Not Compatible		6	
		ak Harmony	DLV703-PW	Bad	2	6	Not compatible with 1, dims completely with 2 or more
	Legrand	al Titan	CDLV703-PW	Bad	1	6	Not compatible with 1, poor operation less than 5, dims completely
Smart Dimmer	Leviton	am Decora Digital (Bluetooth)	DDMX1-BLZ	Best	1	6	Dims completely
	Leviton	an Decora Smart Z-Wave Technology	DZ6HD	Best	1	6	Dims completely
	Leviton	ao Decora Smart WiFi Technology	DW1KD	Best	1	6	Dims completely
	Lutron	ap Caseta Wireless smart dimmer Wi-Fi	PD-10NXD	Best	1	6	Dims to 7%
	Lutron	aq Caseta Wireless smart dimmer Wi-Fi	PD-6WCL	Best	1	6	Dims to 3%
	GE	ar Z WAVE	ZW3005	Good	1	6	Poor operation, abrupt changes while adjusting, dims to 3%
Universal	Legrand	as Adorne SofTap	ADTP703TU	Not Compatible		6	
		at Miro Decorator	DRD4-W	Not Compatible	4	6	Not compatible <4
		au Harmony	H703PTUTC	Not Compatible	5	6	Not compatible <5
		av Adorne Whisper	ADWR700MMTUMW2	Good	1	6	80% at MAX <5, dims completely
		aw Adorne Touch	ADTH700MMTUM2	Good	1	6	80% at MAX, dims completely
	Cooper	ax Decorator	DAL06P-C2-K-L	Not Compatible	2	6	Not compatible with 1, dims completely
		ay Skye	SAL06P-W-K-L		1	6	

*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.

*May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating	Description
Not Compatible	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.
Bad	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.
Good	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.
Best	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBA), wide dimming range - can dim down to 20% or less of light output.
High End (HE) Dead Travel Low End (LE) Dead Travel	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.

©2025 Bulbrite Industries Inc.

All Rights Reserved.