

Dimmer Compatibility Guide

Tested Unit Item Number: 776110

Related Item Number: 776107
Related Ordering Code: LED4A19/YLW/FIL/D Tested Unit Ordering Code: LED4A19/PNK/FIL/D Related Item Number: 776105
Related Ordering Code: LED4A19/RED/FIL/D Related Item Number: 776108
Related Ordering Code: LED4A19/GRN/FIL/D Related Item Number: 776106 Related Item Number: 776109

Related Ordering Code: LED4A19/AMB/FIL/D Related Ordering Code: LED4A19/BLU/FIL/D

Related Ordering Code: LED4A19/AMB/11E/B		Related Ordering Code: LED4A19/BEO/112/D						
						Lamps per Dimmer		
	Manufacturer		Product	Model Number	Overall Rating	Recommended	Maximum	Notes
					_	Minimum	Tested*	
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	а	IllumaTech	IPI06	Bad	1	6	Not smooth, flickers heavily while dimming, flickers below MAX, dims completely
			SureSlide	6633-P	Good	1	6	Flickers at MAX with 1, not smooth, slight flicker while dimming, dims completely
			Vizia	VPI06-1LZ	Good	1	6	Not smooth, very slight flicker while dimming, dims completely
	Lutron		Toggler	TG-600	Good	1	6	Not smooth, flickers while dimming, flickers with 1 at low levels, dims to 3%
			Lumea	LGCL-600	Best	1	6	Dims completely
		f	Diva	DV-600	Good	1	6	Not smooth, flickers while dimming, flickers at low levels, dims completely
		g	Skylark	S-600	Good	1	6	Not smooth, flickers while dimming, flickers at low levels, dims completely
		h	Maestro	MAW-600	Not Compatible		6	,
	Legrand	i.	Titan	CD703-PW	Not Compatible	5	6	
		j	Harmony	D703-PTC	Not Compatible	4	6	Not compatible <4, slight flicker when dimming >3, dims completely
			Harmony	H703-PTC	Not Compatible	4	6	Not compatible <4, slight flicker when dimming >3, dims completely
			·	IIPL06	D 1	4		
	Leviton		IllumaTech		Best	1	6	LE dead travel 20%, dims completely
			Sureslide	6674	Best	1	6	LE dead travel 20%, dims completely
			Decora	6672	Good	1	6	Not smooth, VERY slight flicker when dimming, dims completely
	Lutron		Decora Slide	DSL06-1LZ	Best	1	6	Dims completely Dims to 1.5%
			Skylark	CTCL-153	Best	1	6	
CEL /LED		q	Diva	DVCL-153PL MACL-153MLH	Best	1	6	Dims completely
CFL/LED		г	Maestro		Good	1		Not smooth, VERY slight flicker when dimming, dims to <1%
			Skylark	SCL-153P	Best	1	6	Dims to <1%
			Toggler	TGCL-153PH	Best	1	6	Dims to <1%
	Legrand		Radio RA	RA2RR-6CL-PD	Best Bad	1 2	6	Dims completely
			Harmony	DCL453-PTC		2		Not compatible with 1, dims to 2% with 2 or more
			Harmony Adorne Paddle	HCL453PTC	Good Good	1	6	Not smooth, very slight flicker with 1, Dims to <1% Slight flicker at low levels with 1, dims to 4%
		X	Adome Paddie	ADPD453LM2	G000		0	Signt licker at low levels with 1, dims to 4%
Electronic Low Voltage	Leviton		Vizia	VPE04	Bad	1	6	Not compatible at low levels with 3, slight flicker when dimming, dims completely
			IllumaTech	IPE04	Not Compatible		6	
			Decora	6615-P	Not Compatible		6	
	Lutron		Skylark Countour	CTELV-303P	Best	1	6	Dims completely
		ac	Diva	DVELV-300P	Best	1	6	Dims completely
		ad	Maestro	MAELV-600	Best	1	6	Dims completely
			Skylark	SELVB-300P	Best	1	6	Dims completely
			VIERTI	VTEL-600M-W	Best	1	6	Dims completely
	Legrand	ag	Scene Director	SCELV	Bad	1	6	Heavy flicker at high levels with all quantities
	Leviton	ah	Vizia	VPM-06	Bad	2	6	Not compatible with 1, slight flicker while dimming, dims completely
		ai	Decora	6613-P	Good	1	6	Poor operation with 1, slight flicker while dimming, dims completely
Magnetic Low Voltage	Lutron	-1	Maestro	MALV-600	Not Compatible	4	6	r our operation with 1, siight nicker while dimining, dims completely
iviagnetic Low voitage		a)	Harmony	DLV703-PW	Good	4	6	Not smooth, slight flicker while dimming, flicker at low levels, dims completely
	Legrand		Titan	CDLV703-PW	Not Compatible	<u> </u>	6	reor amount, angre mover write ultilling, mover at low levels, diffis completely
		dl	I Itali	IODEV103-FW	Hot Compatible		U	
Smart Dimmer	Leviton	am	Decora Digital (Bluetooth)	DDMX1-BLZ	Best	1	6	Dims completely
	Leviton	an	Decora Smart Z-Wave Technology	DZ6HD	Good	1	6	90% at MAX
	Leviton		Decora Smart WiFi Technology	DW1KD	Best	1	6	Dims completely
	Lutron	_	Caseta Wireless smart dimmer Wi-Fi	PD-10NXD	Good	1	6	90% at MAX, dims to 5%
	Lutron		Caseta Wireless smart dimmer Wi-Fi	PD-6WCL	Best	1	6	Dims to 4%
		_						
	GE	ar	Z WAVE	ZW3005	Good	1	6	Flickers when dimming, dims completely
Universal	Legrand	as	Adorne SofTap	ADTP703TU	Bad	1	6	Dims to 25%
			Miro Decorator	DRD4-W	Bad	1	6	Not compatible with <3, 90% at MAX, flickers while dimming, dims completely
			Harmony	H703PTUTC	Not Compatible		6	
			Adorne Whisper	ADWR700MMTUW2	Bad	1	6	80% at MAX, slight flicker while dimming, dims completely
		aw	Adorne Touch	ADTH700MMTUM2	Best	1	6	Dims completely
	Cooper	ax	Decorator	DAL06P-C2-K-L	Bad	2	6	Not compatible with 1, not smooth, flickers while dimming, dims completely
		av	Skye	SAL06P-W-K-L		1	6	

*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.
†May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating	Description				
Not Compatible	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.				
Bad	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.				
Good	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.				
Best	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBa), wide dimming range - can dim down to 20% or less of light output.				
High End (HE) Dead Travel Low End (LE) Dead Travel	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.				

©2025 Bulbrite Industries Inc.