

## **Dimmer Compatibility Guide**

Tested Unit Item Number: 776998
Tested Unit Ordering Code: LED4G40/30K/FIL/GRAD/BLU
Related Item Number: 776997
Related Ordering Code: LED4G40/30K/FIL/GRAD/SMK

						Lamps per		Notes
	Manufacturer		Product	Model Number	Overall Rating	Recommended	Maximum	
						Minimum	Tested*	
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton		IllumaTech	IPI06	Best	1	6	Slightly not smooth, dims completely
			SureSlide	6633-P	Bad	1	6	Flickers heavily @ MAX with 1, dims completely
			Vizia	VPI06-1LZ	Good	1	6	Flickers heavily at low levels with 1, dims completely
	Lutron		Toggler	TG-600	Best	1	6	Dims to 4%
			Lumea	LGCL-600	Best	1	6	Dims to 1%
			Diva	DV-600	Best	1	6	Dims completely
			Skylark	S-600	Best	1	6	Dims completely
		h	Maestro	MAW-600	Not Compatible		6	
	Legrand	i	Titan	CD703-PW	Good	1	6	Not smooth with 1, dims to 2%
			Harmony	D703-PTC	Bad	2	6	Flickers with 1,dims completely with 2 or more
		k	Harmony	H703-PTC	Good	1	6	Slight flicker with 1, dims completely
			IlliumaTech	IPL06	Best	1	6	Slight delay in operation, dims completely
-	Leviton		Sureslide	6674	Good	1	6	HE dead travel (15%), slight flicker with 1 or 2, slight delay in operation, dims compl
			Decora	6672	Not Compatible		6	The dead dates (1070), single moves with 1 or 2, single deady in operation, differ compr
			Decora Slide	DSL06-1LZ	Good	1	6	Not smooth, dims completely
	Lutron		Skylark	CTCL-153	Bad	1	6	Not compatible with 1, dims to 4%, flickers heavily, dims compl
			Diva	DVCL-153PL	Good	1	6	Not smooth, slight flicker at low levels, dims completely
CFL/LED			Maestro	MACL-153MLH	Best	1	6	Dims to 4%
CILILED			Skylark	SCL-153P	Best	1	6	Dims completely
		-	Toggler	TGCL-153PH	Best	1	6	Dims completely
			Radio RA	RA2RR-6CL-PD	Bad	1	6	Not compatible with 1, dims completely
_	Legrand		Harmony	DCL453-PTC	Best	1	6	Dims completely
			Harmony	HCL453PTC	Good	1	6	80% at MAX with 1, dims completely
			Adorne Paddle	ADPD453LM2	Best	1	6	Dims to 5%
				•		'	_	
	Leviton		Vizia	VPE04	Good	1	6	Not smooth, slight flicker while dimming, dims completely
Electronic Low Voltage			IllumaTech	IPE04	Not Compatible		6	
			Decora	6615-P	Not Compatible		6	
			Skylark Countour	CTELV-303P	Best	1	6	Dims completely
			Diva	DVELV-300P	Best	1	6	Dims completely
			Maestro	MAELV-600	Best	1	6	Dims completely
-			Skylark	SELVB-300P	Best	1	6	Dims completely
			f VIERTI	VTEL-600M-W	Best	1	6	Dims completely
	Legrand	ag	Scene Director	SCELV	Not Compatible		6	
Magnetic Low Voltage	Leviton	at	Vizia	VPM-06	Best	1	6	Dims to 2% with 1, dims completely with 2 or more
			Decora	6613-P	Best	1	6	Dims completely
	Lutron		Maestro	MALV-600	Not Compatible	'	6	Dillis completely
	Lutron			DLV703-PW		4	-	Net
	Legrand		Harmony		Good	1	6	Not smooth with 1, dims completely
		al	Titan	CDLV703-PW	Good	1	6	Not smooth, slight flicker, dims to 1%
Smart Dimmer	Leviton	an	Decora Digital (Bluetooth)	DDMX1-BLZ	Best	1	6	Dims completely
	Leviton		Decora Smart Z-Wave Technology	DZ6HD	Best	1	6	Dims completely
	Leviton		Decora Smart WiFi Technology	DW1KD	Best	1	6	Dims completely
	Lutron		Caseta Wireless smart dimmer Wi-Fi	PD-10NXD	Best	1	6	Dims to 4%
	Lutron	_	Caseta Wireless smart dimmer Wi-Fi	PD-6WCL	Best	1	6	Dims to 4%
	GE	aı	Z WAVE	ZW3005	Good	1	6	Not smooth, slight flicker while dimming, dims completely
	Legrand	00	Adorne SofTap	ADTP703TU	Not Compatible		6	
			Miro Decorator	DRD4-W	Best	1	6	Dims completely
			Harmony	H703PTUTC	Not Compatible		6	Dinis completely
				IIIIOOFIUIC	140. Compatible	1		I .
Universal	Legrand		Adorno Mhionor	A DIM/D ZOOMMATI IM/O	Cood	- 1	l e	000/ at MAX dime completely
Universal	Legrand	av	Adorne Whisper	ADWR700MMTUW2	Good	1	6	90% at MAX, dims completely
Universal	Legrand	av	Adorne Whisper Adorne Touch Decorator	ADWR700MMTUW2 ADTH700MMTUM2 DAL06P-C2-K-L	Good Good Best	1 1 1	6 6 6	90% at MAX, dims completely 90% at MAX, dims completely Dims completely

\*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.
†May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating	Description				
Not Compatible	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.				
Bad	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.				
Good	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.				
Best	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBa), wide dimming range - can dim down to 20% or less of light output.				
High End (HE) Dead Travel Low End (LE) Dead Travel	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.				

©2025 Bulbrite Industries Inc.