

## **Dimmer Compatibility Guide**

Product Family Name: Item Number: 776821

Ordering Code: LED4ST15/27K/FIL/3

Item Number: Ordering Code:

	Manufacturer					Lamps per l	Dimmer	
			Product	Model Number	Overall Rating	Recommended	Maximum	Notes
						Minimum	Tested*	
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)		а	IllumaTech	IPI06	Good	1	6	Not smooth
	Leviton	ь	SureSlide	6633-P	Bad	1	6	Not compatible with 1, raises when dimming
		С	Vizia	VPI06-1LZ	Good	1	6	Not smooth with 1
	Lutron	d	Toggler	TG-600	Best	1	6	
			Lumea	LGCL-600	Best	1	6	
		f	Diva	DV-600	Best	1	6	
		g	Skylark	S-600	Best	1	6	
		h	Maestro	MAW-600	Not Compatible	6	6	Not compatible <6
	Legrand		Titan	CD703-PW	Not Compatible	4	6	Not compatible <4
			Harmony	D703-PTC	Not Compatible	4	6	Not compatible <4
			Harmony	H703-PTC	Bad	1	6	80% MAX w/ 2, 50% MAX w/ 1
		÷						
CFL/LED	Leviton		IllumaTech	IPL06	Good	1	6	Some buzzing, delay in operation, LE dead travel (30%)
			Sureslide	6674	Best	1	6	
			Decora	6672	Best	1	6	
			Decora Slide	DSL06-1LZ	Best	1	6	
			Skylark	CTCL-153	Best	1	6	
			Diva Maestro	DVCL-153PL MACL-153MLH	Best Best	1	6	
	Lutron		Skylark	SCL-153MLH	Best	1	6	Dims to 1%
			Toggler	TGCL-153PH	Best	1	6	Dims to 1%
			Radio RA	RA2RR-6CL-PD	Best	1	6	DITIS TO 176
			Harmony	DCL453-PTC	Good	1	6	Dims to 1%, 80% @ MAX w/ 1
	Legrand		Harmony	HCL453PTC	Good	1	6	80% MAX w/ 1
	Legianu		Adorne Paddle	ADPD453LM2	Best	1	6	Dims to 4%
							-	DIIIIS to 476
	Leviton		Vizia	VPE04	Best	1	6	
			IllumaTech	IPE04	Bad	6	6	Not smooth <6
			Decora	6615-P	Not Compatible	1	6	
Electronic Low Voltage	Lutron		Skylark Countour	CTELV-303P	Best	1	6	
			Diva	DVELV-300P	Best	1	6	
			Maestro	MAELV-600	Best	1	6	
			Skylark	SELVB-300P	Best	1	6	HE dead travel 10%
			VIERTI	VTEL-600M-W	Best	1	6	
	Legrand	ag	Scene Director	SCELV	Best	1	6	Some flicker while adjusting @ MAX, dims to 3%
Magnetic Low Voltage	Leviton Lutron	ah	Vizia	VPM-06	Best	1	6	
			Decora	6613-P	Best	1	6	
			Maestro	MALV-600	Not Compatible		6	
	LULION			DLV703-PW	Bad	1	6	Not compatible <3
	Legrand	ak	Harmony Titan	CDLV703-PW	Bad	1	6	Not compatible <3 Not smooth <3, Inconsistent with 1
		al	Han	ICDEV/03-PW	Bad		В	INOUSHIOUH NO, INCONSISIENT WITH 1
Smart Dimmer	Leviton	am	Decora Digital (Bluetooth)	DDMX1-BLZ	Best	1	6	Some flicker while adjusting @ MAX
	Leviton	an	Decora Smart Z-Wave Technology	DZ6HD	Best	1	6	
	Leviton		Decora Smart WiFi Technology	DW1KD	Best	1	6	
	Lutron		Caseta Wireless smart dimmer Wi-Fi	PD-10NXD	Best	1	6	Dims to 4%
	Lutron		Caseta Wireless smart dimmer Wi-Fi	PD-6WCL	Best	1	6	Dims to 3%
	GE	ar	Z WAVE	ZW3005	Best	1	6	
Universal	Legrand	as	Adorne SofTap	ADTP703TU	Good	1	6	Dims to 7%
			Miro Decorator	DRD4-W	Good	1	6	Not compatible with 2, compatible with all other quantities
			Harmony	H703PTUTC	Not Compatible		6	Tot companies with 2, companies with all other qualities
			Adorne Whisper	ADWR700MMTUW2	Best	1	6	
			Adorne Touch	ADTH700MMTUM2	Best	1	6	
	Cooper		Decorator	DAL06P-C2-K-L	Bad	1	6	Not compatible with 1
			Skye	SAL06P-W-K-L	Duu	1	6	
		l dy	loule	O, 12001 - TT-11-L				·

\*\*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.

\*\*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.

\*\*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.

\*\*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer anunfacturer.

\*\*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.

\*\*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.

\*\*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.

\*\*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.

\*\*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.

\*\*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.

\*\*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.

\*\*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.

\*\*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer manufacturer.

\*\*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer manufacturer.

\*\*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer manufactu

Overall Rating	Description			
Not Compatible	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.			
Bad	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.			
Good	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.			
Best	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBa), wide dimming range - can dim down to 20% or less of light output.			
High End (HE) Dead Travel Low End (LE) Dead Travel	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.			

©2025 Bulbrite Industries Inc.