



Tested Unit Item Number:	776722
Tested Unit Ordering Code:	LED4T8/21K/FIL-NOS/3

	Manufacturer	Product	Model Number	Overall Rating	Lamps per Dimmer		Notes
					Recommended Minimum	Maximum Tested*	
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	a IllumaTech	IPI06	Bad	1	6	Gently strobes at all levels, not smooth while dimming, dims completely
		b SureSlide	6633-P	Bad	2	6	Gently strobes at all levels, flickers heavily when dimmed with 1, dims completely
		c Vizia	VPI06-1LZ	Bad	1	6	Strobes and flickers at most levels, not smooth, dims completely
		d Toggler	TC-600	Bad	1	6	Flickers at low levels, gently strobes at high levels, dims completely
		e Lumea	LGCL-600	Bad	1	6	Flickers at MAX with greater than 1, smooth, dims completely
	Lutron	f Diva	DV-600	Good	1	6	Very slight strobing, dims completely
		g Skylark	S-600	Good	1	6	Slight strobing, dims completely
		h Maestro	MAW-600	Bad	1	6	Strobes and flickers at most levels, flickers heavily <5, not smooth, dims completely
		i Titan	CD703-PW	Not Compatible	1	6	
		j Harmony	D703-PTC	Not Compatible	5	6	
Legrand	k Harmony	H703-PTC	Not Compatible	5	6	Not compatible with <5, slight flickers with 5 or more, dims completely	
CFL/LED	Leviton	l IllumaTech	IPL06	Bad	1	6	Strobing at multiple levels and quantities, delay in operation, dims completely
		m Sureslide	6674	Bad	1	6	Strobing at multiple levels and quantities, delay in operation, dims completely
		n Decora	6672	Good	1	6	Slight strobing at MAX with >2, dims completely
		o Decora Slide	DSL06-1LZ	Bad	1	6	Strobing at multiple levels and quantities, dims completely
		p Skylark	CTCL-153	Best	1	6	Dims completely
	Lutron	q Diva	DVCL-153PL	Good	1	6	Not smooth, dims completely
		r Maestro	MACL-153MLH	Bad	1	6	Strobing at MAX, dims completely
		s Skylark	SCL-153P	Bad	1	6	Strobing at MAX, dims completely
		t Toggler	TGCL-153PH	Good	1	6	Slight flicker at MAX, dims completely
		u Radio RA	RA2RR-6CL-PD	Good	1	6	Slight strobing at MAX, dims completely
	Legrand	v Sunnata Touch	STCL-153M-BL		1	6	
		w Harmony	DCL453-PTC	Good	1	6	Slight strobing at MAX, dims completely
		x Harmony	HCL453PTC	Good	1	6	Slight strobing at MAX, dims completely
		y Adorne Paddle	ADPD453LM2	Good	1	6	Slight strobing at MAX, dims completely
Electronic Low Voltage	Leviton	y Vizia	VPE04	Good	1	6	Flickers heavily WHILE operating, stable when set, dims completely
		z IllumaTech	IEP04	Not Compatible		6	
		aa Decora	6615-P	Not Compatible		6	
	Lutron	ab Skylark Countour	CTELV-303P	Best	1	6	Very slight flutter when operating, dims completely
		ac Diva	DVELV-300P	Best	1	6	Dims completely
		ad Maestro	MAELV-600	Bad	1	6	Slight strobing, dims completely
		ae Skylark	SELVB-300P	Bad	1	6	Strobing, dims completely
		af VIERTI	VTCL-600M-W	Best	1	6	Dims completely
Legrand	ag Scene Director	SCELV	Not Compatible		6		
Magnetic Low Voltage	Leviton	ah Vizia	VPM-06	Not Compatible		6	
	Lutron	ai Decora	6613-P	Bad	1	6	Strobing and flickering at various levels and quantities, dims completely
		aj Maestro	MALV-600	Not Compatible		6	
	Legrand	ak Harmony	DLV703-PW	Bad	2	6	Not compatible with 1, flickers and strobes with 2 or more at various levels, dims completely
		al Titan	CDLV703-PW	Bad	2	6	Not compatible with 1, flickers and strobes with 2 or more at various levels, dims completely
Smart Dimmer	Leviton	am Decora Digital (Bluetooth)	DDMX1-BLZ	Good	1	6	Slight strobing at MAX, dims completely
		an Decora Smart Z-Wave Technology	DZ6HD	Bad	1	6	Strobes and flickers at most levels, not smooth, dims completely
		ao Decora Smart WiFi Technology	DW1KD	Good	1	6	Slight flicker during operation, steady when stable, dims completely
	Lutron	ap Caseta Wireless smart dimmer Wi-Fi	PD-10NXD	Good	1	6	Slight flutter at MAX, dims to 5%
		aq Caseta Wireless smart dimmer Wi-Fi	PD-6WCL	Good	1	6	Slight strobing at MAX with 6, dims completely
	GE	ar Z WAVE	ZW3005	Good	1	6	Slight strobing at MAX, dims to 1%
Eaton	ay Eaton Smart Dimmer		Not Compatible		6		
Universal	Legrand	as Adorne SoTap	ADTP703TU	Bad	1	6	Flicker at all levels, dims to 15%
		at Miro Decorator	DRD4-W	Not Compatible		6	
		au Harmony	H703PTUTC	Not Compatible		6	
	Cooper	av Adorne Whisper	ADWR700MMTUW2	Bad	1	6	Flicker at multiple levels, dims completely
		aw Adorne Touch	ADTH700MMTUM2	Bad	1	6	Flicker at multiple levels, dims completely
		ax Decorator	DAL06P-C2-K-L	Bad	1	6	Slight flicker while dimming, dims completely
	Eaton	az Universal Toggle Dimmer 120V	TUL06P-C2-KB-L	Not Compatible		6	
		ba Universal Slide Dimmer	FSUL06	Not Compatible		6	
		bb Universal Slide Toggle Dimmer	LSO6P	Not Compatible		6	
		bc Universal Slide Toggle Dimmer	LD06P	Not Compatible		6	
		bd Universal Decorator Dimmer	DUL06P-W-2KB-LW	Not Compatible		6	

*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.

†May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating	Description
Not Compatible	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.
Bad	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.
Good	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.
Best	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBA), wide dimming range - can dim down to 20% or less of light output.
High End (HE) Dead Travel Low End (LE) Dead Travel	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.