

Tested Unit Item Number: 776986 Related Item Number: 776967

Related Ordering Code: LED6B11/50K/FIL/M/3
Related Item Number: 776968 Tested Unit Ordering Code: LED6B11/27K/FIL/M/3 Related Item Number: 776988 Related Ordering Code: LED6B11/30K/FIL/M/3
Related Item Number: 776966 Related Ordering Code: LED6B11/40K/FIL/M/3

Related Ordering Code: LED6B11/50K/FIL//3

				Model Number	Overall Rating	Lamps per Dimmer		
	Manufacturer		Product			Recommended	Maximum	Notes
					_	Minimum	Tested*	
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	а	IllumaTech	IPI06	Good	1	6	Not smooth, jumps while dimming
		Ь	SureSlide	6633-P	Best	1	6	Dims completely
		С	Vizia	VPI06-1LZ	Good	1	6	Slight flicker while dimming, dims completely
	Lutron		Toggler	TG-600	Best	1	6	Dims to <1%
			Lumea	LGCL-600	Best	1	6	Dims completely
			Diva	DV-600	Best	1	6	Dims completely
			Skylark	S-600	Best	1	6	Dims completely
			Maestro	MAW-600	Not Compatible	4	6	Not compatible <4
	Legrand		Titan	CD703-PW D703-PTC	Not Compatible Bad	3	6	Not compatible with <3 Not compatible with 2, poor operation with 1, dims completely
			Harmony	H703-PTC	Bad	1	6	85% MAX with 1, dims completely
			<u> </u>				6	
	Leviton		IllumaTech	IPL06	Good	1	6	Delay in operation, dims completely
			Sureslide	6674	Best	1	6	Slight delay in operation, dims completely
			Decora	6672	Best	1	6	Dims completely
			Decora Slide	DSL06-1LZ	Best	1	6	Dims completely
	Lutron		Skylark	CTCL-153	Best	1	6	Dims to less than 1%
			Diva	DVCL-153PL	Good	1	6	Not smooth, slight flicker and jumps during operation, dims to <1%
CFL/LED		г	Maestro	MACL-153MLH	Best	1	6	Dims completely
		s	Skylark	SCL-153P	Best	1	6	Dims completely
			Toggler	TGCL-153PH	Best	1	6	Dims completely
_	Legrand		Radio RA	RA2RR-6CL-PD DCL453-PTC	Best	1	6	Dims completely
			Harmony Harmony	HCL453-PTC	Good Best	1	6	Not smooth, slight flickers during operation, dims completely Dims to <1%
			Adorne Paddle	ADPD453LM2	Best	1	6	Dims to <1%
				•			0	
	Leviton		Vizia	VPE04	Good	1	6	Flickers at low levels while dimming, dims completely
			IllumaTech	IPE04	Not Compatible		6	
Electronic Low Voltage			Decora	6615-P	Not Compatible		6	
	Lutron		Skylark Countour	CTELV-303P	Good	1	6	HE dead travel (20%), dims completely
			Diva Maestro	DVELV-300P MAELV-600	Best Best	1	6	Dims completely Dims completely
			Skylark	SELVB-300P	Best	1	6	HE dead travel (25%), poor operation, dims completely
			VIERTI	VTEL-600M-W	Best	1	6	Dims completely
			Scene Director	SCELV		1	6	
	Legrand	ag	Scene Director	SCELV	Bad	1	ь	Not smooth, HE dead travel (20%), dims to 3%
Magnetic Low Voltage	Leviton	ah	Vizia	VPM-06	Best	1	6	Dims completely
			Decora	6613-P	Best	1	6	Dims completely
	Lutron	aj	Maestro	MALV-600	Not Compatible		6	
	Legrand	ak	Harmony	DLV703-PW	Good	1	6	Not smooth with 1, slight flicker with 1, jumps with 1, dims completely
		al	Titan	CDLV703-PW	Good	1	6	Not smooth with 1, slight jumps with 1, dims completely
	Leviton	10-	Decora Digital (Bluetooth)	DDMX1-BLZ	Best	1	6	Dims completely
Smart Dimmer		_	<u> </u>					
	Leviton		Decora Smart Z-Wave Technology	DZ6HD	Best	1	6	Dims completely
	Leviton	_	Decora Smart WiFi Technology	DW1KD	Best	1	6	Dims completely
	Lutron		Caseta Wireless smart dimmer Wi-Fi	PD-10NXD	Good	1	6	Slight flicker while operating, dims to 4%
	Lutron		Caseta Wireless smart dimmer Wi-Fi	PD-6WCL	Best	1	6	Dims to 4%
	GE	ar	Z WAVE	ZW3005	Good	1	6	Slight flicker at low levels, dims completely
Universal	Legrand	1	Adorne SofTap	ADTP703TU	Not Compatible		6	
			Miro Decorator	DRD4-W	Not Compatible Bad	2	6	Flickers heavily with 1, dims completely
			Harmony	H703PTUTC	Not Compatible		6	I noncis neavily with 1, units completely
			Adorne Whisper	ADWR700MMTUW2	Good	1	6	Slight flicker @ MAX, dims completely
			Adorne Touch	ADTH700MMTUM2	Best	1	6	Dims completely
	Cooper		Decorator	DAL06P-C2-K-L	Not Compatible		6	Dillio completely
			Skye	SAL06P-W-K-L	HOL GOMPAUDIC	1	6	
		l aly	Torkie	JOURTOOL-MA-K-F			L U	l .

*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.
†May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating	Description			
Not Compatible	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.			
Bad	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.			
Good	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.			
Best	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBa), wide dimming range - can dim down to 20% or less of light output.			
High End (HE) Dead Travel Low End (LE) Dead Travel	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.			

©2025 Bulbrite Industries Inc.