



Tested Unit Item Number:		771109	
Tested Unit Ordering Code:		LED6PAR16GUFK40/50/930/J/D/2	
Related Item Number:		771108	
Related Ordering Code:		LED6PAR16GUFK40/50/927/J/D/2	

	Manufacturer	Product	Model Number	Overall Rating	Lamps per Dimmer		Notes	
					Recommended Minimum	Maximum Tested*		
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	a IllumaTech	IPI06	Good		6	Not smooth, flickers while dimming, dims completely	
		b SureSlide	6633-P	Best	1	6	HE dead travel (15%), dims completely	
		c Vizia	VPI06-1LZ	Best	1	6	Dims completely	
	Lutron	d Toggle	TG-600	Best	1	6	Dims completely	
		e Lumea	LGCL-600	Best	1	6	Dims completely	
		f Diva	DV-600	Best	1	6	Dims completely	
		g Skylark	S-600	Best	1	6	Dims completely	
		h Maestro	MAW-600	Not Compatible		6		
	Legrand	i Titan	CD703-PW	Not Compatible		6		
		j Harmony	D703-PTC	Not Compatible		6		
		k Harmony	H703-PTC	Not Compatible		6		
CFL/LED	Leviton	l IllumaTech	IPL06	Good	1	6	Delay in operation, dims completely	
		m Sureslide	6674	Good	1	6	Delay in operation, HE dead travel (40%), dims completely	
		n Decora	6672	Best	1	6	HE dead travel (20%), dims completely	
	Lutron	o Decora Slide	DSL06-1LZ	Bad	1	6	HE dead travel (20%), not smooth, flickers while operating, dims completely	
		p Skylark	CTCL-153	Best	1	6	Dims completely	
		q Diva	DVCL-153PL	Best	1	6	Dims completely	
		r Maestro	MACL-153MLH	Best	1	6	Dims completely	
		s Skylark	SCL-153P	Best	1	6	Dims completely	
		t Toggle	TGCL-153PH	Best	1	6	Dims completely	
		u Radio RA	RA2RR-6CL-PD	Good	1	6	Not smooth, slight flicker while operating, dims completely	
		v Sunnata Touch	STCL-153M-BL		1	6		
		w Harmony	DCL453-PTC	Best	1	6	Dims completely	
	Legrand	x Harmony	HCL453PTC	Best	1	6	Dims completely	
		y Adorne Paddle	ADPD453LM2	Best	1	6	Dims to <1%	
		Electronic Low Voltage	Leviton	y Vizia	VPE04	Best	1	6
	z IllumaTech			IPE04	Bad	1	6	Poor operation, jumps and flickers during operation, dims completely
	aa Decora			6615-P	Good	1	6	Not smooth, flickers during operation, dims to 8%
	Lutron		ab Skylark Countour	CTELV-303P	Best	1	6	Dims completely
ac Diva			DVELV-300P	Best	1	6	Dims completely	
ad Maestro			MAELV-600	Best	1	6	Dims completely	
ae Skylark			SELVB-300P	Best	1	6	Dims completely	
af VIERTI			VTEL-600M-W	Best	1	6	Dims completely	
Legrand	ag Scene Director		SCELV	Best	1	6	Dims completely	
Magnetic Low Voltage	Leviton	ah Vizia	VPM-06	Good	1	6	Poor operation with 1, dims completely	
		ai Decora	6613-P	Best	1	6	Dims completely	
	Lutron	aj Maestro	MALV-600	Not Compatible		6		
		Legrand	ak Harmony	DLV703-PW	Bad	2	6	Not compatible with 1, not smooth with 2, dims completely
al Titan	CDLV703-PW		Bad	1	6	Poor operation with 1, not smooth with 2, dims completely		
Smart Dimmer	Leviton	am Decora Digital (Bluetooth)	DDMX1-BLZ	Best	1	6	Dims completely	
		an Decora Smart Z-Wave Technology	DZ6HD	Best	1	6	Dims completely	
		ao Decora Smart WiFi Technology	DW1KD	Best	1	6	Dims completely	
	Lutron	ap Caseta Wireless smart dimmer Wi-Fi	PD-10NXD	Best	1	6	Dims to 3%	
		aq Caseta Wireless smart dimmer Wi-Fi	PD-6WCL	Best	1	6	Dims to 1%	
	GE	ar Z WAVE	ZW3005	Good	1	6	Not smooth, slight flickers while operating, dims completely	
	Eaton	ay Eaton Smart Dimmer		Best	1	6	Dims completely	
Universal	Legrand	as Adorne SoftTap	ADTP703TU	Not Compatible	3	6	Not compatible with less than 3	
		at Miro Decorator	DRD4-W	Best	1	6	Dims completely	
		au Harmony	H703PTUTC	Not Compatible		6		
		av Adorne Whisper	ADWR700MMTUM2	Best	1	6	Dims completely	
		aw Adorne Touch	ADTH700MMTUM2	Best	1	6	Dims completely	
	Cooper	ax Decorator	DAL06P-C2-K-L	Best	1	6	Dims completely	
		az Universal Toggle Dimmer 120V	TUL06P-C2-KB-L	Good	1	6	Delay in operation, dims to 1%	
	Eaton	ba Universal Slide Dimmer	FSUL06	Good	1	6	Delay in operation, dims to 3%	
		bb Universal Slide Toggle Dimmer	LSO6P	Good	1	6	Delay in operation, dims to 3%	
		bc Universal Slide Toggle Dimmer	LD06P	Good	1	6	Delay in operation, dims to 2%	
		bd Universal Decorator Dimmer	TUL06P-W-2KB-LW	Good	1	6	Delay in operation, dims to 1%	

*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.

†May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating	Description
Not Compatible	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.
Bad	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.
Good	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.
Best	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBA), wide dimming range - can dim down to 20% or less of light output.
High End (HE) Dead Travel	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.
Low End (LE) Dead Travel	

©2025 Bulbrite Industries Inc.
All Rights Reserved.