



<b>Tested Unit Item Number:</b> 776212 <b>Tested Unit Ordering Code:</b> LED7A19/27K/FIL/D/B/2 <b>Related Item Number:</b> 776213 <b>Related Ordering Code:</b> LED7A19/27K/FIL/M/D/B/2 <b>Related Item Number:</b> 776214 <b>Related Ordering Code:</b> LED7A19/30K/FIL/D/B/2	<b>Related Item Number:</b> 776215 <b>Related Ordering Code:</b> LED7A19/30K/FIL/M/D/B/2 <b>Related Item Number:</b> 776216 <b>Related Ordering Code:</b> LED7A19/40K/FIL/D/B/2 <b>Related Item Number:</b> 776226 <b>Related Ordering Code:</b> LED7A19/27K/FIL/D/B/2/4P	<b>Related Item Number:</b> 776227 <b>Related Ordering Code:</b> LED7A19/30K/FIL/D/B/2/4P <b>Related Item Number:</b> 776228 <b>Related Ordering Code:</b> LED7A19/40K/FIL/D/B/2/4P
---	--	--

	Manufacturer	Product	Model Number	Overall Rating	Lamps per Dimmer		Notes
					Recommended Minimum	Maximum Tested*	
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	a IllumaTech	IPI06	Good	1	6	Dims down to 1%, not smooth dimming
		b SureSlide	6633-P	Best	1	6	Dims down to 1%
		c Vizia	VPI06-1LZ	Best	1	6	Dims down to 1%
	Lutron	d Toggler	TG-600	Best	1	6	Dims down to 1%
		e Lumea	LGCL-600	Best	1	6	Dims down to 1%
		f Diva	DV-600	Best	1	6	Dims down to 1%
		g Skylark	S-600	Best	1	6	Dims down to 1%
	Legrand	h Maestro	MAW-600	Not Compatible	1	6	Doesn't turn on with 1-6
		i Titan	CD703-PW	Good	3	6	Dims down to 1%
		j Harmony	D703-PTC	Good	2	6	Dims down to 1%
k Harmony		H703-PTC	Good	2	6	Dims down to 1%	
CFL/LED	Leviton	l IllumaTech	IPL06	Best	1	6	Dims down to 1%
		m Sureslide	6674	Best	1	6	Dims down to 1%
		n Decora	6672	Best	1	6	Dims down to 1%
	Lutron	o Decora Slide	DSL06-1LZ	Best	1	6	Dims down to 1%
		p Skylark	CTCL-153	Best	1	6	Dims down to 1%
		q Diva	DVCL-153PL	Best	1	6	Dims down to 1%
		r Maestro	MACL-153MLH	Best	1	6	Dims down to 1%
		s Skylark	SCL-153P	Best	1	6	Dims down to 1%
		t Toggler	TGCL-153PH	Best	1	6	Dims down to 1%
		u Radio RA	RA2RR-6CL-PD	Best	1	6	Dims down to 1%
	Legrand	v Harmony	DCL453-PTC	Best	1	6	Dims down to 1%
		w Harmony	HCL453PTC	Best	1	6	Dims down to 1%
		x Adorne Paddle	ADPD453LM2	Best	1	6	Dims down to 1%
Electronic Low Voltage	Leviton	y Vizia	VPE04	Best	1	6	Dims down to 1%
		z IllumaTech	IPE04	Good	1	6	Dims down to 1%, not smooth dimming
	Lutron	aa Decora	6615-P	Good	1	6	Dims down to 15%
		ab Skylark Countour	CTELV-303P	Best	1	6	Dims down to 1%
		ac Diva	DVELV-300P	Best	1	6	Dims down to 1%
		ad Maestro	MAELV-600	Best	1	6	Dims down to 1%
		ae Skylark	SELVB-300P	Best	1	6	Dims down to 1%
		af VIERTI	VTEL-600M-W	Best	1	6	Dims down to 1%
		ag Scene Director	SCELV	Best	1	6	Dims down to 2%
Magnetic Low Voltage	Leviton	ah Vizia	VPM-06	Best	1	6	Dims down to 1%
		ai Decora	6613-P	Best	1	6	Dims down to 1%
	Lutron	aj Maestro	MALV-600	Not Compatible	1	6	Doesn't turn on with 1-6
		Legrand	ak Harmony	DLV703-PW	Good	2	6
	al Titan		CDLV703-PW	Good	2	6	Dims down to 1%
Smart Dimmer	Leviton	am Decora Digital (Bluetooth)	DDMX1-BLZ	Best	1	6	Dims down to 1%
		an Decora Smart Z-Wave Technology	DZ6HD	Best	1	6	Dims down to 1%
	Lutron	ao Decora Smart WiFi Technology	DW1KD	Best	1	6	Dims down to 1%
		ap Caseta Wireless smart dimmer Wi-Fi	PD-10NXD	Best	1	6	Dims down to 1%
	GE	aq Caseta Wireless smart dimmer Wi-Fi	PD-6WCL	Best	1	6	Dims down to 1%
		ar Z WAVE	ZW3005	Best	1	6	Dims down to 1%
Universal	Legrand	as Adorne SoftTap	ADTP703TU	Good	1	6	Dims down to 23%
		at Miro Decorator	DRD4-W	Best	1	6	Dims down to 1%
		au Harmony	H703PTUTC	Bad	1	6	Dims down to 30%
		av Adorne Whisper	ADWR700MMTUW2	Best	1	6	Dims down to 1%
	Cooper	aw Adorne Touch	ADTH700MMTUM2	Best	1	6	Dims down to 1%
		ax Decorator	DAL06P-C2-K-L	Best	1	6	Dims down to 1%
		ay Skye	SAL06P-W-K-L	Best	1	6	Dims down to 1%

\*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.  
 †May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating	Description
<b>Not Compatible</b>	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.
<b>Bad</b>	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.
<b>Good</b>	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.
<b>Best</b>	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBA), wide dimming range - can dim down to 20% or less of light output.
<b>High End (HE) Dead Travel</b> <b>Low End (LE) Dead Travel</b>	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.

©2025 Bulbrite Industries Inc.

All Rights Reserved.