



Tested Unit Item Number: 776937							
Tested Unit Ordering Code: LED8A19/27K/FIL/M/4							
Related Item Number: 776958							
Related Ordering Code: LED8A19/50K/FIL/3							
Related Item Number: 776959							
Related Ordering Code: LED8A19/50K/FIL/M/3							
	Manufacturer	Product	Model Number	Overall Rating	Lamps per Dimmer		Notes
					Recommended Minimum	Maximum Tested*	
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	a IllumaTech	IPI06	Good	1	6	Not smooth, slight flicker at multiple points
		b SureSlide	6633-P	Bad	1	6	Heavy flicker @ MAX
		c Vizia	VPI06-1LZ	Good	1	6	Flicker @ MAX, dims completely
	Lutron	d Toggle	TG-600	Good	1	6	Flicker @ MAX, dims completely
		e Lumea	LGCL-600	Best	1	6	Dims completely
		f Diva	DV-600	Best	1	6	Dims completely
		g Skylark	S-600	Best	1	6	Dims completely
		h Maestro	MAW-600	Not Compatible	1	6	
	Legrand	i Titan	CD703-PW	Bad	1	6	Heavy flicker with 1, flicker with 2, flicker @ MAX with >2
		j Harmony	D703-PTC	Good	1	6	Not smooth with 1, dims completely
		k Harmony	H703-PTC	Good	1	6	Not smooth with 1, dims completely
CFL/LED	Leviton	l IllumaTech	IPL06	Bad	1	6	Slight noise when light turns on, delay in operation, flicker @ MAX, dims completely
		m Sureslide	6674	Bad	1	6	Flicker @ MAX, delay in operation dims completely,
		n Decora	6672	Best	1	6	Dims completely
	Lutron	o Decora Slide	DSL06-1LZ	Bad	1	6	Flickers at many levels, dims completely
		p Skylark	CTCL-153	Best	1	6	Dims completely
		q Diva	DVCL-153PL	Best	1	6	Dims completely
		r Maestro	MACL-153MLH	Good	1	6	Slight flicker, dims completely
		s Skylark	SCL-153P	Good	1	6	Slight flicker, not smooth, dims completely
	Legrand	t Toggle	TGCL-153PH	Best	1	6	Dims completely
		u Radio RA	RA2RR-6CL-PD	Good	1	6	Slight flicker @ MAX, dims completely
		v Harmony	DCL453-PTC	Best	1	6	Dims completely
		w Harmony	HCL453PTC	Best	1	6	Dims completely
		x Adorne Paddle	ADPD453LM2	Good	1	6	90% @ MAX with 1, dims to 5%
Electronic Low Voltage	Leviton	y Vizia	VPE04	Good	1	6	Not smooth, slight jumps and flickers while dimming, 95% MAX with 1, dims completely
		z IllumaTech	IPE04	Bad	1	6	Poor operation with 3 or less, not smooth, dims completely
	Lutron	aaa Decora	6615-P	Bad	1	6	HE dead travel, not smooth, jumps up and down, dims to 8%
		abb Skylark Countour	CTELV-303P	Best	1	6	Dims completely
		ac Diva	DVELV-300P	Good	1	6	97% MAX, dims completely
		ad Maestro	MAELV-600	Best	1	6	Dims completely
		ae Skylark	SELVB-300P	Good	1	6	95% MAX with 1, dims completely
		af VIERTI	VTEL-600M-W	Best	1	6	Dims completely
	Legrand	ag Scene Director	SCELV	Good	1	6	Not smooth, slight jumps while operating, slight flicker, dims completely
Magnetic Low Voltage	Leviton	ah Vizia	VPM-06	Good	1	6	Not smooth with 1, jumps, dims completely
		ai Decora	6613-P	Good	1	6	Slight flicker while dimming, dims completely
	Lutron	aj Maestro	MALV-600	Not Compatible	1	6	
		ak Harmony	DLV703-PW	Bad	1	6	Not compatible with 1, dims completely
		al Titan	CDLV703-PW	Good	1	6	Not smooth with 1, jumps, dims completely
Smart Dimmer	Leviton	am Decora Digital (Bluetooth)	DDMX1-BLZ	Best	1	6	Dims completely
	Leviton	an Decora Smart Z-Wave Technology	DZ6HD	Good	1	6	97% MAX, not smooth, dims completely
	Leviton	ao Decora Smart WiFi Technology	DW1KD	Best	1	6	Dims completely
	Lutron	ap Caseta Wireless smart dimmer Wi-Fi	PD-10NXD	Good	1	6	Not smooth, slight flicker while dimming, dims to 6% with 1
	Lutron	aq Caseta Wireless smart dimmer Wi-Fi	PD-6WCL	Good	1	6	Slight flicker while dimming, dims to 3%
	GE	ar Z WAVE	ZW3005	Good	1	6	Not smooth-jumps, slight flicker while dimming, dims completely
Universal	Legrand	as Adorne SoftTap	ADTP703TU	Not Compatible	1	6	
		at Miro Decorator	DRD4-W	Good	1	6	Not smooth, slight flicker when dimming, flicker @ MAX with 1, dims completely
		au Harmony	H703PTUTC	Bad	1	6	Flicker @ MAX, 97% MAX with <6, dims completely
		av Adorne Whisper	ADWR700MMTUW2	Not Compatible	1	6	Dims to 21%
	Cooper	aw Adorne Touch	ADTH700MMTUM2	Best	1	6	Dims completely
		ax Decorator	DAL06P-C2-K-L	Good	1	6	Flicker @ MAX, 95% @ MAX with 1, dims completely
		ay Skye	SAL06P-W-K-L		1	6	

\*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.

\*May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating	Description
<b>Not Compatible</b>	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.
<b>Bad</b>	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.
<b>Good</b>	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.
<b>Best</b>	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBA), wide dimming range - can dim down to 20% or less of light output.
<b>High End (HE) Dead Travel Low End (LE) Dead Travel</b>	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.