

Tested Unit Item Number: 774265 Related Item Number: 774255 Related Item Number: 774258

Tested Unit Ordering Code: LED9A19/PF60W/950/D/2/1P Related Ordering Code: LED9A19/PF60W/940/D/2/4P Related Ordering Code: LED9A19/PF60W/930/D/2/25P

Related Item Number: 774256

Related Item Number: 774253 Related Ordering Code: LED9A19/PF60W/927/D/2/4P Related Ordering Code: LED9A19/PF60W/950/D/2/4P

Related Item Number: 774254

Related Ordering Code: LED9A19/PF60W/930/D/2/4P Related Item Number: 774257
Related Ordering Code: LED9A19/PF60W/927/D/2/25P

Related Ordering Code: LED9A19/PF60W/930/D/2/4P Related Ordering Code: LED9A19/PF60W/927/D/2/25P								
						Lamps per Dimmer		
	Manufacturer		Product	Model Number	Overall Rating	Recommended	Maximum	Notes
						Minimum	Tested*	
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	а	IllumaTech	IPI06	Good	1	6	Not smooth, flickers whil dimming, dims completely
			SureSlide	6633-P	Best	1	6	Dims completely
			Vizia	VPI06-1LZ	Best	1	6	Dims completely
	Lutron		Toggler	TG-600	Best	1	6	Dims completely
			Lumea	LGCL-600	Best	1	6	Dims completely
			Diva	DV-600	Best	1	6	Dims completely
			Skylark	S-600	Best	1	6	Dims completely
			Maestro	MAW-600	Not Compatible		6	
	Legrand		Titan	CD703-PW	Bad	2	6	Not compatible with 1, dims completely
			Harmony	D703-PTC	Bad	1	6	Not compatible with 1, not smooth, jumps, dims completely
		k	Harmony	H703-PTC	Bad	1	6	80% MAX with 1, dims completely
	Leviton	- 1	IllumaTech	IPL06	Best	1	6	Dims completely
		m	Sureslide	6674	Best	1	6	Dims completely
		n	Decora	6672	Best	1	6	Dims to 2%
		0	Decora Slide	DSL06-1LZ	Best	1	6	Dims completely
	Lutron	р	Skylark	CTCL-153	Best	1	6	Dims to 4%
		q	Diva	DVCL-153PL	Best	1	6	Dims to 4%
CFL/LED		r	Maestro	MACL-153MLH	Best	1	6	Dims completely
		s	Skylark	SCL-153P	Best	1	6	Dims completely
		t	Toggler	TGCL-153PH	Best	1	6	Dims completely
		u	Radio RA	RA2RR-6CL-PD	Good	1	6	Not smooth, slight flicker, dims completely
	Legrand	v	Harmony	DCL453-PTC	Best	1	6	Dims to 3%
			Harmony	HCL453PTC	Best	1	6	Dims to 3%
		х	Adorne Paddle	ADPD453LM2	Bad	1	6	Dims to 11%
	Leviton	v	Vizia	VPE04	Good	1	6	Not smooth, jumps, dims completely
			IllumaTech	IPE04	Not Compatible		6	, , , , , , , , , , , , , , , , , , , ,
			Decora	6615-P	Not Compatible		6	
	Lutron	ab	Skylark Countour	CTELV-303P	Good	1	6	HE dead travel (20%), dims completely
Electronic Low Voltage			Diva	DVELV-300P	Best	1	6	Dims completely
		ad	Maestro	MAELV-600	Best	1	6	Dims completely
			Skylark	SELVB-300P	Good	1	6	HE dead travel (20%), dims completely
		af	VIERTI	VTEL-600M-W	Best	1	6	Dims completely
	Legrand	ag	Scene Director	SCELV	Bad	1	6	Flickers @ MAX, dims to 1%
	Leviton			1	Cood	1	6	
Magnetic Low Voltage			Vizia	VPM-06 6613-P	Good	1	6	90% MAX with 1, dims completely
			Decora		Best	2	6	Dims completely
	Lutron		Maestro	MALV-600	Not Compatible	2	6	Not compatible with 1 or 6
	Legrand		Harmony	DLV703-PW	Best	1	6	Dims completely
		al	Titan	CDLV703-PW	Best		6	Dims completely
Smart Dimmer	Leviton	am	Decora Digital (Bluetooth)	DDMX1-BLZ	Best	1	6	Dims completely
	Leviton		Decora Smart Z-Wave Technology	DZ6HD	Good	1	6	Not smooth, jumps while operating, dims completely
	Leviton		Decora Smart WiFi Technology	DW1KD	Best	1	6	Dims completely
	Lutron		Caseta Wireless smart dimmer Wi-Fi	PD-10NXD	Good	1	6	Dims to 10%
						1		
	Lutron		Caseta Wireless smart dimmer Wi-Fi	PD-6WCL	Good	1	6	Dims to 8%
	GE	ar	Z WAVE	ZW3005	Best	1	6	Dims completely
Universal	Legrand	as	Adorne SofTap	ADTP703TU	Bad	1	6	Dims to 12%
		at	Miro Decorator	DRD4-W	Good	1	6	Not smooth, jumps, dims to 6%
			Harmony	H703PTUTC	Not Compatible	1	6	Dims to 35%
			Adorne Whisper	ADWR700MMTUW2	Good	1	6	95% @ MAX, dims completely
		aw	Adorne Touch	ADTH700MMTUM2	Good	1	6	95% @ MAX, dims completely
	Cooper		Decorator	DAL06P-C2-K-L	Best	1	6	Dims completely
		ay	Skye	SAL06P-W-K-L		11	6	

*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.

†May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating	Description					
Not Compatible	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.					
Bad	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.					
	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved vaffecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.					
Best	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBa), wide dimming range - can dim down to 20% or less of light output.					
High End (HE) Dead Travel Low End (LE) Dead Travel	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.					

©2025 Bulbrite Industries Inc.