



Tested Unit Item Number: 773117	
Tested Unit Ordering Code: LED9REC/4//940/WHRD/D	
Related Item Number: 773115	
Related Ordering Code: LED9REC/4//927/WHRD/D	

	Manufacturer	Product	Model Number	Overall Rating	Lamps per Dimmer		Notes
					Recommended Minimum	Maximum Tested*	
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	a IllumaTech	IPI06	Good	1	6	Not smooth, flickers while adjusting, dims to <1%
		b SureSlide	6633-P	Good	1	6	Not smooth, flickers while adjusting, dims completely
		c Vizia	VPI06-1LZ	Good	1	6	LE dead travel (30%), dims completely
	Lutron	d Toggle	TG-600	Good	1	6	LE dead travel (50%), dims completely
		e Lumea	LGCL-600	Good	1	6	LE dead travel (50%), dims completely
		f Diva	DV-600	Good	1	6	LE dead travel (50%), dims completely
		g Skylark	S-600	Good	1	6	LE dead travel (50%), dims completely
	Legrand	h Maestro	MAW-600	Good	1	6	Slight flicker when dimming, dims to 8%
		i Titan	CD703-PW	Good	1	6	Slight flicker in the middle, dims to 5%
		j Harmony	D703-PTC	Good	1	6	LE dead travel (50%), slight flicker while dimming, dims completely
k Harmony	H703-PTC	Good	1	6	LE dead travel (40%), slight flicker/jumps, dims completely		
CFL/LED	Leviton	l IllumaTech	IPL06	Good	1	6	Significant delay in operation, slight flicker when dimming, dims to 4%
		m Sureslide	6674	Good	1	6	Slight delay in operation, dims to <1%
		n Decora	6672	Good	1	6	Not smooth, jumps at LE, dims to 5%
	Lutron	o Decora Slide	DSL06-1LZ	Best	1	6	Very slight flicker while dimming, dims to <1%
		p Skylark	CTCL-153	Bad	1	6	Not smooth, jumps and flicker while dimming, poor operation, dims to 5%
		q Diva	DVCL-153PL	Best	1	6	Dims completely
		r Maestro	MACL-153MLH	Good	1	6	90% MAX, dims to 5%
		s Skylark	SCL-153P	Best	1	6	Dims completely
		t Toggle	TGCL-153PH	Best	1	6	Dims completely
		u Radio RA	RA2RR-6CL-PD	Best	1	6	Dims completely
		v Harmony	DCL453-PTC	Good	1	6	Not smooth, jumps and flickers, dims to 4%
		w Harmony	HCL453PTC	Good	1	6	Not smooth, jumps and flickers, dims to 5%
		x Adorne Paddle	ADPD453LM2	Bad	1	6	Not smooth, jumps and flickers, dims to 12%
	Electronic Low Voltage	Leviton	y Vizia	VP04	Best	1	6
z IllumaTech			IPE04	Not Compatible		6	
aa Decora			6615-P	Not Compatible		6	
Lutron		ab Skylark Countour	CTELV-303P	Best	1	6	Dims to 5%
		ac Diva	DVELV-300P	Good	1	6	Slight flicker while dimming, dims to 4%
		ad Maestro	MAELV-600	Best	1	6	Dims to 3%
		ae Skylark	SELVB-300P	Good	1	6	Slight flicker while dimming, dims to 4%
		af VIERTI	VTEL-600M-W	Best	1	6	Dims to 5%
		ag Scene Director	SCELV	Bad		6	Heavy flicker @ MAX, not smooth, flickers while dimming, dims to 6%
Magnetic Low Voltage	Leviton	ah Vizia	VPM-06	Good	1	6	Dims to 4% with 1, dims completely with 3 or more
		ai Decora	6613-P	Best	1	6	Dims completely
	Lutron	aj Maestro	MALV-600	Not Compatible		6	
		ak Harmony	DLV703-PW	Good	1	6	LE dead travel (35%), not smooth, slight flicker and jumps, dims completely
	al Titan	CDLV703-PW	Good	1	6	LE dead travel (35%), not smooth, slight flicker and jumps, dims to 3.5%	
Smart Dimmer	Leviton	am Decora Digital (Bluetooth)	DDMX1-BLZ	Good	1	6	95% MAX, slight flicker while dimming, dims to 5%
	Leviton	an Decora Smart Z-Wave Technology	DZ6HD	Best	1	6	Dims completely
	Leviton	ao Decora Smart WiFi Technology	DW1KD	Best	1	6	Dims completely
	Lutron	ap Caseta Wireless smart dimmer Wi-Fi	PD-10NXD	Bad		6	Dims to 14%
	Lutron	aq Caseta Wireless smart dimmer Wi-Fi	PD-6WCL	Good	1	6	95% MAX, slight flicker while dimming, dims to 5%
	GE	ar Z WAVE	ZW3005	Best	1	6	Dims completely
Universal	Legrand	as Adorne SofTap	ADTP703TU	Good	1	6	Dims to 8%
		at Miro Decorator	DRD4-W	Best	1	6	Dims completely
		au Harmony	H703PTUC	Not Compatible		6	
		av Adorne Whisper	ADWR700MMTUW2	Good	1	6	Not smooth, very slight flicker while dimming
	Cooper	aw Adorne Touch	ADTH700MMTUM2	Best	1	6	Dims completely
		ax Decorator	DAL06P-C2-K-L	Good	1	6	Not smooth, light flicker while dimming, jumps, dims completely
		ay Skye	SAL06P-W-K-L		1	6	

\*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.

\*May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating	Description
Not Compatible	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.
Bad	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.
Good	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.
Best	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBA), wide dimming range - can dim down to 20% or less of light output.
High End (HE) Dead Travel Low End (LE) Dead Travel	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.

©2025 Bulbrite Industries Inc.

All Rights Reserved.